


应用图示 APPLICATION DIAGRAM

检查·测量 Inspection·measurement

各种工件的计数 Counting various parts

用微小光点光电传感器，金属通过传感器，智能传感器等多种检查方法对各种工件进行计数。
Use Micro photoelectric sensors, proximity sensors, and intelligent sensors to check and count various parts.


利用声波原理对前方透明物体进行监测，并进行数据传输。
Use ultrasonic waves to monitor the transparent objects in front and transmit data.



超声波传感器
Ultrasonic sensor

RU18系列
RU18 Series


适用于自动化流水线，电梯，危险禁区，锻压机，冲剪机床，切纸机等安全检测，起保护作用。
Suitable for security protection for automated assembly line, lift, dangerous restricted area, forging machine, punching machine, paper cutter and other facilities.



超薄型安全光幕
Ultra-thin safety curtain

GM系列
GM Series


用CCD摄像机型智能传感器检查列孔的个数，由于进行的是面监测，即使工件位置有偏移，也能进行检查。
Use a CCD camera-based intelligent sensor to check out the number of holes, as a result of the face detection; even if there is a shift of the position of parts, the check can be done.



智能传感器--(超高速CCD摄像机型)
Intelligent sensor (ultra-high-speed CCD camera-based type)

ZFV系列
ZFV Series

将被测物体放在B点，然后长按设定按钮(约1秒)，等LED灯亮起，即B点设定完成。
A to B point's distance is the sensing distance.
Put the object at point B, then press and hold the set button (1 second). The point B was set when the LED light on. The distance from point B to point A is the sensing distance.



超声波传感器
Ultrasonic sensor


RU18系列
RU18 Series

威卡炉灶节能器具有环保，操作方便，性能稳定，使用寿命长，
连续点燃150万次无故障等优点。节能效果高达40-50%。
Weika stove energy-saving device is environmentally friendly, and easily operational.
It has stable performance and long life and can continuously light up to 1.5 million times
without failure. Energy could be saved by 40-50%.



智能炉灶传感器
Intelligent stove sensor

由于进行的是面监测，即使工件位置有偏移，也能进行检查。
As a result of the face detection, even if there is a shift of the position of parts, the check can be done.



检测有无IC
Check whether is IC

PK3-V03NFV

接近开关 PROXIMITY SWITCH



接近开关 PROXIMITY SWITCH

接近开关型号说明 Model explanation of proximity switch

LM 18 - 30 05 N A □ / L
1 2 3 4 5 6 7 8

开关类别 Switch category

Lm: 电感式 Inductance type
Cm: 电容式 Capacitance type
Sm: 霍尔式 Hall type
Am: 安全防爆式 Safety Explosion-proof type
Xm: 模拟线性式 Mimic Linear type
Hm: 舌簧式 Reed type
Ru: 超声波 Ultrasonic type

外形代号 Outward appearance code

□: 圆柱型 Cylinder type
F□: 角柱型及平面安装型 Angular Column Type And Plane Installation Type


工作电压 Working voltage

30:6-36VDC 310:5-24VDC 320:12-60VDC 330:10-30VDC
340:10-55VDC 350:10-60VDC 360:5-36VDC 20:90-250VAC
210:24-250VAC 220:380VAC 40:12-240VDC/24-240AC
50:特殊电压 Special voltage

检测距离 Detection distance

01:1mm 05:5mm 10:10mm


电感式接近开关工作原理 Working principle inductive proximity switch



电感式接近开关由三大部分组成：振荡器、开关电路及放大输出电路。振荡器产生一个交变磁场。当金属目标接近这一磁场，并达到感应距离时，在金属目标内产生涡流，从而导致振荡器衰减，以至停振。振荡器振荡及停振的变化被后级放大电路处理并转换成开关信号，触发驱动控制器件，从而达到非接触式之检测目的。


目标离传感器越近，线圈内的阻尼就越大，阻尼越大，传感器振荡器的电流越小。

Inductive proximity switch is composed of three parts: oscillator, switch circuit and magnified output circuit. The oscillator will generate an alternating electric field. When metal object approaches this electric field and reaches the induction distance, whirlpool will generate in metal object, resulting in attenuation of vibration and then stop. The change of vibration and stop of oscillator is treated by big stage magnified circuit and converted to switching signal, triggering driving contact detection.




电感式接近开关的电流损耗，随着与金属目标距离的减小而减小。
Current consumption of inductive proximity switch decreases proportional to the metal object distance.


接近开关应用图例 Application illustration of proximity switch




机加工中心的各种位置检测
Various location detection of machinery process center



瓶盖检测
Bottle lid detection



磨床的挡块检测
Stopper detection of grinding machine



机器人手臂位置检测
Arm location detection of robot



检测纸包装内有无牛奶
Inspection of the existing of milk inside the paper package

限位检测
Spacing detection

接近开关 PROXIMITY SWITCH

接近开关的特性 Features of proximity switch

主要特性 Main features






以高频振荡型接近传感器(前面检测器)为代表例，概略说明接近传感器的一般特性。

Take high frequency oscillation type proximity sensor (front detector) as representative example to briefly explain features of proximity switch







项目/Item	说明/Explanation	特性/Features	◆ 关于检测物体 / About detected object												
检测物体的大小和检测距离 the size of detected object and detection distance		<ul style="list-style-type: none"> 检测物体为正方形金属板，厚度恒定($t=1\text{mm}$)，改变其边长$d\text{mm}$时的检测距离X进行测定。If the detected object is square metal sheet with constant thickness($t=1\text{mm}$), detect at detection distance X when change its side length $d\text{mm}$. 根据机种的不同，有时和左边特性不同。 贯通型等，以圆柱状金属棒为检测物体。 当检测物体是大于标准检测物体时，检测距离基本上恒定。但厚度为大于0.01mm左右的箔材料时，会获得和磁性物体相同的检测距离，而镀膜等级其薄时及无导电性时，则不能检测。 镀层的影响检测物体具有镀层时，请注意其检测距离就变了。 	<ul style="list-style-type: none"> 检测物体的材料是非磁性金属时，动作的距离要下降。但厚度为大于0.01mm左右的箔材料时，会获得和磁性物体相同的检测距离，而镀膜等级其薄时及无导电性时，则不能检测。 当检测物体是大于标准检测物体时，检测距离基本上恒定。但厚度为大于0.01mm左右的箔材料时，会获得和磁性物体相同的检测距离，而镀膜等级其薄时及无导电性时，则不能检测。 根据机种的不同，有时和左边特性不同。 贯通型等，以圆柱状金属棒为检测物体。 镀层的影响检测物体具有镀层时，请注意其检测距离就变了。 												
检测物体的厚度和检测距离 the thickness of detected object and detection distance		<ul style="list-style-type: none"> 当检测物体是大于标准检测物体时，检测距离基本上恒定。但厚度为大于0.01mm左右的箔材料时，会获得和磁性物体相同的检测距离，而镀膜等级其薄时及无导电性时，则不能检测。 对于超过1mm厚的磁性金属如铁，厚度在1mm以上时，检测距离基本上没有变化。 对于超过1mm厚的磁性金属如铁，厚度在1mm以上时，检测距离基本上没有变化。 对于超过1mm厚的磁性金属如铁，厚度在1mm以上时，检测距离基本上没有变化。 	<ul style="list-style-type: none"> 当检测物体是大于标准检测物体时，检测距离基本上恒定。但厚度为大于0.01mm左右的箔材料时，会获得和磁性物体相同的检测距离，而镀膜等级其薄时及无导电性时，则不能检测。 对于超过1mm厚的磁性金属如铁，厚度在1mm以上时，检测距离基本上没有变化。 对于超过1mm厚的磁性金属如铁，厚度在1mm以上时，检测距离基本上没有变化。 对于超过1mm厚的磁性金属如铁，厚度在1mm以上时，检测距离基本上没有变化。 												
检测物体材料和镀层等造成的影响 the effects resulted from the thickness of detected object and cladding material	<table border="1"> <thead> <tr> <th>材料</th> <th>检测距离</th> </tr> </thead> <tbody> <tr> <td>铁</td> <td>100%</td> </tr> <tr> <td>不锈钢</td> <td>约60%</td> </tr> <tr> <td>黄铜</td> <td>约40%</td> </tr> <tr> <td>铝</td> <td>约30%</td> </tr> <tr> <td>铜</td> <td>约28%</td> </tr> </tbody> </table>	材料	检测距离	铁	100%	不锈钢	约60%	黄铜	约40%	铝	约30%	铜	约28%	<ul style="list-style-type: none"> 铁以外的金属造成的检测距离及镀层的影响，根据不同的机种而不同。 检测所有金属的机种时，基本上不受镀层的影响。 铁以外的金属造成的检测距离及镀层的影响，根据不同的机种而不同。 检测所有金属的机种时，基本上不受镀层的影响。 	<ul style="list-style-type: none"> 为了使接近传感器长期稳定工作，和一般的控制器一样请实行下列定期检查。 1.被测物体及接近传感器的安装位置，偏移、松动，变形的有无。 2.配线，连接部位有无松动，接触，不良，断线。 3.有无附着金属粉末等积物。 4.使用温度条件，周围环境条件有无异常。 5.检查距离有无异常。
材料	检测距离														
铁	100%														
不锈钢	约60%														
黄铜	约40%														
铝	约30%														
铜	约28%														
			<ul style="list-style-type: none"> 为了使接近传感器长期稳定工作，和一般的控制器一样请实行下列定期检查。 1.被测物体及接近传感器的安装位置，偏移、松动，变形的有无。 2.配线，连接部位有无松动，接触，不良，断线。 3.有无附着金属粉末等积物。 4.使用温度条件，周围环境条件有无异常。 5.检查距离有无异常。 												

接近开关 PROXIMITY SWITCH

技术用词的说明 EXPLANATION OF TECHNICAL TERMS

检测距离 Detection distance	设定距离 Setting distance	标准检测物体 Standard detected object
		
按指定方法移动检测物体，从基准位置(基准面到测定动作复位)的距离 Move the detected object according to assigned method, the distance from the reference position (reference plane) to the detecting action(resetting)	包括温度、电压影响在内，没有误动作从能实用的检测面到检测物体通过位置的距离。 Including the effects like temperature and voltage, without erroraction, the distance passed through from the practical detection surface to the objected object.	为测定基本性能作为标准的检测物体，形状尺寸、材料已决定的 Take as standard detected object to detect the basic performance. The shape, size and material have been determined.
差动距离 Differential distance	响应时间 Response time	响应效率 Response frequency
		
到动作的距离和到复位的距离之差的绝对值。 The absolute value of the distance difference between the distance to action and the distance to resetting	T1: 检测物体进入动作区内，从接近传感器成为动作状态到出现输出的时间。 T2: 从离开动作区到输出消失为止的时间。 T1: When the objected object enters the action zone, the time from proximity sensor being in action state to output appearance. T2: The time from leaving action zone to output disappearance.	反复接近检测物体时，能得出跟踪它的输出每秒次数。测定方法概略如上图。 Work out the tracking output times per second repeatedly approaching the detected object, Brief detection method sees the above diagram.




串联、并联 SERIES CONNECTION AND PARALLEL CONNECTION

★ 三线电流与三线直流传感器的串联 Series connection of three-wire DC and three-wire DC sensor	★ 三线电流与三线直流传感器的并联 Parallel connection of three-wire DC and three-wire DC sensor	★ 两线交流传感的串联 Series connection of two-wire AC sensor
		
◆ 两线交流传感的并联 Parallel connection of two-wire AC sensor	◆ 机械开关与交流传感的串联 Series connection of machinery switch and AC sensor	◆ 机械开关与交流传感的并联 Parallel connection of machinery switch and AC sensor
		



主要特征 Main features

- 体积小 Compact volume
- 重复定位精度高 High precision of repeated location
- 外形结构多样 Diversified exterior structures
- 抗干扰性能好 Good performance of anti-interference
- 输出形式多 Many output forms
- 开关频率高 High on-off frequency
- 电压范围宽 Wide voltage range
- 防尘、防震、防水、防油 Dustproof, vibration proof, water proof and oil proof
- 具备短路保护, 反连接保护 With short-circuit protection and inverted connecting protection
- 使用寿命长 Long service life

正确使用和安装及注意事项 Correct use, installation and cautions

		
<ul style="list-style-type: none"> ● 螺纹式开关的安装 Mounting screw switch ● 安装开关时不可采用过大力矩紧固，紧固时请务必采用齿垫圈 Do not tighten with over-torque when mounting the switch, Adopt toothed washer then tightening 	<ul style="list-style-type: none"> ● 无螺纹式柱型开关的安装 Mounting non screw type pillar switch ● 采用调节螺钉时，紧固力矩请用2-4kgf-cm以下安装 When adopt adjusting screw, the tightening torque should be within 2-4kgf-cm. 	<ul style="list-style-type: none"> ● 防止非检测物体的干扰 Protection against the interference of non detected object ● 在金属上按装接近开关时，请务必参照下图，所示预留一定空间，以避免开关产生误动作 When mounting the proximity switch in the metal part, do refer to the following diagram. Reserve a certain space in advance according to the shown diagram so as to prevent the switch from error action

正确使用和安装及注意事项 Correct use, installation and cautions

		
<ul style="list-style-type: none"> ● 螺纹式开关的安装 Mounting screw switch ● 安装开关时不可采用过大力矩紧固，紧固时请务必采用齿垫圈 Do not tighten with over-torque when mounting the switch, Adopt toothed washer then tightening 	<ul style="list-style-type: none"> ● 开关动作距离(灵敏度)可调节 Adjustable switch actiondistance (sensitivity) ● 接近开关可通过微调电位器调节动作距离(灵敏度)。顺时针动作距离增大(灵敏度减低)，逆时针，切忌在动作距离最大临界状态下使用 The action distance (sensitivity) of proximity switch can be adjusted by the means of trimming potentiometer, increase the action distance and reduce sensitivity when turnclockwise, vice versa. Do not use in the critical state of max. Action distance. 	<ul style="list-style-type: none"> ● 开关引线的防护 Guard of switch lead-wire ● 按装开关时，请将离开开关10cm左右引线位置用线夹固定，防止开关引线受外力的作用损坏。 When mount switch, fix the lead-wire at a distance apit 10cm from the switch with wire clip so as to prevent the switch lead wire from damage from outer force.

注意事项 Cautions





- 直流开关应使用绝缘变压器，并确保稳压电源纹波。
- 如有电力线动力线通过开关引线周围时，防止开关损坏或误动作，将金属管套在开关引线上并接地。
- 开关使用距离请设定在额定距离以内，以免受温度和电压影响。
- 严禁通电接线，应严格按照接线图输出回路原理图接线。
- 用户如需要防水、防油、耐酸、碱、耐高温开关等特殊要求或其他规格应在订货时说明，并给予定做。
- Dc switch should adopt insulation transformer and ensure stable voltage mains corrugation.
- If any electric power line or dynamic line passes through the surrounding of switch lead-wire, in order to prevent the switch from damage or error action, cover the metal bushing on the switch lead-wire and ground it to the earth.
- Set the switch use distance within the rated distance to avoid the effects from temperature and voltage.
- Wiring while power-on is strictly prohibited. connecting the wires strictly according to the wiring diagram and output return elementary diagram.
- If there are any special requirements to the switch like water proof, oil proof, acid proof, base proof, high temperature proof of with any other specifications, the users are required to give clear indication when placing an order. we can produce according to the requirements of the user.






接近开关 PROXIMITY SWITCH

结构分类 Structural category		圆柱型 Cylinder type	接插件型 Connector type		
外形编号 Outward Appearance code		LM8-□□T / LM8-□□T3	LM12-□T / LM12-□T3	LM18-□T	
外形图例	Outward appearance illustration				
外形尺寸	Overall dimensions				
检测距离 DETECTION DISTANCE		1mm	2mm	5mm	
埋入式 Flush	NPN DC 10-30 VDC	NO	LM8-3001NAT	LM12-3002NAT	LM18-3005NAT
		NC	LM8-3001NBT	LM12-3002NBT	LM18-3005NBT
		NO+NC		LM12-3002NCT	LM18-3005NCT
		NO	LM8-3001PAT	LM12-3002PAT	LM18-3005PAT
		NC	LM8-3001PBT	LM12-3002PBT	LM18-3005PBT
	PNP AC 90-250 VAC	NO+NC		LM12-3002PCT	LM18-3005PCT
		NO	LM8-3001LAT	LM12-3002LAT	LM18-3005LAT
		NC	LM8-3001LBT	LM12-3002LBT	LM18-3005LBT
		NO		LM12-2002AT	LM18-2005AT
		NC		LM12-2002BT	LM18-2005BT
继电器输出 Relay output					
非埋入式 Non-Flush	NPN DC 10-30 VDC	检测距离 DETECTION DISTANCE	2mm	4mm	
		NO	LM8-3002NAT	LM12-3004NAT	LM18-3008NAT
		NC	LM8-3002NBT	LM12-3004NBT	LM18-3008NBT
		NO+NC		LM12-3004NCT	LM18-3008NCT
		NO	LM8-3002PAT	LM12-3004PAT	LM18-3008PAT
		NC	LM8-3002PBT	LM12-3004PBT	LM18-3008PBT
	PNP AC 90-250 VAC	NO+NC		LM12-3004PCT	LM18-3008PCT
		NO	LM8-3002LAT	LM12-3004LAT	LM18-3008LAT
		NC	LM8-3002LBT	LM12-3004LBT	LM18-3008LBT
		NO	LM8-2002AT	LM12-2004AT	LM18-2008AT
		NC		LM12-2004BT	LM18-2008BT
继电器输出 Relay output					
输出电流 Control output		DC	150mA	200mA	
		SCR/继电器 Relay		300mA	
输出电压降 Output voltage drop DC/AC		直流(NPN PNP)型3V以下、二线型:3.9V以下、交流AC 10V以下 DC<3V、AC<10V			
消耗电流 Consumption current		直流(NPN PNP)型DC 12V时8mA、24V时15mA、交流AC 10mA以下 DC<15mA、AC<10mA			
标准检测物体 Standard detected object		8×8×1(A3铁iron)	12×12×1(A3铁iron)	18×18×1(A3铁iron)	
重复精度 Repeated precision		0.01	0.01	0.02	
响应频率 DC/AC		500Hz/10Hz	400Hz/10Hz	200Hz/10Hz	
工作环境温度 Working environment temperature		-25°C~+70°C	-25°C~+70°C	-25°C~+70°C	
绝缘电阻 Insulation resistance		50MΩ	50MΩ	50MΩ	
外壳材料 Shell material		金属 Metal	金属 Metal	金属 Metal	
防护等级 Protection grade		IP67	IP67	IP67	
可替代国内型号 Alyematic model at home and abroad		E2E-X1R5-M1	E2E-X2E1-M1	E2E-X5E5-M1	

结构分类 Structural category		圆柱型 Cylinder type					
外形编号 Outward Appearance code		LM4/LM5	LM6	LM06	LM8		
外形图例	Outward appearance illustration						
外形尺寸	Overall dimensions						
检测距离 DETECTION DISTANCE		0.8mm/1mm	1mm	1mm	1mm		
埋入式 Flush	NPN DC 10-30 VDC	NO	LM4-300.8NA/LM5-3001NA	LM6-3001NA	LM06-3001NA	LM8-3001NA	
		NC		LM6-3001NB		LM8-3001NB	
		NO+NC				LM8-3001NC	
		NO	LM4-300.8PA/LM5-3001PA	LM6-3001PA	LM06-3001PA	LM8-3001PA	
		NC		LM6-3001PB		LM8-3001PB	
	PNP AC 90-250 VAC	NO+NC				LM8-3001PC	
		NO		LM6-3001LA		LM8-3001LA	
		NC		LM6-3001LB		LM8-2001LB	
		NO		LM6-2001A		LM8-2001A	
		NC		LM6-2001B		LM8-2001B	
继电器输出 Relay output							
非埋入式 Non-Flush	NPN DC 10-30 VDC	检测距离 DETECTION DISTANCE	1.5mm	2mm			
		NO		LM6-3002NA		LM8-3002NA	
		NC		LM6-3002NB		LM8-3002NB	
		NO+NC					
		NO		LM6-3002PA		LM8-3002PA	
	PNP AC 90-250 VAC	NC		LM6-3002PB		LM8-3002PB	
		NO+NC					
		NO		LM6-3002LA		LM8-3002LA	
		NC		LM6-3002LB		LM8-3002LB	
		NO		LM6-2002A		LM8-2002A	
		NC		LM6-2002B		LM8-2002B	
继电器输出 Relay output							
输出电流 Control output	DC	输出电流 Control output	200mA	200mA	200mA	200mA	
		SCR/继电器 Relay					
		输出电压降 Output voltage drop DC/AC	直流(NPN PNP)型3V以下、二线型:3.9V以下、交流AC 10V以下 DC<3V、AC<10V				
		消耗电流 Consumption current	直流(NPN PNP)型DC 12V时8mA、24V时15mA、交流AC 10mA以下 DC<15mA、AC<10mA				
		标准检测物体 Standard detected object	6×6×1(A3铁iron)	8×8×1(A3铁iron)	8×8×1(A3铁iron)	8×8×1(A3铁iron)	
	SCR/继电器 Relay	重复精度 Repeated precision	0.01	0.01	0.01	0.01	
		响应频率 DC/AC	500Hz	500Hz	500Hz	500Hz/25Hz	
		工作环境温度 Workong environment temperature	-25°C~+70°C	-25°C~+75°C	-25°C~+70°C	-25°C~+75°C	
		绝缘电阻 Insulation resistance	50MΩ	≥30MΩ	50MΩ	≥50MΩ	
		外壳材料 Shell material	金属 Metal	不锈钢 Stainless steel	金属 Metal	金属 Metal	
防护等级 Protection grade		IP67	IP67	IP67	IP67	IP67	
可替代国内型号 Alyematic model at home and abroad		E2E-X1R5-M1			E2E-X1R5-□□		

接近开关 PROXIMITY SWITCH

结构分类 Structural category		圆柱型 Cylinder type			
外形编号 Outward Appearance code		LM12	LM14	LM18	LM20
外形图例 Outward appearance illustration					
外形尺寸 Overall dimensions					
检测距离 DETECTION DISTANCE		2mm	3mm	5mm	
埋入式 Flush	NPN DC 10-30 VDC	NO LM12-3002NA	LM14-3003NA	LM18-3005NA	
	NC LM12-3002NB	LM14-3003NB	LM18-3005NB		
	NO+NC LM12-3002NC	LM14-3003NC	LM18-3005NC		
	NO LM12-3002PA	LM14-3003PA	LM18-3005PA		
	NC LM12-3002PB	LM14-3003PB	LM18-3005PB		
	NO+NC LM12-3002PC	LM14-3003PC	LM18-3005PC		
	NO LM12-3002LA	LM14-3003LA	LM18-3005LA		
	NC LM12-2002LB	LM14-2003LB	LM18-3005LB		
	NO LM12-2002A	LM14-2003A	LM18-2005A		
	NC LM12-2002B	LM14-2003B	LM18-2005B		
非埋入式 Non-Flush	NO+NC LM12-2005C		LM18-2005C		
	继电器输出 Relay output				
检测距离 DETECTION DISTANCE		4mm	5mm	8mm	10mm
NPN DC 10-30 VDC	NO LM12-3004NA	LM14-3005NA	LM18-3008NA	LM20-3010NA	
NC LM12-3004NB	LM14-3005NB	LM18-3008NB	LM20-3010NB		
NO+NC LM12-3004NC	LM14-3005NC	LM18-3008NC	LM20-3010NC		
NO LM12-3004PA	LM14-3005PA	LM18-3008PA	LM20-3010PA		
NC LM12-3004PB	LM14-3005PB	LM18-3008PB	LM20-3010PB		
NO+NC LM12-3004PC	LM14-3005PC	LM18-3008PC	LM20-3010PC		
NO LM12-3004LA	LM14-3005LA	LM18-3008LA	LM20-3010LA		
NC LM12-3004LB	LM14-3005LB	LM18-2008LB	LM20-3010LB		
NO LM12-2004A	LM14-2005A	LM18-2008A	LM20-2010A		
NC LM12-2004B	LM14-2005B	LM18-2008B	LM20-2010B		
NO+NC LM12-2008C			LM20-2010C		
继电器输出 Relay output					
输出电流 Control output		DC 200mA	200mA	200mA	200mA
SCR/继电器 Relay		300mA	300mA	300mA	300mA/1A
输出电压降 Output voltage drop DC/AC					
直流(NPN PNP)型3V以下、二线型:3.9V以下、交流AC 10V以下 DC<3V、AC<10V					
消耗电流 Consumption current					
直流(NPN PNP)型DC 12V时8mA、24V时15mA、交流AC 10mA以下 DC<15mA、AC<10mA					
标准检测物体 Standard detected object		15×15×1(A3铁iron)	15×15×1(A3铁iron)	18×18×1(A3铁iron)	20×20×1(A3铁iron)
重复精度 Repeated precision		0.01	0.02	0.02	0.05
响应频率 DC/AC		400Hz/25Hz	300Hz/25Hz	200Hz/25Hz	200Hz/25Hz
工作环境温度 Working environment temperature		-25°C~+75°C	-25°C~+75°C	-25°C~+75°C	-25°C~+75°C
绝缘电阻 Insulation resistance		≥50MΩ	≥50MΩ	50MΩ	50MΩ
外壳材料 Shell material		金属 Metal	金属 Metal	金属 Metal	ABS树脂 Resin
防护等级 Protection grade		IP67	IP67	IP67	IP67
可替代国内型号 Alyematic model at home and abroad		E2E-X5□□	LJ14A3-□□	LJ18A3-8-□□	

接近开关 PROXIMITY SWITCH				
圆柱型 Cylinder type				
LM24	LM30	LM34	LM35	LM38
				
				
8mm	10mm	12mm		
LM24-3008NA	LM30-3010NA			LM38-3012NA
LM24-3008NB	LM30-3010NB			LM38-3012NB
LM24-3008NC	LM30-3010NC			LM38-3012NC
LM24-3008PA	LM30-3010PA			LM38-3012PA
LM24-3008PB	LM30-3010PB			LM38-3012PB
LM24-3008PC	LM30-3010PC			LM38-3012PC
LM24-3008LA	LM30-3010LA			LM38-3012LA
LM24-3008LB	LM30-3010LB			LM38-3012LB
LM24-2008A	LM30-2010A			LM38-2012A
LM24-2008B	LM30-2010B			LM38-2012B
LM24-2008C	LM30-2010C			LM38-2012C
LM30-2010JC				
10mm	15mm	17mm	17mm	18mm
LM24-3010NA	LM30-3015NA	LM34-3017NA	LM35-3017NA	LM38-3018NA
LM24-3010NB	LM30-3015NB	LM34-3017NB	LM35-3017NB	LM38-3018NB
LM24-3010NC	LM30-3015NC	LM34-3017NC	LM35-3017NC	LM38-3018NC
LM24-3010PA	LM30-3015PA	LM34-3017PA	LM35-3017PA	LM38-3018PA
LM24-3010PB	LM30-3015PB	LM34-3017PB	LM35-3017PB	LM38-3018PB
LM24-3010PC	LM30-3015PC	LM34-3017PC	LM35-3017PC	LM38-3018PC
LM24-3010LA	LM30-3015LA	LM34-3017LA	LM35-3017LA	LM38-3018LA
LM24-3010LB	LM30-3015LB	LM34-3017LB	LM35-3017LB	LM38-3018LB
LM24-2010A	LM30-2015A	LM34-2017A	LM35-2017A	LM38-2018A
LM24-2010B	LM30-2015B	LM34-2017B	LM35-2017B	LM38-2018B
LM24-2010C	LM30-2015C	LM34-2017C	LM35-2017C	LM38-2018C
LM30-2015JC	LM34-2017JC	LM35-2017JC	LM38-2018JC	
200mA	200mA	200mA	200mA	200mA
300mA	300mA/1A			
直流(NPN PNP)型3V以下、二线型:3.9V以下、交流AC 10V以下 DC<3V、AC<10V				
直流(NPN PNP)型DC 12V时8mA、24V时15mA、交流AC 10mA以下 DC<15mA、AC<10mA				
24×24×1(A3铁iron)	30×30×1(A3铁iron)	34×34×1(A3铁iron)	40×40×1(A3铁iron)	40×40×1(A3铁iron)
0.05	0.05		0.1	
200Hz/25Hz	200Hz/25Hz		100Hz/15Hz	
-25°C~+75°C	-25°C~+75°C		-25°C~+75°C	
50MΩ	50MΩ		50MΩ	
金属 Metal	金属 Metal	ABS树脂 Resin	ABS树脂 Resin	ABS树脂 Resin
IP67	IP67		IP67	
LJ24A3-10-□□	E2E-X18M□			LJ38A4-18-□□