

# LogiLink®

## Emergency Hand Crank Radio with LED Flashlight

Art. No.: SP0061



## The Must-Have Emergency Kit

When trapped in natural disasters such as earthquakes, snowstorms, hurricanes with no electricity; go camping/hiking with no lights at night; or when car broke down on the highway with a dead phone battery. The portable multifunctional Emergency Hand Crank Radio is your best tool, always be prepared.



## Multifunctional

4 Modes: Radio/Flashlight/  
SOS/USB device charger.

## FM/AM/SW1/SW2 Radio

Tune to all your local radio  
stations with a long range  
antenna.



## 2 LED Light Modes

Bright flashlight and  
SOS mode.

## Portable Size

Lightweight, easy to carry  
and store.

## Never Power Off with Multiple Power Sources

Built-in rechargeable battery can be recharged by solar panel, hand  
crank, through USB port, or power with 3 AAA batteries.



Solar power



Hand crank



USB charging



3 AAA batteries



### Up-To-Date Weather Report

Hear the latest information in your area and be well-prepared.



### Emergency SOS Alarm

Call for help with loud siren and SOS light in any catastrophic situation.



### Integrated Power Bank

Keep your USB device/smartphone powered in an emergency.

## Specifications:

|                           |   |
|---------------------------|---|
| Frequency Band            | FM: 87–108 MHz<br>AM: 520–1710 kHz<br>SW1: 5.8–10.0 MHz<br>SW2: 11.6–18.2 MHz   |
| Battery Capacity          | 1200 mAh  |
| Power By                  | 3.7 V lithium polymer battery or 3x AAA battery   |
| Input Power               | Micro-B: 5 V/0.3 A (1.5 W)<br>Solar panel: 5 V/0.035 A (0.175 W)<br>Hand crank generator: 5 V/0.4 A (2 W)               |
| Output Power              | USB-A: 5 V/0.4 A (2 W)  |
| LED Indicator             | Red LED for Power; Green LED for charging   |
| Controls                  | Radio On/Off and volume knob, AM/FM/SW1/SW2 switch, radio channel tuning dial, phone charger/radio/LED light/SOS switch |
| Protections               | Over charge and discharge   |
| Audio Jack                | TS (single channel)   |
| SNR                       | 50 dB   |
| RMS                       | 1 W   |
| Loudspeaker Diameter      | 50 mm   |
| Loudspeaker Sensitivity   | 85 dB/W/m $\pm$ 3 dB  |
| Loudspeaker Impedance     | 8 $\Omega$  |
| Frequency Response        | 145 Hz – 20 kHz   |
| Frequency Range           | 45 Hz – 20 kHz  |
| Standby Power Consumption | 0.0005 W  |
| Flashlight Modes          | Steady, strobe (SOS mode)   |
| Operating Temperature     | 10–50°C   |
| Operating Humidity        | 10–90% RH (no condensation)   |
| Housing Material          | ABS   |
| Color                     | Black   |
| Dimensions                | 13.8 x 6.9 x 4.85 cm  |
| Weight                    | 227 g   |
| Cable Length              | 45 cm   |

## Package Contents:

- » 1x Multifunctional Radio
- » 1x USB-A to Micro-B Charging Cable
- » 1x User Manual

## Package Information:

- » Packing Dimension: mm
- » Packing Weight: kg
- » Carton Dimension: mm
- » Carton Q'ty: pcs
- » Carton Weight: kg



\*The specifications and pictures are subject to change without prior notice.  
\*All trade names referenced are the registered trademarks of their respective owners.



SP0061



4 052792 069655

Made in China