


Scimagic Auto Scan RF Multi Frequency Universal Remote Control Duplicator

Best position for duplication



Feature

Auto scan type

Multi frequency 280-868mhz
Duplicate rolling code and fixed code
Up to 4 different remotes in 1

Programming

A) Standard

- 1.Press and hold button 1 and press button 2 four times at same time
2. Release 2 buttons till LED flashed once every three seconds
3. Put original remote in the front of new remote (about 2-3cm), press the original remote button which need to be copied until the LED of new remote flash quickly (LED have regular flashes)
4. Press the button of New remote that you want to use to save the code
5. If you do not copy successfully, please repeat above steps
6. To duplicate a second button, repeat the above steps

B) Automatic matching code

After copy successfully, don't use any remote first, then put the new remote close to the receiver to active it, press and hold the button until the led of it flash quickly, then you can try it

Emitting seed code

Pressing the button 1 and button 2 at the same time until LED flashes quickly.
Release 2 buttons,press the button that you want to emit seed code, it has emitted seed code successfully

AMC: Automatic Matching Code

BFT

- 1) Press and hold button 1 and press button 2 four times at same time,Release 2 buttons till LED flashed once every three seconds
- 2) Put original remote in the front of new remote (about 2-3cm), press and hold the original remote button which need to be copied until the LED will turn on with a fixed light and then emits a double flash very 2 seconds
- 3) Pressing the hidden button or the button 1 and 2 simultaneously in the new models (transmit the seed code of original BFT remote)
- 4) Now the led will flash quickly,press the new remote button that you want to save the code, the LED will off
- 5) Now active the remote with AMC procedure

FAAC and GENIUS

Note: your original remote control must be in a master version
How to recognise a master/slave transmitter:

master: if you press any key of a master transmitter, the LED flashes before becoming steady.

slave: if you press any key of a slave transmitter, the LED goes on immediately with steady light

- 1) Press and hold button 1 and press button 2 four times at same time,Release 2 buttons till LED flashed once every three seconds
- 2) Put original remote in the front of new remote (about 2-3cm), press and hold the original remote button which need to be copied until the LED will turn on with a fixed light and then emits a double flash very 2 seconds
- 3) Pressing and hold the button 2 and 3 simultaneously of original FAAC/GENIUS to transmit the seed code
- 4)While the led of FAAC and GENIUS is flashing, put it close to new remote about 2-3cm, and press the button that you want to copy until the LED will change the frequency of flash(faster than before to confirm the correct copy the code)

V2

- 1) Press and hold button 1 and press button 2 four times at same time,Release 2 buttons till LED flashed once every three seconds
- 2) Put original remote in the front of new remote (about 2-3cm), press and hold the original remote button which need to be copied until the LED will turn on with a fixed light and then emits a double flash very 2 seconds
- 3) Press and hold once again the same button of original remote, the LED of new remote will flashes quickly, press the button that you want to save the code, until the LED off
- 4) Now active the remote with AMC procedure

Compatible List

Brand	Model	Brand	Model
ACM (AMC)	TX2, TX2 COLOR, TX4	KEY	900TXB-42R,SUB44,TXB-44R,TXG-44R
ADYX	TE4433H BLUE, 433-HG BRAVO	KINGGATES	STYLO,CLIPPER
AERF	COMPACT HY-DOM, MERCURY B, MERCURY C, SABUTON, MARS,SATURA, ST3/N, TERBA, TMP-1,TMP-2, UNITECH	KLING	KUA,KUAE,KUA S
ALLMATIC (AMC)	BROWN, BROWN RED, BRO.OVER, PASS, MINIFASS	LABEL	SPYCO, RAW4E
APERIO	GO, GO PRO, GO MINI	LEB	TMW
APERTO (SOMMER)	TX02-434-2, TX02-868-2 BLUE, 4025 TX02-868-2, 4022 TX02-434-2, 4020 TX03-434, TX-03-868-4, 4013, TX03-434-4	LINCE	JR2035
APRIMATIC (AMC)	TR2/TR4, TM4, TXM	LIFE	LIFE FID02 / FID04 / VIP2 / VIP4 / VIP2R / VIP4R / STAR2 / STARR / BRAVO2 / BRAVO4
ATA	PTX4 BLUEM PTX4 PINK	LINEAR	MCT-11,ACT-23,ACT-21,STING RAY ACT-31,STING RAY ACT-34B
AVIDSEN	104251, 104250, 104250 OLD, 104250 RED, 104257, 104350, 654250	MHOUSE (AMC)	GTx6, GTx4C, TX4
		MA	TX1,TX2,TX3
		MOOVO (AMC)	MT4G

BALLAN	FM400, FM400E, FM404B, 4013	MARANTEC	D101,D12,DIGITAL302,DIGITAL304
BENINCA (AMC)	TO GO,WIV, TWV, ROLLKEY,APPLE, LOT WCV, CLIPIDO,TO GO QV, IQ, LOT2WCV,LOT1W, LOT2W, LOT4W, LOT1WM, LOT2WM,T2W, T4W	MERLIN/PROLIFT	M230T(PROLIFT),M430R(PROLIFT)
BESIDE	BEZAP, HIT	MERLIN 2.0	E945M,E943M,E940M
BFT (AMC)	MITTO, MITTO M(MITTO 2M/MITTO4M), MITTO RCB(MITTO RCB02/MITTO RCB04), MITTOA(MITTO 2A/MITTO 4A), MITTO B(TX02/TX4C), GHIBLI, MURALE, KLEIO, TEO1, TEO2,TE04, RB4 MURALE	MONSIEGNEUR	ARC
CAME	T431, T434, TOP432A, TOP434a, TOP432, TAM4325A, TOP4323NA	NORTON	NEO,TKCD,GO NORTON,GO MINI NORTON
CARDIN (AMC)	TRQ 5449 (TRQ449100/TRQ449200/TRQ449300/TRQ449400), TRQ 5449 GREEN(RECODE), TXQ 5449(TXQ449200/TXQ449300/TXQ449400), TXQ 5449 GREEN, TRQ 5486(TRQ486200/TRQ486400), TXQ 5486(TXQ486200/TXQ 486200/TXQ486400), S437 TX, XRAD0, S449, S476TX2, S476TX, S486	NOVOTECNICA (AMC)	BLXL2
CASALI	JA33 AMIGO, GENIUS/CASALI A.252RC	NOVOFERM	NOVOTRON 502-504-512MX43-2,MTX40-2,MCH543-2,MH543(2-4),MNH5433(2-4),MCH5, MINI-NOVOTRON504,MICRO-NOVOTRON 502
CASIT	ERTS92B, ERTS92T, ERTS476D, ERTS20DQ, ERTS476D, ERTS476Q	NOLOGO	ECO DIP
CELISA	S10 1, S10 2	O&O (AMC)	T.BOM,TWIN,TX, TWIN,TX2,TX4
CENTURION	CLASSIC, SMART	O&G	DG62,DG64
CHAMBERLIN/ LIFTMASTER/ MOTORLIFT	953ESTD, 371LM,315MHZ), 81LM,371LM(390MHZ),84330E,94334CE, 94333E/94334E/94335E, 9747E, 1A5477, 1A6487, 1328372, 94335EM/94333EM/94335EM, 84330EM/84333EM/84335EM, 8747EML	OPENOUT	TMQ
CLEMSA	MUTANCODE, T, T-8, E-CODE N, MASTERCODE MV	PECCININ	TX MENBRANA
CPS	TCP3, CPS1, CPS2, CPS4	PORTAMATIC	MPH01,MPH02
DASPI (AMC)	HAPPY2, POPS 2, ZERO RC(ZERO 2RC, 4RC)	PRASEL	TC2E(BE),SLIM,BFOT,MPSTP2E,MPSTF2,MPSTF4,MPSTF2RE,MPSTF4RE,MPSTP2E,MPSTP2EB, UE
DEA	TR MID, 133 1, 433 2, GENIE, PUNTO S2, PUNTO 278, GOLDR, GENIE R 273, GENE R-GT2N	PROEM	ER4CACCS
DELMA	MIXARD 433 1, MIXARD 433 2, KING 433 2	PROGET	ETY_432N2,ETY_432N4
DICKERT	MAH5433 01, MAH5433 04	PROTECO	TX433,EUROMATIC
DITEC (AMC)	GOL, GOL4C, BIXLS2, BIXLP2, BIXAG4, BIXLG	PUOOL	MARTE,P215,TWIN,VARIO,VARIO MARS, VARIOOCEAN,NEO
DOORMATIC	SAW	QUASAR	433
DOITRAND	MPSTF2E, JAUNE	RIB	LITHILO
DOORHAN	TRANSMITTER 4	ROPER	NEO,GO ROPER,GO MINI ROPER
DUICATI	TSAW1, TSAW2, TSAW3, 124, TE2	SABUTOM	BROOVER,BROSTAR
ECOSTAR	RSE,RSC,R5Z	SEA	SMART DIP
ELBE	S01, S02, S04, S02A, S04A	SECUX	NEO
ERREKA	IRS, ROLLER 2, ROLLER 433, ROLLER 868, SOL433, SOL868, VEGA 433, VEGA 868	SILVELOX	MH2 2007, QUARZ SAW
ELCA	IRS, ASTER,ASTER 1000,ASTER 1001	SICE	4790207
FALCA (AMC)	XT 433 RC, TM1 433 DS,TM2 433 DS, TM3 433 DS	SIMINOR	CVXN,MITTO,SIM433
FADINI (AMC)	FADINI JUB,JUB SMALL, ASTRO 43 SMALL,433 M2 ASTRO 433-2, ASTRO 433-4, AIBR2/JUB4	SERAI	OG/S2,OG54,OG82,OG84,OG/28,OG48,OG62,OG64
FERPORT	TAC1,TAC2,TAC4,TAC 1K,TAC 2K,TAC 4K,TAC2KR	SOMFY	LEIS,K-EASY,K-EASY NEW,K-EASY OLD,MITTO.KEY GO RTS,TEUS,KEYTIS RTS
GHIDI	GHIDI OPEN TM8, OPEN OUT, AUO1590, AU1600, DOMI-NO AU1680 WOOD, GHIDI AU1616,GHIDI AU1680, AU1810, AUJO3000,AUJO3000 DOMINO,DTIC 433A,DT5433-4-AUQ400	SOMMER	SOMMER 4026 TX03-868-2,SOMMER 4020 TX03-868-4,SOMMER 4031,SOMMER 4025,SOMMER 4011,SOMMER 4035,APERTO 4025
GULLIVER	MDW	STAGNOLI	KALLISTO,VENUS AV223
GENIUS (AMC)	AMIGO,AMIGOLD,KILO,BRAVO,ECHO	TAU (AMC)	25OK-SLIMP,25OK-SLIMM,25OT-48P
GENIE (AMC)	GTR-3, GIT, GICT390, GIFT390-4, G3T-BX, G1T-BX, GM3T, GICTD, GIFTD	TELCOMA	FM402,FM402E,FM400E,FM400
HORMANN	HSM2,HSM4	TORLIFT	TORMIT4
JAY	UBEI X 15L1,UBET 21,UBET 41,UBET 61	VDS (AMC)	TRQ P,ECO-R
KBLUE	UBEI X 15L1,UBET 21,UBET 41,UBET 61	VARWIFORD	EA433 4K,SMART2,SMART3
		V2 (AMC)	V2 PHOX 2, V2 PHOX 4,V2 PHOENIX 2,V2 PHOENIX 4,V2 TXC,V2 TRC,V2 TSC4,V2 HAND