

17	Assign special calling number	ADM	41FF ABCD #
		Clear all	41 #
		Clear the licensed first digit of dialing-out of group PP	41 PP #
18	Private password setting	setting the extension No. UV private password	3 UV WWW/L#
19	clear private passwords	clear all	300#
		clear the extension No. UV private password	3UV#
20	Setting call duration for extension	Enable	6 N TT #
		Disable	6 N 00 #
21	Assign extension 1 access CO line right	Extension N not access CO line M	7 M N 6 #
		Not allowed extension N access CO line M	7 M N 1 #
		All extension can access CO line M	7 M #
22	Flexible extension number	change the number of extension N in ABCD	9 N ABCD #
		revert the factory setting	9000#

Chap 1 system synopsis

208C/308C:

1. Three paragraph of computer operator's voice
2. FSK/DTMF sender chip inside, CO line CID can be transferred from one extension to another freely
3. CO line monitor
4. Outgoing call restrict range
5. Trunk line transfer to trunk line, 3-party conference call
6. Call splitting and call forwarding
7. Auto transfer to another when transfer to a busy extension
8. External music input
9. Use PC to program, compatible with CDX1000 PC manager system

832C

The basic function as 208C/308C, more powerful function as following:

1. 32 group password
2. Intelligent routing
3. Upgradeable module design (From 416 to 832)
4. Internal CID, alarm clock
5. Hi-efficiency safe switching power, back up battery optional
6. 300 charge data can be stored

Chap 2 Installation

1. System Appearance



Front View



208C/308C Rear View



416C/832C Rear View

2. Attention:

Please pay attention to the important items of installation:

- ①The telephone exchange shall be installed in a stable indoor place with dry, ventilated environment. (Temperature Range: 0°C-45°C, Humidity Range: 20%-80%. Avoid straight sun shine or in the environment of flammable or caustic gas.) Special telephone wire is preferable.
- ②A marginal space around the exchange should be remained for heat sink, inspection and maintenance of the system.
- ③A wall bore is available at the underside of mainframe for wall installation. Desk installation is also admitted. But the contact of wall belt and circuit board inside the mainframe should be avoided.
- ④Please keep the exchange away from other equipment producing large electromagnetic disturbance (such as motor and large transformer).
- ⑤Note of the wiring of any extension should share the pipeline with power supply or antenna. Neither should the extension be close to antenna for air broadcasting (including short-wave).
- ⑥Avoid damaging the power-supply cable. Keep it away from water. Encountering the leakage of water cut off the power immediately.
- ⑦Please don't impact or shake the exchange at any situation. Don't remove the exchange in working status.
- ⑧If the wiring pipeline of the extension is disturbed by electromagnetic wave while substitution is unavailable in site, special insulating wire for communication is suggested for substitution, also, the insulating net of which should be grounded.

3. Warning:

- The wiring should not be done in thundering.
- Avoid using telephone in thundering.
- Please don't use the telephone in flammable and leaking gas environment.
- Unless the equipment is disconnected, please don't touch the broken part of the wiring or any connection ends.

Chap 3 System programming

Notice:

Using DTMF phone as extension, and all setting must be done on extension 001-604. Commands can be continuously input, press "*" to indicate the end of command. If there is any mistake during programming, just press "*" to restart without hang up. User will hear a prompt tone "du" when input is correct while three "du" for incorrect input. Notice that input is only allowed when the prompt tone finishes or it will be invalid and incorrect input may happen. Once programming finishes, it can keep on working without restart. When programming, especially notice that the extension sequence number is 01-32 (two digits), and exterior number is 1-8 (one digit).

How to Enter Programming mode:

In direct outgoing mode, press *#xxxx

In indirect outgoing mode, press #*xxxx

xxxx: programming password, factory set is 0000

1. Restore the default setting

Instruction: 0000#

Explanation: Please wait the confirm tone, see Appendix 2 for the details of default setting; this will not change the setting of "Flexible coding".

2. Change password

Instruction: 09 xxxx #

Explanation: xxxx is the original programming password

3. Flash time (For active the hold and diverting operating) setting

Instruction: 00 L #

Explanation: L=1-5

L=10.8s

L=21.0s

L=31.2s

L=41.5s

L=51.8s

4. System date/time setting (Only for 416c/832c)

Instruction: 01 YYMMDD #

Explanation:

YY: year, 00-99

MM: month, 01-12

DD: date, 01-31

Instruction: 02 HH TT #

Explanation:

HH: hour, 00-23, 24 hours mode

TT: minutes, 00-59

5. Set active charge delay time

Instruction: 03 TT #

Explanation: The PC charge software will delay TT (from 00-99) seconds to active the charge time after the user dialed out.

6. Clear the charge list

Instruction: 0400 #

Explanation: Clear the charge list stored in system memory.

-5-

7. Extension alarm time setting

Instruction: 05 #

Explanation: Clear all extensions' alarm setting

Instruction: 05N #

Explanation: Clear alarm time setting of extension N(01-32)

Instruction: 05Nhh tt #

Explanation: Set alarm time(hh: hour, 00-23; tt: minutes, 00-59) of extension N (01-32).

8. CO line incoming ringing delay

Instruction: 0610 #

Explanation: No delay, extensions will ring at the same time as CO lines.

Instruction: 0611 #

Explanation: Extensions will delay one cycle to ring.

9. Operator mode /Auto-attendant mode

Instruction: 10# All exterior lines are Auto-attendant mode

10M# No M exterior line is Auto-attendant mode (M is exterior line code number that from 1-8)

11M# No M exterior line is operator mode (M is exterior line code number that from 1-8)

11# All exterior lines are operator mode

Explanation: if the setting is operator mode, when there is an incoming by exterior line, the extensions that have already been set will ring simultaneously. Pick up to talk or to transfer, the extensions which do not ringing can also answer it use the call pick up order; if the setting is Auto-attendant mode, when there is an incoming by exterior line, exterior line will hear digital record, and if dial one of the extension numberend it will ring, if dial 0 for inquiry, the operator will ring.

10. Recording outgoing message:

Instruction: 12 # (..... the paragraph of the OCM)

Explanation: Input 12-# is in the state of system programming, it begins second digital recording when hear "du" and end it when hear "du" again. During recording, please use high quality double audio frequency phone and pick up handset for recording. User can do recording for several times until satisfy.

Instruction: 13-# (the paragraph of the OGM)

Explanation: In the state of system programming, it begins record listen in when hear "du" and end it when hear "du" again. Record can do several times until satisfy, better makes the practical effect of the exterior line incoming as final standard.

11. Monitoring the recorded message:

Instruction: 13-# (the paragraph of the OGM)

Explanation: In the state of system programming, it begins record listen in when hear "du" and end it when hear "du" again. Record can do several times until satisfy, better makes the practical effect of the exterior line incoming as final standard.

12. Monitoring the holding music:

Instruction: 14#

Explanation: Input 14# in the state of system programming, it begins music listen in when hear "du" and end it when hear "du" again.

13. Operator setting:

Instruction: 15N#

Explanation: N is extension sequence number (01-32)

14. Auto-attendant mode no answer process

Instruction: 160# Release the exterior line

161# Transfer to operator

Explanation: When there is an incoming by exterior line, after playing the recorded message, if the caller didn't dial the extension No, use this instruction to set the exterior connect to operator or cut it.

15. Add digits for intercom CID

Instruction: 180# Disable add digits for intercom CID

180kk# Add kk in intercom CID number

Explanation: Some CID telephone can't display the CID number less than 4 digits, so we must add more digits for intercom CID.

16. Setting dialing out mode

Instruction: 2N0# (direct outgoing, N is the extension sequence number 01-32)

2N1# (indirect outgoing, press 9 for outgoing N is the extension sequence number 01-32)

20# (all extensions direct outgoing)

21# (all extensions press 9 for outgoing)

17. C.O Line Ringing Assignment

Instruction: 3MN0# Enable one extension

3MN1# Disable one extension

3M# Disable all

Explanation: "M" means C.O line port No. (1-4). "N" The last 2 digits of original extensions (601-632)

18. Setting service grade:

Order: 40NL (set service grade is the grade L of extension N)

40L# (all extension are grade L)

Explanation: L is the grade number, from 0 to 6.

L=0----Permit to dial the special calling number only

L=1----no call-out limitation

L=2----call-out with limiting of international distance dialing

L=3----call-out with limiting of domestic distance dialing

L=4----call-out with limiting initial of item A

L=5----call-out with limiting initial of item B

L=6----forbid local call, only intercom is allowed.

19. Setting restriction Group A

Order: 4 1 QQ A B C D # (QQ is the group number, from 01 to 16)
4 1 # (Clear all the call out limitation of initial of item A)
4 1 QQ # (Clear the call out limitation of initial of item QQ in term A)

Explanation: limitation A can lock 16 groups of 4-digit initial, ABCD is the initial of the number, to be locked, it can be ended with # if digit less than 4. User can set for internal or international telephone limitation, or special number.

Setting restriction Group B

Order: 4 2 QQ A B C D # (Q is the number of group, from 01 to 16)
4 2 # (Clear all the call out limitation of initial of item B)
4 2 QQ # (Clear the call out limitation of initial of item QQ in term B)

Explanation: User can set limitation of all codes.

20. Assign special calling number (Item C of Class Setup)

Instruction: 4 3 PP A B C D # (PP is the number of group, from 01 to 16)
4 3 # (Clear all the first-digit number of dialing-out)
4 3 PP # (Clear the licensed first-digit of dialing-out of group PP)

Note: that is to say 16 groups 4-digit first-digit can be used, ABCD is the first-digit of the locking numbers, it could be less than 4 digits, ended with #. Licensed dialing means that the first-digit of the locking numbers of certain locked extensions can be rescind. More convenience can be achieved when calling these certain telephone number, used for Grade 3.

21. Private password setting

Instruction: 500# clear all private passwords
5 UV WWW L # setting the extension No. UV' private password
5 UV # release the extension No. UV' private password

Explanation: UV is one of number from 1 to 99, it is private password sequence number; WWW is 4 digits password; L is the service grade of private password (refer to "service grade setting"). When using private password user must input private password with sequence number (refer to "private password using in using way"), in other word, must input UV WWW (6 digits)

22. Setting call duration for extension

Instruction: 6 N TT # (N is the sequence number of extension, TT is the limited time, counted by minutes, ranges from 1 to 99)

Explanation: This function can only limit the time of exterior call. For example, if the calling time of extension 06 must be limited in 8 minutes, the user can dial 60608# while programming.

23. Assign extension's access CO line right

Instruction: 7 M N 0 # Extension N (N=01-32) can access CO line M (M=1-8)
7 M N 1 # Not allowed extension N access CO line M
7 M # All extension can access CO line M

Explanation: If you want to set extension 603 can't access CO line 2, and extension 606, 608 can access CO line 1, please input:

72031# 71060# 71080#

24. Flexible extension number:

Instruction: 9 0 0 0 # (restore the factory setting)
9 Nabc# (change the number of extension N to abcd)

Explanation: N is the sequence number of the extension, abcd is the new number, 1 to 4 digit number, ended by #. The new numbers range from 1-8999, all extensions must not be same number. (The length of new number must follow the extension No.1; it must be emphasized that if the length of new number changed, all the extensions must be reset after setting extension No.1. Any two new numbers couldn't be the same. Otherwise abnormality will appear. For example, to set the extension's number to 4-digit number (6001-6040), the user should dial 9016001# then dial 9026002#, 9036003#... one by one, up to 8406040.)

Function brief introduction

Important Notice: If you choose indirect outgoing dialing out mode, no need to dial * in following operation.

Incoming call

1. Answering calls at operator mode:

The extension(s) set to ring will ring when an incoming call is received, and pick up the handset you may answer the call directly.

2. Answering calls at auto-attendant mode:

No extension will ring when an incoming call is received, the message recorded will be heard before dialing extension number.

Remark: 1. You can set different DISA mode.

2. When a caller dials "0" for inquiry, operator extension will ring.

If operator extension is busy, then system can use the function "busy call transfer".

3. Call pick up

The incoming call can be answered by the extension that is not ringing rather than the ringing one, thus makes the answering more convenient.

Operation: Pick up and press * # 9

Outgoing call

4. Outward dialing directly:

Pick up the handset and dial external number directly after hearing the C.O line tone.

Outward dialing by dial 9 first:

Pick up the handset and dial "9" first after hearing the internal dialing tone, then dial the C.O line number after hearing the C.O line dialing tone.

5. Exterior-line Booking

If exterior line is busy and calling has to be done immediately, a booking of exterior line will be done and will be clue to the current user.

- 11 -

6. Selecting CO line

Operation: * # 1 M (M=1-8, CO line no.)

You can use this operation if you want to select a CO line to dial out.

7. Use the private password. (For 832/416)

Operation: * # 5 + private password (including the sequence number).

Remark: (1) private password UVW'W'W is 6 digit (2 digit sequence number + 4 digit code).

(2) Use private password dial IP telephone: # 5 + private password. (including: sequence number). Direct dial Long-Distance code + Telephone number + # (the restriction class serviced by the private password permit you dial Long distance call) after hear the internal tone.

8. Outgoing call Transfer Function

Format: Put the hook then dial the extension number

Description: This function let you make an outgoing call from one extension then divert and connect other extension to C.O line.

9. Call transfer

Operation: Put the hook then dial the extension number

Description: Allows you to transfer an incoming call to another extension.

Remark:

1> There may be following 4 cases after a call is transferred from A to B:

a. A does not hang up and B picks up his handset

Then communication between A and B is established while the outside caller is on-holding (music on holding), whoever hangs up (A or B), the system transfer to outside caller to the other.

b. A does not hang up and B does not answer A within 25 seconds

If Ext. B does not answer A within 25 seconds, then A will restore the connection with C.O line, and B will stop ringing.

c. A hangs up and B answers the call

B will answer the outside caller.

d. A hangs up and B does not answer the call within 25 seconds

Call will be back to A and will ring for 25 seconds. If A is busy, the system will cut off.

- 2> The FLASH TIME is from 750ms to 2000ms for putting the hook, you may press FLASH button instead of press the hook for transferring the incoming call.
- 3> The extension, which transfer the call, has 5 seconds to dial the extension number, required otherwise the incoming call will be back to him again.

4> The Flash time can be set.

10. Conference (2 extensions and 1 C.O line)

Format: Put the hook and * + extension number

Description: Allows you to add a third part to a two-parts conversation and make a three-parts conference. You can have only two extensions with one C.O line

11. C.O Line Reservation:

Operation: Put the hook and press * +

The occupying exterior line can be reserved by exchanger. Then another exterior line can be transferred or talked by interphone, which can solve the problem that the incoming call waits long for answering or even no answer. Therefore the function of the exchanger is largely extended.

The exterior lines for incoming or outgoing call are both reserved.

12. R key function:

Operation: * 8 9

Use this to make a R key operation (As telephone's R key) in C.O line, this is always used for switching the call waiting.

Intercom calling

13. Intercom calling at direct outward mode

Operation: * + Extension number

Description: Make internal call between extensions with direct outward mode.

Intercom calling at indirect outward mode

Operation: Dial the extension number directly.

Remark: Intercom calling is free of charge.

14. Call operation:

Operation: * 0 (at direct outward mode)
* 0 (at indirect outward mode)

Other Functions:

15. Alarming clock (Optional)

Operation: * 4 4 hhr (at direct outward mode)

hh: hour (00-23)

mm: minutes (00-59)

Notice: System will lose the alarming clock setting after power off.

16. Query functions:

Extension number query (Through DU DU tone)

Operation: * # 60 (at direct outward mode)

The number of DU DU tone indicate the extension number.

Extension number query (Through CID)

Operation: * # 62 (at direct outward mode)

When hang down the telephone will ring, and the extension number will be displayed in your caller identify telephone.

System time query

Operation: * # 63 (at direct outward mode)

After input the command and hang down, telephone will ring, and the time will be displayed in your caller identify telephone.

* # 66 (at direct outward mode)

After input the command and hang down, telephone will ring, and the date will be displayed in your caller identify telephone.

17. Call forwarding

Operation for enable: *#81 abc (at direct outward mode)

Operation for disable: *#81# (at direct outward mode)

Description: Allows an extension to transfer incoming calls automatically to another extension.

Remark: (1) Input "*" at first if the extension is direct outward mode.

(2) After successful setting, you can hear a beeper. "abc" is the current extension number.

(3) This setting cannot save if the system power off.

18. Call busy transfer

Operation for enable: *#82 abc (at direct outward mode)

Operation for disable: *#82# (at direct outward mode)

Description: When an extension is busy, allow it to transfer incoming calls automatically to another extension.

Remark: (1) Input "*" at first if the extension is direct outward mode.

(2) After successful setting, you can hear a beeper. "abc" is the current extension number.

(3) This setting cannot save if the system power off.

19. No disturbing

Operation for enable: *#83 (at direct outward mode)

Operation for disable: It will be disable automatically next time you pick up the phone.

Description: When an extension is setting to no disturbing mode, it will not ring.

20. Call all extensions (Emergency call)

Operation: *#88

Troubleshooting

BREAKDOWN	CAUSE	SOLUTION
Running light malfunction	Power off	Check the power on and off Power supply
No sound from extension	Disconnected wiring or malfunction of extension	Reconnect the wiring or try to remove the defective extension
Extension	Disconnected	Reconnect the wire
Extension	The disturbing of line or not receivable	Check telephone lines for abnormality
Call tone	The setting of call transfer frequency	Adjust the transfer frequency
No receiving telephone display	Incorrect function of receiving telephone display Wrong setting of "No disturbing" and "Call transfer"	Check the display Adjust the setting and set receiving telephone display
Call transfer malfunction	Extension not in call transfer mode	Check whether the line is connected well
Unusual ringing time	Time setting	Adjust the time
Cannot program the telephone	Wrong setting	Check the programming extension and use the right code
Others	Others	Refer to professional

Technical terms

N-----	Sequential number of the extensions (01-32 with corresponding input ports 601-632) (two digits)
M-----	Sequential number of the exterior line (No. 1-8 with corresponding input ports of Line 1- 8)
XXXX-----	4 digits of programming codes on host extension
abcd-----	Number of the extension (1-8999, except for the digits with the first digit: 0 or 9, an equal length) is accordance with N
QQ-----	First-digit limitation group number (01-16)
ABCD-----	Licensed or limited number of first 1-4 digits, end for 8
L-----	Service grade
PP-----	Licence Group Number (01-16)
TT-----	01-99, minutes
UVwww-----	6 digits of portable passwords, UV stands for sequential number (01-32, fixed), www stands for 4-digit password, which can be setup.

Kk.....two digits will be added in your dialing number
 YYMMDD.....YY-year(00-99),MM-month(01-12),DD-date(01-31)
 HHmm.....hh-hour(00-23),mm-minutes(00-59)

Default settings

Operating mode.....operator mode
 Ringing extension.....602
 Trunk line grouping.....no setting
 Restriction class.....class 2
 Restrict outgoing digits.....no
 C.O line.....1-8
 Extension numbers.....601-632
 Dialing out mode.....dial "9" or delayed for outgoing call

System Programming Instruction

Index	System functions	Codes
1	Reset the default setting	0000#
2	Change password	99 XXXX #
3	System date time setting	01YYMMDDMM
4	Set active change delay time	02HHMM
5	Clear all extension alarm	03#
6	Clear alarm time setting of extension N	05N#
7	Set alarm time of extension N	06NHHMM
8	Operator mode	11#
9	No M extension line is operator mode	12MM
10	All extension lines are Auto-attendant mode	13#
11	No M extension line is Auto-attendant mode	14MM

1	Recording incoming message	99999999#	1111#
2	Recording outgoing message	99999999#	1112#
3	Recording outgoing message	99999999#	1113#
4	Monitoring the recorded message	99999999#	1114#
5	Monitoring the recorded message	99999999#	1115#
6	Monitoring the recorded message	99999999#	1116#
7	Monitoring the recorded message	99999999#	1117#
8	Monitoring the recorded message	99999999#	1118#
9	Monitoring the recorded message	99999999#	1119#
10	Monitoring the recorded message	99999999#	1120#
11	Operator setting	99999999#	1121#
12	Auto-attendant mode on answer process	99999999#	1122#
13	Transfer to operator	99999999#	1123#
14	Add digits for extension C.O	99999999#	1124#
15	Setting dialing out mode	99999999#	1125#
16	C.O Line Ringing Assignment	99999999#	1126#
17	Setting service grade	99999999#	1127#
18	Setting restriction	99999999#	1128#
19	Setting restriction	99999999#	1129#
20	Setting restriction	99999999#	1130#
21	Setting restriction	99999999#	1131#
22	Setting restriction	99999999#	1132#
23	Setting restriction	99999999#	1133#
24	Setting restriction	99999999#	1134#
25	Setting restriction	99999999#	1135#
26	Setting restriction	99999999#	1136#
27	Setting restriction	99999999#	1137#
28	Setting restriction	99999999#	1138#
29	Setting restriction	99999999#	1139#
30	Setting restriction	99999999#	1140#
31	Setting restriction	99999999#	1141#
32	Setting restriction	99999999#	1142#
33	Setting restriction	99999999#	1143#
34	Setting restriction	99999999#	1144#
35	Setting restriction	99999999#	1145#
36	Setting restriction	99999999#	1146#
37	Setting restriction	99999999#	1147#
38	Setting restriction	99999999#	1148#
39	Setting restriction	99999999#	1149#
40	Setting restriction	99999999#	1150#
41	Setting restriction	99999999#	1151#
42	Setting restriction	99999999#	1152#
43	Setting restriction	99999999#	1153#
44	Setting restriction	99999999#	1154#
45	Setting restriction	99999999#	1155#
46	Setting restriction	99999999#	1156#
47	Setting restriction	99999999#	1157#
48	Setting restriction	99999999#	1158#
49	Setting restriction	99999999#	1159#
50	Setting restriction	99999999#	1160#
51	Setting restriction	99999999#	1161#
52	Setting restriction	99999999#	1162#
53	Setting restriction	99999999#	1163#
54	Setting restriction	99999999#	1164#
55	Setting restriction	99999999#	1165#
56	Setting restriction	99999999#	1166#
57	Setting restriction	99999999#	1167#
58	Setting restriction	99999999#	1168#
59	Setting restriction	99999999#	1169#
60	Setting restriction	99999999#	1170#
61	Setting restriction	99999999#	1171#
62	Setting restriction	99999999#	1172#
63	Setting restriction	99999999#	1173#
64	Setting restriction	99999999#	1174#
65	Setting restriction	99999999#	1175#
66	Setting restriction	99999999#	1176#
67	Setting restriction	99999999#	1177#
68	Setting restriction	99999999#	1178#
69	Setting restriction	99999999#	1179#
70	Setting restriction	99999999#	1180#
71	Setting restriction	99999999#	1181#
72	Setting restriction	99999999#	1182#
73	Setting restriction	99999999#	1183#
74	Setting restriction	99999999#	1184#
75	Setting restriction	99999999#	1185#
76	Setting restriction	99999999#	1186#
77	Setting restriction	99999999#	1187#
78	Setting restriction	99999999#	1188#
79	Setting restriction	99999999#	1189#
80	Setting restriction	99999999#	1190#
81	Setting restriction	99999999#	1191#
82	Setting restriction	99999999#	1192#
83	Setting restriction	99999999#	1193#
84	Setting restriction	99999999#	1194#
85	Setting restriction	99999999#	1195#
86	Setting restriction	99999999#	1196#
87	Setting restriction	99999999#	1197#
88	Setting restriction	99999999#	1198#
89	Setting restriction	99999999#	1199#
90	Setting restriction	99999999#	1200#
91	Setting restriction	99999999#	1201#
92	Setting restriction	99999999#	1202#
93	Setting restriction	99999999#	1203#
94	Setting restriction	99999999#	1204#
95	Setting restriction	99999999#	1205#
96	Setting restriction	99999999#	1206#
97	Setting restriction	99999999#	1207#
98	Setting restriction	99999999#	1208#
99	Setting restriction	99999999#	1209#
100	Setting restriction	99999999#	1210#

17	Assign special calling number	ADM	41FF ABCD #
		Clear all	41 #
		Clear the licensed first digit of dialing-out of group PP	41 PP #
18	Private password setting	assign the extension No. UV private password	3 UV WWWW L#
19	clear private passwords	clear all	300#
		clear the extension No. UV private password	3UV#
20	Setting call duration for extension	Enable	6 N TT #
		Disable	6 N 00 #
21	Assign extension N access CO line right	Extension N can access CO line M	7 M N 0 #
		Not allowed extension N access CO line M	7 M N 1 #
		All extensions can access CO line M	7 M #
22	Flexible extension number	change the number of extension N in ABCD	9 N ABCD #
		revert the factory setting	9000#