

RAID AHCI 6Gbps 4x (mSATA + SATA) PCIe Host Adapter

1. Features

- 6Gbps SATA and mSATA total 4 Ports Host Adapter
- Supports PCIe 1.0 and PCIe 2.0 motherboard
- Supports SATA III transfer rate of 6.0Gbps
- Supports SATA I & SATA II & SATA III HDD, SSD, mSATA SSD, Optical Drive and Blu-Ray Drive
- Supports ATA and ATAPI commands
- Supports Native Command Queuing (NCQ)
- Supports max one SATA FIS-based or Command-based Port Multiplier and max 4 drives connected to PM
- SATA Hot-plug capability
- 64bit / 32bit Windows 8, Win7, Vista, 2008, 2012, Linux and Mac 10.x built-in AHCI inbox driver support, no additional driver required
- Supports Windows XP driver
- Fully RoHS compliant

BUY ON
www.cablematic.com

2. Package Contents

- SATA III 4 Ports Host Adapter
- Users Manual

3. mSATA Green LED and SATA LED Pin Header

mSATA Green LED or SATA LED0 ~ LED3 Pin Header:

ON: When drive linked

Blink: When drive accessing

(LED ALL) Pin Header:

ON: When any one of 4 drives linked

Blink: When any one of 4 drives accessing

4. Installation

1. When Windows XP or 2003, run installer "**drvSetup.exe**" on driver CD folder "**E:\SATA6G_M9128**" until "**Finish**".
2. When Windows 8, Win7, Vista, 2008, 2012, Linux and Mac 10.x, OS built-in AHCI inbox driver support, no additional driver required.
3. If you concern the yellow mark of "Marvell Console ATA Device" in Windows Device Manage, you may run **drvConsoleSetup.exe** to remove it.

***For Hardware RAID 0, RAID 1, HybridDrive mode setting in Windows, please refer MSU_user_guide.pdf and MSUSetup.exe in driver CD path E:\SATA6G_M9128\GUI.