

INDEX

DVI SPLITTER MANUAL 1~3

HDMI SPLITTER MANUAL 4~6

VGA SPLITTER MANUAL 7~9

VGA AND AUDIO SPLITTER MANUAL 10~13

BUY ON

www.cablematic.com

INTRODUCTION

Thank you for purchasing our DVI splitter.

The DVI splitter/distribution enables 2, 4 or 8 DVI-D monitors to be driven by a single PC with no loss of signal. DVI output-1 is the primary connection and is used for the main display. DVI other output follows the main display.

FEATURES

- Distributes computer DVI graphic signal to 2, 4 or 8 displays simultaneously.
- Accurate and reliable reproduction of digital video signal, with no signal attenuation or distortion
- Fully compliant with the DVI 1.0 standard
- Provides high digital resolution up to 1920 x 1200 @ 60 Hz
- Full DDC2B communications are supported on Output-1.
- DVI cables are used to connect the DVI input and the computers output
- Installs in seconds

Note: The DVI splitter will only output a DVI-D (DVI digital) signal. If your using a DVI-I cable, it will ONLY pass the digital signal.

SPECIFICATIONS

| | |
|------------------------------------|--|
| Video Amplifier Bandwidth | 1.65 GHz |
| Single Link Range | 1920 x 1200 |
| DVI Input/Output Connector Type | DVI-I |
| Cable Distance (Device to Monitor) | 10 m (Max.) |
| Video In Ports | 1 |
| Video Out Ports | SP201D , DVISP102A : 2 SP401D , DVISP104A : 4 SP801D , DVISP108A : 8 |
| LED Indicators | 1 x Power |
| Power Supply | 12V/2A DC |
| Power Consumption | SP201D , DVISP102A : 5 Watts (max.) SP401D , DVISP104A : 9 Watts (max.) SP801D , DVISP108A : 18 Watts (max.) |
| Dimensions(W x H x D) | SP201D , DVISP102A :150mm x 74mm x 31mm SP401D , DVISP104A :240mm x 89mm x 31mm SP801D , DVISP108A :438mm x 161mm x 44.5mm |
| Shipping Weight | SP201D , DVISP102A :0.3Kg SP201D , DVISP102A :0.558Kg SP201D , DVISP102A :2.0Kg |

INCLUDES

- The DVI splitter
- 12V/2A DC Power Supply
- Users Manual

Installation

- (1) Turn off the power of all devices (computer, monitors and splitter).
- (2) Connect the video source's DVI output port to the splitter DVI input port using standard DVI cable.
- (3) Connect the DVI display's DVI input port to the splitter DVI output port.
- (4) Plug the 12V power supply into the DVI Splitter.
- (5) Plug the 12V wallmount power supply into the wall outlet or power bar. Check to see if the power LED light is active on the front of the DVI splitter.
- (6) Turn on the displays.
- (7) Turn on the video source.

Operation for Cascade

If you need to add more monitors, you need to attach an additional splitter box.

Connect a DVI male/male extension cable between a Video Out port of the primary splitter (the splitter connected to the computer) and the Video In port on the cascaded splitter.

NOTE: Even though you can cascade the splitters, the image might become unstable if you cascade too many tiers of splitters.

HDMI SPLITTER USER MANUAL

INTRODUCTION

Congratulations on your purchase of our HDMI splitter.

The HDMI splitter allows one HDMI source to be outputted on up to 2, 4,

or 8 HDMI devices. All outputs will have mirrored images.

The connection is simple.

BUY ON
www.cablematic.com

FEATURES

- Distributes easily up to 2, 4, or 8 HDMI/DVI displays
- Maintains 480i, 480p, 720i, 720p, and 1080i, 1080p Resolutions
- Maintains highest HDMI single link video resolution
- Maintains highest HDMI digital audio signal
- Fully HDCP Compliant
- HDMI or DVI to HDMI cables are used to connect the inputs and output

SPECIFICATIONS

| | |
|--------------------------------------|---|
| Video Amplifier Bandwidth | 1.65 GHz |
| Single Link Range | 1080p / 1920 x 1200 |
| DVI Input/Output | HDMI A type |
| Connector Type | |
| Cable Distance (Device to Monitor) | 15 m (Max.) |
| Video Input Connector (HDMI Female) | 1 |
| Video Output Connector (HDMI Female) | SP201H , HDMISP102A : 2 SP201H , HDMISP102A : 4 SP201H , HDMISP102A : 8 |
| LED Indicators | 1 x Power |
| Power Supply | 12V/2A DC |
| Power Consumption | SP201H , HDMISP102A : 6 Watts (max.) SP201H , HDMISP102A : 10 Watts (max.) SP201H , HDMISP102A : 20 Watts (max.) |
| Dimensions(W x H x D) | SP201H , HDMISP102A : 121mm x 74mm x 36mm SP401H , HDMISP104A : 180mm x 105mm x 36mm SP801H , HDMISP108A : 260mm x 135mm x 36mm |

INCLUDES

The HDMI splitter
 12V/2A DC Power Supply
 Users Manual

Installation

- (1) Connect the supplied cable from the HDMI source into the HDMISP108A input.
- (2) Connect the cables from your displays (monitor or projector) into the HDMI outs of the HDMI splitter.
- (3) Plug the 12VDC power supply into the HDMI splitter.
- (4) Plug the 12VDC wallmount power supply into the wall outlet.

Operation for Cascade

If you need to add more monitors, you need to attach an additional splitter box.

Connect a HDMI male/male extension cable between a Video Out port of the primary splitter (the splitter connected to the computer) and the Video In port on the cascaded splitter.

NOTE: Even though you can cascade the splitters, the image might become unstable if you cascade too many tiers of splitters.

INTRODUCTION

Congratulations on your purchase of our VGA Video splitters. These splitters are Professional Splitters that allow a PC to display on 2, 4, or 8 monitors simultaneously. They are perfect for presentations, classrooms, tradeshow, or in-store displays where the highest quality video on several monitors is needed. The splitters support monitors with up to 400MHz of bandwidth allowing it to display images of 2048 x 1536 pixels or higher. A built-in booster circuit allows the video signal to be extended up to 100 meters. These splitters are also daisy-chainable for future expansion and are compatible with a wide range of monitors.

FEATURES

- Allows one computer to provide simultaneous displays on 2, 4, or 8 different monitors
- Works with VGA, SVGA, XGA, QXGA, UXGA and Multisync monitors
- High video bandwidth (400 MHz) provides crystal clear 2048 x 1536 resolution
- Daisy chainable for almost unlimited expansion
- Built-in video amplifier boosts the signal to allow a cable length of up to 100 meters
- Uses standard monitor extension cables
- Compatible with DDC, DDC2 & DDC2B (on Video Out port 1, all other monitors must be able to support the highest Video resolution of the DDC-type monitor connected to Video Out 1)

SPECIFICATIONS

| | |
|-----------------------|---|
| Signal Type | XGA, VGA, SVGA, QXGA, UXGA & Multisync |
| Cable Length | 100m maximum |
| Input Connector | 1 x HDDB15 (male) |
| Output Connectors | SP240 : 2 x HDDB15 (female) SP440 : 4 x HDDB15 (female) SP840 : 8 x HDDB15 (female) |
| LED | 1 x Power |
| Enclosure | Metal |
| Power | DC 9V1A |
| Dimensions | SP240 : 213x85x30 mm SP440 : 213x85x30 mm SP840 : 213x85x44.5 mm |
| VGA Bandwidth (-3dB) | 400 MHz |
| VGA Resolution (max.) | 2048 x 1536 @ 70Hz |

INCLUDES

- The VGA Video splitter
- Power adapter (Optional)
- USB A-B cable (Optional)
- User Manual

Installation

Note: If you are connecting the splitter to a DDC monitor, the other monitors you connect to the splitter must be of the same resolution as the DDC monitor. The DDC monitor must be plugged into Video Out port number 1.

- (1) Make sure that your computer and monitors are turned off.
- (2) Using an HD-15 video cable, connect your computer's Video Out port to the Video In port on the back of the splitter.
- (3) Plug your monitors into the Video Out ports on the back of the splitter.
- (4) Plug the power adapter into the DC port on the back of the splitter. Plug the other end of the adapter into an available power source. The Power LED on the front will now be lit.

Cascade Configuration

Connect an HD-15 male-male cable between a Video Out port of the primary splitter (the splitter connected to the computer) and the Video In port on the cascaded splitter.

Note: Adding too many layers of splitters may cause a decline in video quality.

INTRODUCTION

Congratulations on your purchase of our video and audio splitter.

Now you'll be able to broadcast the audio and video signals from one PC over multiple sound systems and monitors. It is perfect for presentations, classrooms, tradeshow, or in-store displays where the highest quality video on several monitors is needed.

The splitter supports monitors with up to 400MHz of bandwidth allowing it to display images of 2048 x 1536 pixels or higher. A built-in booster circuit allows the video signal to be extended up to 100 meters. These splitters are also daisy-chainable for future expansion and are compatible with a wide range of monitors.

FEATURES

- Allows one computer to provide simultaneous displays on 2, 4, or 8 different monitors with audio support
- Works with VGA, SVGA, XGA, QXGA, UXGA and Multisync monitors
- High video bandwidth (400 MHz) provides crystal clear 2048 x 1536 resolution
- Daisy chainable for almost unlimited expansion
- Built-in video amplifier boosts the signal to allow a cable length of up to 100 meters
- Uses standard monitor extension cables
- Compatible with DDC, DDC2 & DDC2B (on Video Out port 1, all other monitors must be able to support the highest Video resolution of the DDC-type monitor connected to Video Out 1)

SPECIFICATIONS

| | |
|----------------------|---|
| Signal Type | XGA, VGA, SVGA, QXGA, UXGA & Multisync |
| Cable Length | 100m maximum |
| Input Connector | 1 x HDDB15 (male) 1 x 3.5mm Audio Jack (male) |
| Output Connectors | SP240A : 2 x HDDB15 (female) 2 x 3.5mm Audio Jack (male) SP440A : 4 x HDDB15 (female) 4 x 3.5mm Audio Jack (male) SP840A : 8 x HDDB15 (female) 8 x 3.5mm Audio Jack (male) |
| LED | 1 x Power |
| Enclosure | Metal |
| Power | DC 9V1A |
| Dimensions | SP240A : 267x85x30 mm SP440A : 267x85x30 mm SP840A : 267x85x44.5 mm |
| GA Bandwidth (-3dB) | 400 MHz |
| GA Resolution (max.) | 2048 x 1536 @ 70Hz |

INCLUDES

The VGA Video splitter with audio

Power adapter (Optional)

USB A-B cable (Optional)

User Manual

Installation

Note: If you are connecting the splitter to a DDC monitor, the other monitors you connect to the splitter must be of the same resolution as the DDC monitor. The DDC monitor must be plugged into Video Out port number 1.

(1) Make sure that your computer and monitors are turned off.

(2) Using an HD-15 video cable, connect your computer's Video Out port to the Video In port on the back of the splitter.

(3) Using a 3.5" audio cable, connect your computer's Audio Out port to the Audio In port on the back of the splitter.

(4) Plug your monitors into the Video Out ports on the back of the splitter.

(5) Plug your speakers/headphones into the Audio Out ports on the back of the splitter. Plug the

(6) Plug the power adapter into the DC port on the back of the other end of the adapter into an available power source. The Power LED on the front will now be lit.

Cascade Configuration

Connect an HD-15 male-male cable between a Video Out port of the primary splitter (the splitter connected to the computer) and the Video In port on the cascaded splitter. Do the same with the audio ports.

Note: Adding too many layers of splitters may cause a decline in video and audio Quality.

BUY ON
www.cablematic.com