

LED 6 Lantern light

Please read this user manual before using this product.

Features

Voltage: AC220V/110V 50/60Hz

Power: 50W

Equipped with 90pcs (30R, 30G, 30B) intensive brightness LEDs

4 operation modes: Automatic running, DMX, Sound Active, Master/Slave

Sound controlled via built-in microphone

12 DMX channels

Advantages of LED-technology: extremely long life, low power consumption minimal heat emission, defacto maintenance free with brilliant light radiation

Size: L49*W27*H16

Weight: 2.2kg

INTRUDCTION

Thank you for choosing, you will see you have acquired a powerful and versatile device.

DMX512 Controller instruction)

CH1	0-4	Not working
	5-251	15 effect choices
	252-255	Sound control mode
CH2	0-255	Speed control quick---slow
CH3	0-4	Not working
	5-255	Stroboscopic control quick---slow
CH4,5,6,7,8, 9,10,11	0-35	Not working
	36-49	Diffusion display
	50-255	Static display
CH12	0-49	Not working
	50-91	Red
	92-133	Green
	134-175	Blue
	176-218	All shining

Address code control instruction)

Address code	Address code	Function instruction
ON	OFF	
10	1.2.3.4.5.6.7.8.9	Automatic mode
10.9	1.2.3.4.5.6.7.8	Twinkling mode
2.3.4.5.6.7.8.10	1.9	All shining
	1.2.3.4.5.6.7.8.9.10	Sound mode
10.4	1.2.3.5.6.7.8.9	Mode 4
10.3	1.2.4.5.6.7.8.9	Mode 3
10.2	1.3.4.5.6.7.8.9	Mode 2
10.1	2.3.4.5.6.7.8.9	Mode 1
10.(5.6)	1.2.3.4.7.8.9	Speed 2
10.(7.8)	1.2.3.4.5.6.9	Speed 1
1	2.3.4.5.6.7.8.9	DMX512

Safety instruction

CAUTION!

Be careful with your operations. With a dangerous voltage you can suffer a dangerous electric shock when touching the wires !
Electric shock when touching the wires!

to ensure a safe operation, it is absolutely necessary for the user to follow the safety instructions and warning notes written in this manual.

BUY ON
www.cablematic.com