

4 Gang Fused Socket User Instructions BLACK, WHITE & ORANGE




IMPORTANT

These instructions must be followed to ensure the safe usage of this 4 gang socket.

WARNING

The total maximum load must not exceed 13amps/3120watts. Ensure that all plugs to be used in this unit are fitted with fuses of the correct amperage as recommended by the appliance manufacturers. The total power consumed by the appliances plugged into this unit must not exceed 3120watts.



WIRING INSTRUCTIONS

- 1 Use only 1.25mm² (13amp) or 1.5mm² 3 core flexible cable. Use of a smaller cable could result in overheating.
- 2 Prepare cable as shown in Figure 1.
- 3 Remove cover and cord grip as shown in Figure 2.
- 4 It is important to connect the correct coloured wire to the appropriate terminal as shown in Figure 3 and to ensure that all terminal screws are securely tightened.




Fig. 2

4 Gang Fused Socket User Instructions continued

- 5 Ensure that the cable sheath is securely clamped using the cord grip as shown in Figure 3.
- 6 Replace and tighten securely the terminal cover. The other end of the cable must be fitted with a 13amp plug fused at 13amps (recommended Permaplug HDPT13 or PT13). An unfused plug must not be used.

TO CHANGE THE FUSE

WARNING

Always switch off the mains supply and remove the plug before removing or replacing the fuse carrier.

- 1 Switch off the mains supply and remove the plug.
- 2 Remove the fuse carrier by turning anticlockwise with a coin and lifting carrier and fuse clear.
- 3 Always fit a 13amp fuse to BS 1362.
- 4 Ensure the carrier is turned fully home when replacing.




Fig. 3

**CONSULT A QUALIFIED
ELECTRICIAN FOR ANY
FURTHER ADVICE**

MOUNTING

- 1 This unit may be mounted by use of the key-holes provided on the base of the unit. These are set at 180mm centres. **Under no circumstances must this unit be hard wired or connected as a fixed installation.** Mains connection must be by use of a flexible cable and 13amp plug to BS1363:Part 1:1995
- 2 Do not use or mount as a trailing socket where it may be subject to the effects of dampness or excessive moisture.