

---

**High Speed,  $\pm 0.1 \mu\text{V}/^\circ\text{C}$  Offset Drift, Fully Differential ADC Driver****FEATURES**

- ▶ Broad power supply range: 3 V to 10 V
- ▶ Wide input common-mode voltage range:  
 $-V_s$  to  $+V_s - 1.3 \text{ V}$
- ▶ Rail-to-rail output
- ▶ Fully specified dual power mode operation
  - ▶ 4 mA full power mode (145 MHz)
  - ▶ 1.4 mA low power mode (80 MHz)
- ▶ Full power mode
  - ▶ Low harmonic distortion
    - ▶  $-133 \text{ dBc HD2}$  and  $-140 \text{ dBc HD3}$  at 1 kHz
    - ▶  $-133 \text{ dBc HD2}$  and  $-116 \text{ dBc HD3}$  at 100 kHz
- ▶ Fast settling time
  - ▶ 18-bit: 100 ns
  - ▶ 16-bit: 50 ns
- ▶ Input voltage noise:  $2.0 \text{ nV}/\sqrt{\text{Hz}}$ ,  $f = 100 \text{ kHz}$
- ▶  $\pm 115 \mu\text{V}$  maximum offset voltage from  $-40^\circ\text{C}$  to  $+125^\circ\text{C}$
- ▶ Adjustable output clamps for ADC input protection

**APPLICATIONS**

- ▶ Low power  $\Sigma\text{-}\Delta$ , PulSAR®, and SAR ADC drivers
- ▶ Single-ended to differential converters
- ▶ Differential buffers
- ▶ Medical imaging
- ▶ Process control
- ▶ Portable electronics

**GENERAL DESCRIPTION**


The ADA4945-1 is a low-noise, low-distortion, fully differential amplifier with two selectable power modes. The device operates over a broad power supply range of 3 V to 10 V. The low DC offset, DC offset drift, and excellent dynamic performance of the ADA4945-1 make it well suited for a variety of data acquisition and signal processing applications. The device is an ideal choice for driving high-resolution, high-performance successive approximation register (SAR) and  $\Sigma\text{-}\Delta$  analog-to-digital converters (ADCs) on 4 mA of quiescent current (full power mode). The device can also be selected to operate on 1.4 mA of quiescent current (low power mode) to scale the power consumption to the desired performance necessary for an ADC drive application. The adjustable common-mode voltage allows the ADA4945-1 to match the input common-mode voltage of multiple ADCs. The internal common-mode feedback loop provides exceptional output balance, as well as suppression of even order harmonic distortion products.

With the ADA4945-1, differential gain configurations are achieved with a simple external feedback network of four resistors determining the closed-loop gain of the amplifier. The ADA4945-1 is fabricated using Analog Devices, Inc., proprietary, silicon germanium (SiGe), complementary bipolar process, enabling the device to achieve low levels of distortion with an input voltage noise of only  $2.0 \text{ nV}/\sqrt{\text{Hz}}$  (full power mode).

The ADA4945-1 is available in a RoHS-compliant, 3 mm  $\times$  3 mm, 16-lead LFCSP package. It is specified to operate from  $-40^\circ\text{C}$  to  $+125^\circ\text{C}$ .

High Speed,  $\pm 0.1 \mu\text{V}/^\circ\text{C}$  Offset Drift, Fully Differential ADC Driver

## FUNCTIONAL BLOCK DIAGRAM



### NOTES

- CONNECT THE EXPOSED PAD TO  $-V_S$ .

**Figure 1. Functional Block Diagram**

## TABLE OF CONTENTS

Features.....	1
Applications .....	1
General Description .....	1
FUNCTIONAL BLOCK DIAGRAM .....	2
Revision History .....	4
Specifications.....	5
Absolute Maximum Ratings .....	21
Thermal Resistance.....	21
Maximum Power Dissipation.....	21
ESD Caution .....	22
Pin Configurations and Function Descriptions.....	23
Typical Performance Characteristics (FULL POWER MODE) .....	24
Typical Performance Characteristics (LOW POWER MODE).....	32
Test Circuits.....	40
TERMINOLOGY .....	41
Differential Voltage .....	41
Common-Mode Voltage (CMV) .....	41
Common-Mode Offset Voltage .....	41
Differential $V_{OS}$ , Differential CMRR, and $V_{OCM}$ CMRR .....	41
Balance .....	42
Theory of Operation .....	43
Fully Differential and Common-Mode Signal Paths.....	43
Output Voltage Clamp .....	44
Power Modes .....	45
Applications Information .....	46
Analyzing an Application Circuit .....	46
Setting the Closed-Loop Gain.....	46
Estimating the Output Noise Voltage .....	46
Impact of Mismatches in the Feedback Networks .....	47
Calculating the Input Impedance of an Application Circuit .....	47
Terminating a Single-Ended Input.....	48
Input Common-Mode Voltage Range.....	50
Input and Output Capacitive AC Coupling.....	50
Setting the Output Common-Mode Voltage.....	50

Disable Pin .....51

Driving a Capacitive Load .....51

Output Clamps .....52

Driving a High Precision ADC .....53

LAYOUT, GROUNDING, AND BYPASSING .....55

OUTLINE DIMENSIONS .....56

Ordering Guide.....56

**REVISION HISTORY**

Nature of Change	Page Number
<b>4/2019, Rev 0</b> Initial release	—
<b>5/2024, Rev A</b> Updated <i>Features, General Description</i> sections	1
Updated <i>Electrical Characteristics</i> (Table 1, Table 4, Table 7)	5, 6, 7, 11, 12, 15, 16, 17
Updated <i>Driving a High Precision ADC</i> section	53
Updated Table 14	54
Updated Figure 33, Figure 34, Figure 78, Figure 79	28, 29, 36, 37

## SPECIFICATIONS

**Table 1. Positive Input (+D<sub>IN</sub>) or Negative Input (-D<sub>IN</sub>) to Differential Output Voltage (V<sub>OUT, dm</sub>) Performance**

(SUPPLY VOLTAGE (V<sub>S</sub>) = 10 V Output common-mode voltage (V<sub>OCM</sub>) = midsupply, Gain (G) = 1, feedback resistance (R<sub>F</sub>) = gain resistance (R<sub>G</sub>) = 499 Ω, differential load resistance (R<sub>L, dm</sub>) = 1 kΩ, and T<sub>A</sub> = 25°C, unless otherwise noted. All specifications refer to single-ended input and differential outputs, unless otherwise noted. Refer to Figure 98 for circuit definitions.)

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
DYNAMIC PERFORMANCE									
-3 dB Small Signal Bandwidth	f <sub>3dB</sub>	V <sub>OUT, dm</sub> = 20 mV p-p, G = 1		145			80		MHz
		V <sub>OUT, dm</sub> = 20 mV p-p, G = 2		95			40		MHz
		V <sub>OUT, dm</sub> = 20 mV p-p, G = 5		40			17		MHz
-3 dB Large Signal Bandwidth		V <sub>OUT, dm</sub> = 2 V p-p, G = 1		60			18		MHz
		V <sub>OUT, dm</sub> = 2 V p-p, G = 2		54			40		MHz
		V <sub>OUT, dm</sub> = 2 V p-p, G = 5		52			16		MHz
Bandwidth for 0.1 dB Flatness	f <sub>0.1dB</sub>	V <sub>OUT, dm</sub> = 20 mV p-p, G = 1		28			27		MHz
		V <sub>OUT, dm</sub> = 20 mV p-p, G = 2		20			7		MHz
Slew Rate	SR	V <sub>OUT, dm</sub> = 8 V step		600			100		V/μs
Settling Time to 0.1%	t <sub>ST</sub>	V <sub>OUT, dm</sub> = 8 V step		35			85		ns
Settling Time	t <sub>ST</sub>	16-bit		50			150		ns
		18-bit		100			300		ns
Input Overdrive Recovery		G = 1, differential input voltage (V <sub>IN, dm</sub> ) = 10 V p-p, triangular waveform		500			300		ns
Output Overdrive Recovery		G = 10, V <sub>IN, dm</sub> = 2.4 V p-p, triangular waveform		200			120		ns
NOISE/HARMONIC PERFORMANCE									
NOISE/HARMONIC PERFORMANCE		V <sub>OUT, dm</sub> = 8 V p-p							
Second Harmonic Distortion	HD2	Center frequency (f <sub>C</sub> ) = 1 kHz		-133			-133		dBc
		f <sub>C</sub> = 100 kHz		-133			-133		dBc
		f <sub>C</sub> = 100 kHz, G = 2		-128			-128		dBc
		f <sub>C</sub> = 1 MHz		-95			-68		dBc
Third Harmonic Distortion	HD3	f <sub>C</sub> = 1 kHz		-140			-138		dBc

(SUPPLY VOLTAGE ( $V_S$ ) = 10 V Output common-mode voltage ( $V_{OCM}$ ) = midsupply, Gain ( $G$ ) = 1, feedback resistance ( $R_F$ ) = gain resistance ( $R_G$ ) = 499  $\Omega$ , differential load resistance ( $R_{L, dm}$ ) = 1 k $\Omega$ , and  $T_A$  = 25°C, unless otherwise noted. All specifications refer to single-ended input and differential outputs, unless otherwise noted. Refer to Figure 98 for circuit definitions.)

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
Third Harmonic Distortion	HD3	$f_c = 100$ kHz		-116			-116		dBc
		$f_c = 100$ kHz, $G = 2$		-123			-122		dBc
		$f_c = 1$ MHz		-88			-62		dBc
Input Voltage Noise Differential	$V_{N, DIFF}$	$f = 10$ Hz		5			6		nV/ $\sqrt{\text{Hz}}$
		$f = 100$ kHz		2.0			3.5		nV/ $\sqrt{\text{Hz}}$
		1/f corner frequency		100			40		Hz
Common Mode	$V_{N, CM}$	$f = 10$ Hz		350			284		nV/ $\sqrt{\text{Hz}}$
		$f = 100$ kHz		30			38		nV/ $\sqrt{\text{Hz}}$
		1/f corner frequency		1000			1000		Hz
Integrated Voltage Noise		0.1 Hz to 10 Hz		35			35		nV rms
Input Current Noise	$I_N$	$f = 10$ Hz		17			7		pA/ $\sqrt{\text{Hz}}$
		$f = 100$ kHz		1.0			0.6		pA/ $\sqrt{\text{Hz}}$
		1/f corner frequency		2000			1000		Hz

## INPUT CHARACTERISTICS

Input Offset Voltage	$V_{OS}$	25°C		$\pm 10$	$\pm 50$		$\pm 10$	$\pm 50$	$\mu\text{V}$
		$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		$\pm 15$	$\pm 80$		$\pm 15$	$\pm 80$	$\mu\text{V}$
		$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		$\pm 30$	$\pm 115$		$\pm 30$	$\pm 115$	$\mu\text{V}$
Input Offset Voltage Drift	$V_{OS, TC}$	$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		$\pm 0.1$	$\pm 0.5$		$\pm 0.1$	$\pm 0.5$	$\mu\text{V}/^\circ\text{C}$
		$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		$\pm 0.2$	$\pm 1.0$		$\pm 0.2$	$\pm 1.0$	$\mu\text{V}/^\circ\text{C}$
Input Bias Current	$I_B$	$T_A = 25^\circ\text{C}$		-1.2	-2.5		-0.5	-0.8	$\mu\text{A}$
		$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		-1.5	-3.0		-0.6	-1.0	$\mu\text{A}$
		$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		-1.8	-3.4		-0.7	-1.2	$\mu\text{A}$
Input Bias Current Drift	$I_{B, TC}$	$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		-10	-50		-10	-50	nA/ $^\circ\text{C}$
Input Bias Current Drift	$I_{B, TC}$	$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		-10	-50		-10	-50	nA/ $^\circ\text{C}$
Input Offset Current	$I_{OS}$	$T_A = 25^\circ\text{C}$		$\pm 20$	$\pm 200$		$\pm 10$	$\pm 130$	nA
		$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		$\pm 25$	$\pm 250$		$\pm 20$	$\pm 150$	nA
		$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		$\pm 40$	$\pm 300$		$\pm 25$	$\pm 200$	nA

(SUPPLY VOLTAGE ( $V_S$ ) = 10 V Output common-mode voltage ( $V_{OCM}$ ) = midsupply, Gain ( $G$ ) = 1, feedback resistance ( $R_F$ ) = gain resistance ( $R_G$ ) = 499  $\Omega$ , differential load resistance ( $R_{L, dm}$ ) = 1 k $\Omega$ , and  $T_A$  = 25°C, unless otherwise noted. All specifications refer to single-ended input and differential outputs, unless otherwise noted. Refer to Figure 98 for circuit definitions.)

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
Input Offset Current Drift	$I_{OS\_TC}$	$T_A = 20^\circ\text{C to } 85^\circ\text{C}$		$\pm 0.1$	$\pm 0.6$		$\pm 0.06$	$\pm 0.38$	nA/ $^\circ\text{C}$
		$T_A = -40^\circ\text{C to } +125^\circ\text{C}$		$\pm 0.12$	$\pm 0.7$		$\pm 0.07$	$\pm 0.4$	nA/ $^\circ\text{C}$
Input Common-Mode Voltage Range	$V_{CM}$		$-V_S$		$+V_S$ $-1.3$	$-V_S$		$+V_S$ $-1.3$	V
Input Resistance	$R_{IN, DIFF}$	Differential		50			50		k $\Omega$
	$R_{IN, CM}$	Common mode		50			50		M $\Omega$
Input Capacitance	$C_{IN}$			1			1		pF
Common-Mode Rejection Ratio	CMRR	$V_{CM} = 0.5 \text{ V to } 8.7 \text{ V}$		-110			-110		dB
Open-Loop Gain	$A_{OL}$	Output voltage ( $V_{OUT}$ ) = $\pm 4 \text{ V}$		120			115		dB

## OUTPUT CHARACTERISTICS

Output Voltage Swing	$V_{OUT}$	Load resistance ( $R_L$ ) = 100 $\Omega$ for each single-ended output	$-V_S$ + 0.55		$+V_S$ - 0.55	$-V_S$ + 0.55		$+V_S$ - 0.55	V
		$R_L = 1 \text{ k}\Omega$	$-V_S$ +0.1		$+V_S$ -0.1	$-V_S$ +0.1		$+V_S$ -0.1	V
Short-Circuit Current	$I_{SC}$			170			140		mA peak
Output Balance Error		$f = 100 \text{ kHz}$ , $\Delta V_{OUT, cm} / \Delta V_{OUT, dm}$		100			100		dB

**Table 2.  $V_{OCM}$  to Common-Mode Output Voltage ( $V_{OUT, cm}$ ) Performance**

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
$V_{OCM}$ DYNAMIC PERFORMANCE									
-3 dB Small Signal Bandwidth	$f_{3dB, VO_{CM}}$	$V_{OUT, cm} = 20 \text{ mV p-p}$		35			15		MHz
-3 dB Large Signal Bandwidth		$V_{OUT, cm} = 2 \text{ V p-p}$		3.8			1.3		MHz
Slew Rate	$SR_{VO_{CM}}$	$V_{OUT, cm} = 2 \text{ V p-p}$		26			9		V/ $\mu$ s
Input Voltage Noise	$V_{N, VO_{CM}}$	$f = 100 \text{ kHz}$		35			45		nV/ $\sqrt{\text{Hz}}$
Gain		$\Delta V_{OUT, cm} / \Delta V_{OCM}, \Delta V_{OCM} = \pm 1 \text{ V}$	0.99	1	1.01	0.99	1	1.01	V/V
$V_{OCM}$ CHARACTERISTICS									
Input Common-Mode Voltage Range	$V_{OCM}$		$-V_S$ + 0.4		$+V_S$ - 1.4	$-V_S$ + 0.4		$+V_S$ - 1.4	V
Input Resistance	$R_{IN, VO_{CM}}$			125			125		k $\Omega$
Offset Voltage	$V_{OS, VO_{CM}}$	Common mode offset ( $V_{OS, cm}$ ) = $V_{OUT, cm} - V_{OCM}$ , positive input ( $V_{IP}$ ) = negative input ( $V_{IN}$ ) = $V_{OCM} = 0 \text{ V}, 25^\circ\text{C}$		$\pm 5$	$\pm 60$		$\pm 5$	$\pm 60$	mV
		$T_A = 20^\circ\text{C to } 85^\circ\text{C}$		$\pm 10$			$\pm 10$		mV
		$T_A = -40^\circ\text{C to } +125^\circ\text{C}$		$\pm 20$			$\pm 20$		mV
Input Offset Voltage Drift	$V_{OS, TC, VO_{CM}}$	$T_A = 20^\circ\text{C to } 85^\circ\text{C}$		$\pm 5$			$\pm 5$		$\mu\text{V}/^\circ\text{C}$
		$T_A = -40^\circ\text{C to } +125^\circ\text{C}$		$\pm 10$			$\pm 10$		$\mu\text{V}/^\circ\text{C}$
Input Bias Current	$I_{B, VO_{CM}}$	$T_A = 25^\circ\text{C}$		-220			-160		nA
		$T_A = 20^\circ\text{C to } 85^\circ\text{C}$		-300			-205		nA
		$T_A = -40^\circ\text{C to } +125^\circ\text{C}$		-350			-230		nA
Input Bias Current Drift	$I_{B, TC, VO_{CM}}$	$T_A = 20^\circ\text{C to } 85^\circ\text{C}$		-1.3			-0.75		nA/ $^\circ\text{C}$
		$T_A = -40^\circ\text{C to } +125^\circ\text{C}$		-1.5			-1.0		nA/ $^\circ\text{C}$
CMRR	$CMRR_{VO_{CM}}$	$\Delta V_{OS, dm} / \Delta V_{OCM}, \Delta V_{OCM} = \pm 1 \text{ V}$		-130			-130		dB



Table 3. General Performance

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
CLAMP									
Clamp Output Voltage		Differential	$-V_S$ -0.5		$+V_S$ +0.5	$-V_S$ -0.5		$+V_S$ +0.5	V
		Common mode	$-V_S$		$+V_S$	$-V_S$		$+V_S$	V
Recovery Time				100			100		ns
Input Resistance		Resistance between $+V_{CLAMP}$ and $-V_{CLAMP}$		480			480		k $\Omega$
DISABLE ( $\overline{DISABLE}$ PIN) MODE									
Input Voltage		Disabled	$-V_S$ -0.3		$D_{GND}$ +1	$-V_S$ -0.3		$D_{GND}$ +1	V
		Enabled	$D_{GND}$ +1.4		$+V_S$ +0.3	$D_{GND}$ +1.4		$+V_S$ +0.3	V
Turn Off Time	$t_{OFF}$	Quiescent current < 10% of enabled quiescent current		6			6		$\mu$ s
Turn On Time	$t_{ON}$	Turn on time ( $t_o$ ) > 90% of final $V_{OUT}$		1.2			2		$\mu$ s
$\overline{DISABLE}$ Pin Bias Current Enabled		$\overline{DISABLE} = 10$ V		50			50		nA
$\overline{DISABLE}$ Pin Bias Current Disabled		$\overline{DISABLE} = 0$ V		50			50		nA
$D_{GND}$ PIN									
VOLTAGE RANGE	$IVR_{DGND}$		$-V_S$		$+V_S$ -2.5	$-V_S$		$+V_S$ -2.5	V
POWER SUPPLY									
Operating Range	$\pm V_S$		3		10	3		10	V
Quiescent Current Enabled	$I_q$	Full power mode, MODE = $+V_S$		4	4.2				mA
		Low power mode, MODE = $-V_S$					1.4	1.6	mA
Quiescent Current Disabled		Full power mode, MODE = $+V_S$		60	70				$\mu$ A

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
Quiescent Current Disabled		Low power mode, MODE = $-V_S$					60	70	$\mu\text{A}$
Positive Power Supply Rejection Ratio	+PSRR	$\Delta V_{OS, dm} / \Delta V_S$ , $\Delta V_S = 1 \text{ V p-p}$		-120			-120		dB
Negative Power Supply Rejection Ratio	-PSRR	$\Delta V_{OS, dm} / \Delta V_S$ , $\Delta V_S = 1 \text{ V p-p}$		-120			-120		dB
OPERATING TEMPERATURE RANGE			-40		+125	-40		+125	$^{\circ}\text{C}$

**Table 4. +D<sub>IN</sub> or -D<sub>IN</sub> to V<sub>OUT, dm</sub> Performance**

( $V_S = 5 \text{ V}$ ,  $V_{OCM} = \text{midsupply}$ ,  $G = 1$ ,  $R_F = R_G = 499 \Omega$ ,  $R_{L, dm} = 1 \text{ k}\Omega$ ,  $T_A = 25^{\circ}\text{C}$ , unless otherwise noted. All specifications refer to single-ended input and differential outputs, unless otherwise noted. Refer to Figure 98 for circuits definitions.)

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
DYNAMIC PERFORMANCE									
-3 dB Small Signal Bandwidth	$f_{3dB}$	$V_{OUT, dm} = 20 \text{ mV p-p}$ , $G = 1$		145			80		MHz
		$V_{OUT, dm} = 20 \text{ mV p-p}$ , $G = 2$		95			40		MHz
		$V_{OUT, dm} = 20 \text{ mV p-p}$ , $G = 5$		40			17		MHz
-3 dB Large Signal Bandwidth		$V_{OUT, dm} = 2 \text{ V p-p}$ , $G = 1$		60			18		MHz
		$V_{OUT, dm} = 2 \text{ V p-p}$ , $G = 2$		54			40		MHz
		$V_{OUT, dm} = 2 \text{ V p-p}$ , $G = 5$		52			16		MHz
Bandwidth for 0.1 dB Flatness	$f_{0.1dB}$	$V_{OUT, dm} = 20 \text{ mV p-p}$ , $G = 1$		28			27		MHz
		$V_{OUT, dm} = 20 \text{ mV p-p}$ , $G = 2$		20			7		MHz
Slew Rate	SR	$V_{OUT, dm} = 8 \text{ V step}$		600			100		$\text{V}/\mu\text{s}$
Settling Time to 0.1%	$t_{ST}$	$V_{OUT, dm} = 8 \text{ V step}$		35			85		ns
Settling Time	$t_{ST}$	16-bit		50			150		ns
		18-bit		100			300		ns

( $V_S = 5\text{ V}$ ,  $V_{OCM} = \text{midsupply}$ ,  $G = 1$ ,  $R_F = R_G = 499\ \Omega$ ,  $R_{L, dm} = 1\ \text{k}\Omega$ ,  $T_A = 25^\circ\text{C}$ , unless otherwise noted. All specifications refer to single-ended input and differential outputs, unless otherwise noted. Refer to Figure 98 for circuits definitions.)

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
Input Overdrive Recovery		$G = 1$ , $V_{IN, dm} = 10\ \text{V p-p}$ , triangular waveform		300			500		ns
Output Overdrive Recovery		$G = 2$ , $V_{IN, dm} = 6\ \text{V p-p}$ , triangular waveform		145			80		ns

## NOISE/HARMONIC PERFORMANCE

NOISE/HARMONIC PERFORMANCE		$V_{OUT, dm} = 8\ \text{V p-p}$							
Second Harmonic Distortion	HD2	$f_c = 1\ \text{kHz}$		-133			-133		dBc
		$f_c = 100\ \text{kHz}$		-133			-133		dBc
		$f_c = 100\ \text{kHz}$ , $G = 2$		-128			-128		dBc
		$f_c = 1\ \text{MHz}$		-95			-68		dBc
Third Harmonic Distortion	HD3	$f_c = 1\ \text{kHz}$		-140			-138		dBc
		$f_c = 100\ \text{kHz}$		-116			-116		dBc
		$f_c = 100\ \text{kHz}$ , $G = 2$		-123			-122		dBc
		$f_c = 1\ \text{MHz}$		-88			-62		dBc
Input Voltage Noise Differential	$V_{N, DIFF}$	$f = 10\ \text{Hz}$		5			6		nV/ $\sqrt{\text{Hz}}$
		$f = 100\ \text{kHz}$		2.0			3.5		nV/ $\sqrt{\text{Hz}}$
		1/f corner frequency		100			40		Hz
Input Voltage Noise Common Mode	$V_{N, CM}$	$f = 10\ \text{Hz}$		350			284		nV/ $\sqrt{\text{Hz}}$
		$f = 100\ \text{kHz}$		30			38		nV/ $\sqrt{\text{Hz}}$
		1/f corner frequency		1000			1000		Hz
Integrated Voltage Noise		0.1 Hz to 10 Hz		35			35		nV rms
Input Current Noise	$I_N$	$f = 10\ \text{Hz}$		17			7		pA/ $\sqrt{\text{Hz}}$
		$f = 100\ \text{kHz}$		1.0			0.6		pA/ $\sqrt{\text{Hz}}$
		1/f corner frequency		2000			1000		Hz

## INPUT CHARACTERISTICS

Input Offset Voltage	$V_{OS}$	25°C		$\pm 10$	$\pm 50$		$\pm 10$	$\pm 50$	$\mu\text{V}$
		$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		$\pm 15$	$\pm 80$		$\pm 15$	$\pm 80$	$\mu\text{V}$
		$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		$\pm 30$	$\pm 115$		$\pm 30$	$\pm 115$	$\mu\text{V}$

( $V_S = 5\text{ V}$ ,  $V_{OCM} = \text{midsupply}$ ,  $G = 1$ ,  $R_F = R_G = 499\ \Omega$ ,  $R_{L, dm} = 1\ \text{k}\Omega$ ,  $T_A = 25^\circ\text{C}$ , unless otherwise noted. All specifications refer to single-ended input and differential outputs, unless otherwise noted. Refer to Figure 98 for circuits definitions.)

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
Input Offset Voltage Drift	$V_{OS\_TC}$	$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		$\pm 0.1$	$\pm 0.5$		$\pm 0.1$	$\pm 0.5$	$\mu\text{V}/^\circ\text{C}$
		$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		$\pm 0.2$	$\pm 1.0$		$\pm 0.2$	$\pm 1.0$	$\mu\text{V}/^\circ\text{C}$
Input Bias Current	$I_B$	$T_A = 25^\circ\text{C}$		-1.2	-2.5		-0.5	-0.8	$\mu\text{A}$
		$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		-1.5	-3.0		-0.6	-1.0	$\mu\text{A}$
		$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		-1.8	-3.4		-0.7	-1.2	$\mu\text{A}$
Input Bias Current Drift	$I_{B\_TC}$	$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		-10	-50		-10	-50	$\text{nA}/^\circ\text{C}$
		$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		-10	-50		-10	-50	$\text{nA}/^\circ\text{C}$
Input Offset Current	$I_{OS}$	$T_A = 25^\circ\text{C}$		$\pm 20$	$\pm 200$		$\pm 10$	$\pm 130$	$\text{nA}$
		$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		$\pm 25$	$\pm 250$		$\pm 20$	$\pm 150$	$\text{nA}$
		$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		$\pm 40$	$\pm 300$		$\pm 25$	$\pm 200$	$\text{nA}$
Input Offset Current Drift	$I_{OS\_TC}$	$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		$\pm 0.1$	$\pm 0.6$		$\pm 0.06$	$\pm 0.38$	$\text{nA}/^\circ\text{C}$
		$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		$\pm 0.12$	$\pm 0.7$		$\pm 0.07$	$\pm 0.4$	$\text{nA}/^\circ\text{C}$
$V_{CM}$ Range	$V_{CM}$		$-V_S$	$+V_S$ -1.3		$-V_S$	$+V_S$ -1.3	$\text{V}$	
Input Resistance	$R_{IN, DIFF}$	Differential		50			50		$\text{k}\Omega$
	$R_{IN, CM}$	Common mode		50			50		$\text{M}\Omega$
Input Capacitance	$C_{IN}$			1			1		$\text{pF}$
CMRR		$V_{CM} = 0.5\text{ V}$ to $3.7\text{ V}$		-110			-110		$\text{dB}$
Open-Loop Gain	$A_{OL}$	$V_{OUT} = \pm 4\text{ V}$		120			115		$\text{dB}$

## OUTPUT CHARACTERISTICS

Output Voltage Swing	$V_{OUT}$	$R_L = 100\ \Omega$	$-V_S$ + 0.55		$+V_S$ - 0.55	$-V_S$ + 0.55		$+V_S$ - 0.55	$\text{V}$
Output Voltage Swing	$V_{OUT}$	$R_L = 1\ \text{k}\Omega$	$-V_S$ +0.1		$+V_S$ -0.1	$-V_S$ +0.1		$+V_S$ -0.1	$\text{V}$
Short-Circuit Current	$I_{SC}$			170			140		$\text{mA}$ peak
Output Balance Error		$f = 100\ \text{kHz}$ , $\Delta V_{OUT, cm} / \Delta V_{OUT, dm}$		100			100		$\text{dB}$

Table 5. VO<sub>CM</sub> to V<sub>OUT</sub>, CM Performance

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
V <sub>OCM</sub> DYNAMIC PERFORMANCE									
-3 dB Small Signal Bandwidth	f <sub>3dB, VO<sub>CM</sub></sub>	V <sub>OUT, cm</sub> = 20 mV p-p		35			15		MHz
		V <sub>OUT, cm</sub> = 2 V p-p		3.8			1.3		MHz
Slew Rate	SR <sub>VO<sub>CM</sub></sub>	V <sub>OUT, cm</sub> = 2 V p-p		26			9		V/μs
Input Voltage Noise	V <sub>N, VO<sub>CM</sub></sub>	f = 100 kHz		35			45		nV/√Hz
Gain		$\Delta V_{OUT, cm} / \Delta V_{OCM}, \Delta V_{OCM} = \pm 1 V$	0.99	1	1.01	0.99	1	1.01	V/V
V <sub>OCM</sub> CHARACTERISTICS									
Input Common-Mode Voltage Range	V <sub>OCM</sub>		-V <sub>S</sub> +0.4		+V <sub>S</sub> -1.4	-V <sub>S</sub> +0.4		+V <sub>S</sub> -1.4	V
Input Resistance	R <sub>IN, VO<sub>CM</sub></sub>			125			125		kΩ
Offset Voltage	V <sub>OS, VO<sub>CM</sub></sub>	V <sub>OS, cm</sub> = V <sub>OUT, cm</sub> - V <sub>OCM</sub> , V <sub>IP</sub> = V <sub>IN</sub> = V <sub>OCM</sub> = 0 V, 25°C		±10	±60		±10	±60	mV
		T <sub>A</sub> = 20°C to 85°C		±10			±10		mV
		T <sub>A</sub> = -40°C to +125°C		±20			±20		mV
Input Offset Voltage Drift	V <sub>OS, TC, VO<sub>CM</sub></sub>	T <sub>A</sub> = 20°C to 85°C		±5			±5		μV/°C
		T <sub>A</sub> = -40°C to +125°C		±10			±10		μV/°C
Input Bias Current	I <sub>B, VO<sub>CM</sub></sub>	T <sub>A</sub> = 25°C		-220			-160		nA
		T <sub>A</sub> = 20°C to 85°C		-300			-205		nA
		T <sub>A</sub> = -40°C to +125°C		-350			-230		nA
Input Bias Current Drift	I <sub>B, TC, VO<sub>CM</sub></sub>	T <sub>A</sub> = 20°C to 85°C		-1.3			-0.75		nA/°C
		T <sub>A</sub> = -40°C to +125°C		-1.5			-1.0		nA/°C
CMRR	CMRR <sub>VO<sub>CM</sub></sub>	$\Delta V_{OS, dm} / \Delta V_{OCM}, \Delta V_{OCM} = \pm 1 V$		-130			-130		dB

Table 6. General Performance

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
CLAMP									
Clamp Output Voltage		Differential	$-V_S$ -0.5		$+V_S$ +0.5	$-V_S$ -0.5		$+V_S$ +0.5	V
		Common mode	$-V_S$		$+V_S$	$-V_S$		$+V_S$	V
Recovery Time				100			100		ns
Input Resistance		Resistance between $+V_{CLAMP}$ and $-V_{CLAMP}$		480			480		k $\Omega$
DISABLE ( $\overline{DISABLE}$ PIN) MODE									
Input Voltage		Disabled	$-V_S$ -0.3		$D_{GND}$ + 1	$-V_S$ -0.3		$D_{GND}$ + 1	V
		Enabled	$D_{GND}$ +1.4		$+V_S$ + 0.3	$D_{GND}$ +1.4		$+V_S$ + 0.3	V
Turn Off Time	$t_{OFF}$	Quiescent current < 10% of enabled quiescent current		6			6		$\mu$ s
Turn On Time	$t_{ON}$	$t_o$ > 90% of final $V_{OUT}$		1.2			2		$\mu$ s
$\overline{DISABLE}$ Pin Bias Current Enabled		$\overline{DISABLE} = 5$ V		50			50		nA
$\overline{DISABLE}$ Pin Bias Current Disabled		$\overline{DISABLE} = 0$ V		50			50		nA
$D_{GND}$ PIN									
VOLTAGE RANGE	$IV_{DGND}$		$-V_S$		$+V_S$ - 2.5	$-V_S$		$+V_S$ - 2.5	V
POWER SUPPLY									
Operating Range	$\pm V_S$		3		10	3		10	V
Quiescent Current Enabled	$I_q$	Full power mode, MODE = $+V_S$		4	4.2				mA
		Low power mode, MODE = $-V_S$					1.4	1.6	mA
Quiescent Current Disabled		Full power mode, MODE = $+V_S$		60	70				$\mu$ A
		Low power mode, MODE = $-V_S$					60	70	$\mu$ A
+PSRR	+PSRR	$\Delta V_{OS, dm} / \Delta V_S$ , $\Delta V_S = 1$ V p-p		-120			-120		dB
-PSRR	-PSRR	$\Delta V_{OS, dm} / \Delta V_S$ , $\Delta V_S = 1$ V p-p		-120			-120		dB

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
OPERATING TEMPERATURE RANGE			-40		+125	-40		+125	°C

**Table 7. +D<sub>IN</sub> or -D<sub>IN</sub> to V<sub>OUT, DM</sub> Performance**

(V<sub>S</sub> = 3 V V<sub>OCM</sub> = midsupply, G = 1, R<sub>F</sub> = R<sub>G</sub> = 499 Ω, R<sub>L, dm</sub> = 1 kΩ, T<sub>A</sub> = 25°C, unless otherwise noted. All specifications refer to single-ended input and differential outputs, unless otherwise noted. Refer to Figure 98 for circuit definitions.)

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
DYNAMIC PERFORMANCE									
-3 dB Small Signal Bandwidth	f <sub>3dB</sub>	V <sub>OUT, dm</sub> = 20 mV p-p, G = 1		145			80		MHz
		V <sub>OUT, dm</sub> = 20 mV p-p, G = 2		95			40		MHz
		V <sub>OUT, dm</sub> = 20 mV p-p, G = 5		40			17		MHz
-3 dB Large Signal Bandwidth		V <sub>OUT, dm</sub> = 2 V p-p, G = 1		22			11		MHz
Bandwidth for 0.1 dB Flatness	f <sub>0.1dB</sub>	V <sub>OUT, dm</sub> = 20 mV p-p, G = 1		28			27		MHz
		V <sub>OUT, dm</sub> = 20 mV p-p, G = 2		20			7		MHz
Slew Rate	SR	V <sub>OUT, dm</sub> = 4 V step		600			100		V/μs
Settling Time to 0.1%	t <sub>ST</sub>	V <sub>OUT, dm</sub> = 4 V step		35			85		ns
Settling Time	t <sub>ST</sub>	16-bit		50			150		ns
		18-bit		100			300		ns
Input Overdrive Recovery		G = 1, V <sub>IN, dm</sub> = 3 V p-p, triangular waveform		500			300		ns
Output Overdrive Recovery		G = 2, V <sub>IN, dm</sub> = 3 V p-p, triangular waveform		200			120		ns
NOISE/HARMONIC PERFORMANCE									
NOISE/HARMONIC PERFORMANCE		V <sub>OUT, dm</sub> = 4 V p-p							
Second Harmonic Distortion	HD2	Center frequency (f <sub>C</sub> ) = 1 kHz		-133			-133		dBc
		f <sub>C</sub> = 100 kHz		-133			-133		dBc
		f <sub>C</sub> = 100 kHz, G = 2		-128			-128		dBc

( $V_S = 3\text{ V}$ ,  $V_{OCM} = \text{midsupply}$ ,  $G = 1$ ,  $R_F = R_G = 499\ \Omega$ ,  $R_{L, dm} = 1\ \text{k}\Omega$ ,  $T_A = 25^\circ\text{C}$ , unless otherwise noted. All specifications refer to single-ended input and differential outputs, unless otherwise noted. Refer to Figure 98 for circuit definitions.)

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
Second Harmonic Distortion	HD2	$f_c = 1\ \text{MHz}$		-95			-68		dBc
Third Harmonic Distortion	HD3	$f_c = 1\ \text{kHz}$		-140			-138		dBc
		$f_c = 100\ \text{kHz}$		-116			-116		dBc
		$f_c = 100\ \text{kHz}$ , $G = 2$		-123			-122		dBc
		$f_c = 1\ \text{MHz}$		-88			-62		dBc
Input Voltage Noise Differential	$V_{N, \text{DIFF}}$	$f = 10\ \text{Hz}$		5			6		nV/ $\sqrt{\text{Hz}}$
		$f = 100\ \text{kHz}$		2.0			3.5		nV/ $\sqrt{\text{Hz}}$
		1/f corner frequency		100			40		Hz
Common Mode	$V_{N, \text{CM}}$	$f = 10\ \text{Hz}$		350			284		nV/ $\sqrt{\text{Hz}}$
		$f = 100\ \text{kHz}$		30			38		nV/ $\sqrt{\text{Hz}}$
		1/f corner frequency		1000			1000		Hz
Integrated Voltage Noise		0.1 Hz to 10 Hz		35			35		nV rms
Input Current Noise	$I_N$	$f = 10\ \text{Hz}$		17			7		pA/ $\sqrt{\text{Hz}}$
		$f = 100\ \text{kHz}$		1.0			0.6		pA/ $\sqrt{\text{Hz}}$
		1/f corner frequency		2000			1000		Hz

## INPUT CHARACTERISTICS

Input Offset Voltage	$V_{OS}$	25°C		±10	±50		±10	±50	μV
		$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		±15	±80		±15	±80	μV
		$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		±30	±115		±30	±115	μV
Input Offset Voltage Drift	$V_{OS, \text{TC}}$	$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		±0.1	±0.5		±0.1	±0.5	μV/°C
		$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		±0.2	±1.0		±0.2	±1.0	μV/°C
Input Bias Current	$I_B$	$T_A = 25^\circ\text{C}$		-1.2	-2.5		-0.5	-0.8	μA
Input Bias Current	$I_B$	$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		-1.5	-3.0		-0.6	-1.0	μA
		$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		-1.8	-3.4		-0.7	-1.2	μA
Input Bias Current Drift	$I_{B, \text{TC}}$	$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		-10	-50		-10	-50	nA/°C
		$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		-10	-50		-10	-50	nA/°C
Input Offset Current	$I_{OS}$	$T_A = 25^\circ\text{C}$		±20	±200		±10	±130	nA
		$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		±25	±250		±20	±150	nA



( $V_S = 3\text{ V}$ ,  $V_{OCM} = \text{midsupply}$ ,  $G = 1$ ,  $R_F = R_G = 499\ \Omega$ ,  $R_{L, dm} = 1\ \text{k}\Omega$ ,  $T_A = 25^\circ\text{C}$ , unless otherwise noted. All specifications refer to single-ended input and differential outputs, unless otherwise noted. Refer to Figure 98 for circuit definitions.)

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
Input Offset Current	$I_{OS}$	$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		$\pm 40$	$\pm 300$		$\pm 25$	$\pm 200$	nA
Input Offset Current Drift	$I_{OS, TC}$	$T_A = 20^\circ\text{C}$ to $85^\circ\text{C}$		$\pm 0.1$	$\pm 0.6$		$\pm 0.06$	$\pm 0.38$	nA/ $^\circ\text{C}$
		$T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$		$\pm 0.12$	$\pm 0.7$		$\pm 0.07$	$\pm 0.4$	nA/ $^\circ\text{C}$
$V_{CM}$ Range	$V_{CM}$		$-V_S$		$+V_S$ $-1.3$	$-V_S$		$+V_S$ $-1.3$	V
Input Resistance	$R_{IN, DIFF}$	Differential		50			50		k $\Omega$
	$R_{IN, CM}$	Common mode		50			50		M $\Omega$
Input Capacitance	$C_{IN}$			1			1		pF
CMRR		$V_{CM} = 0.5\text{ V}$ to $1.7\text{ V}$		-110			-110		dB
Open-Loop Gain	$A_{OL}$	$V_{OUT} = \pm 2\text{ V}$		120			115		dB

## OUTPUT CHARACTERISTICS

Output Voltage Swing	$V_{OUT}$	$R_L = 100\ \Omega$	$-V_S$ + 0.55		$+V_S$ - 0.55	$-V_S$ + 0.55		$+V_S$ - 0.55	V
Output Voltage Swing	$V_{OUT}$	$R_L = 1\ \text{k}\Omega$	$-V_S$ +0.1		$+V_S$ -0.1	$-V_S$ +0.1		$+V_S$ -0.1	V
Short-Circuit Current	$I_{SC}$			170			140		mA peak
Output Balance Error		$f = 100\ \text{kHz}$ , $\Delta V_{OUT, cm} / \Delta V_{OUT, dm}$		100			100		dB

Table 8.  $V_{OCM}$  to  $V_{OUT, CM}$  Performance

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
$V_{OCM}$ DYNAMIC PERFORMANCE									
-3 dB Small Signal Bandwidth	$f_{3dB, VO_{CM}}$	$V_{OUT, cm} = 20 \text{ mV p-p}$		35			15		MHz
-3 dB Large Signal Bandwidth		$V_{OUT, cm} = 2 \text{ V p-p}$		3.8			1.3		MHz
Slew Rate	$SR_{VO_{CM}}$	$V_{OUT, cm} = 2 \text{ V p-p}$		26			9		V/ $\mu$ s
Input Voltage Noise	$V_{N, VO_{CM}}$	$f = 100 \text{ kHz}$		35			45		nV/ $\sqrt{\text{Hz}}$
Gain		$\Delta V_{OUT, cm} / \Delta V_{OCM}, \Delta V_{OCM} = \pm 1 \text{ V}$	0.99	1	1.01	0.99	1	1.01	V/V
$V_{OCM}$ CHARACTERISTICS									
Input Common-Mode Voltage Range	$V_{OCM}$		$-V_S$ +0.4		$+V_S$ -1.4	$-V_S$ +0.4	$+V_S$ -1.4		V
Input Resistance	$R_{IN, VO_{CM}}$			125			125		k $\Omega$
Offset Voltage	$V_{OS, VO_{CM}}$	$V_{OS, cm} = V_{OUT, cm} - V_{OCM}, V_{IP} = V_{IN} = V_{OCM} = 0 \text{ V}, 25^\circ\text{C}$		$\pm 10$	$\pm 60$		$\pm 10$	$\pm 60$	mV
		$T_A = 20^\circ\text{C} \text{ to } 85^\circ\text{C}$		$\pm 10$			$\pm 10$		mV
		$T_A = -40^\circ\text{C} \text{ to } +125^\circ\text{C}$		$\pm 20$			$\pm 20$		mV
Input Offset Voltage Drift	$V_{OS, TC, VO_{CM}}$	$T_A = 20^\circ\text{C} \text{ to } 85^\circ\text{C}$		$\pm 5$			$\pm 5$		$\mu\text{V}/^\circ\text{C}$
		$T_A = -40^\circ\text{C} \text{ to } +125^\circ\text{C}$		$\pm 10$			$\pm 10$		$\mu\text{V}/^\circ\text{C}$
Input Bias Current	$I_{B, VO_{CM}}$	$T_A = 25^\circ\text{C}$		-220			-160		nA
		$T_A = 20^\circ\text{C} \text{ to } 85^\circ\text{C}$		-300			-205		nA
		$T_A = -40^\circ\text{C} \text{ to } +125^\circ\text{C}$		-350			-230		nA
Input Bias Current Drift	$I_{B, TC, VO_{CM}}$	$T_A = 20^\circ\text{C} \text{ to } 85^\circ\text{C}$		-1.3			-0.75		nA/ $^\circ\text{C}$
		$T_A = -40^\circ\text{C} \text{ to } +125^\circ\text{C}$		-1.5			-1.0		nA/ $^\circ\text{C}$
CMRR	$CMRR_{VO_{CM}}$	$\Delta V_{OS, dm} / \Delta V_{OCM}, \Delta V_{OCM} = \pm 1 \text{ V}$		-130			-130		dB

Table 9. General Performance

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
CLAMP									
Clamp Output Voltage		Differential	$-V_S$ -0.5		$+V_S$ +0.5	$-V_S$ -0.5		$+V_S$ +0.5	V
		Common mode	$-V_S$		$+V_S$	$-V_S$		$+V_S$	V
Recovery Time				100			100		ns
Input Resistance		Resistance between $+V_{CLAMP}$ and $-V_{CLAMP}$		480			480		k $\Omega$
DISABLE ( $\overline{DISABLE}$ PIN) MODE									
Input Voltage		Disabled	$-V_S$ -0.3		$D_{GND}$ +1	$-V_S$ -0.3		$D_{GND}$ +1	V
		Enabled	$D_{GND}$ +1.4		$+V_S$ +0.3	$D_{GND}$ +1.4		$+V_S$ +0.3	V
Turn Off Time	$t_{OFF}$	Quiescent current < 10% of enabled quiescent current		6			6		$\mu$ s
Turn On Time	$t_{ON}$	( $t_0$ ) > 90% of final $V_{OUT}$		1.2			2		$\mu$ s
$\overline{DISABLE}$ Pin Bias Current Enabled		$\overline{DISABLE} = 3$ V		50			50		nA
$\overline{DISABLE}$ Pin Bias Current Disabled		$\overline{DISABLE} = 0$ V		50			50		nA
$D_{GND}$ PIN									
VOLTAGE RANGE	$IV_{RDGND}$		$-V_S$		$+V_S$ -2.5	$-V_S$		$+V_S$ -2.5	V
POWER SUPPLY									
Operating Range	$\pm V_S$		3		10	3		10	V
Quiescent Current Enabled	$I_q$	Full power mode, MODE = $+V_S$		4	4.2				mA
		Low power mode, MODE = $-V_S$					1.4	1.6	mA
Quiescent Current Disabled		Full power mode, MODE = $+V_S$		60	70				$\mu$ A

PARAMETER	SYMBOL	TEST CONDITIONS/COMMENTS	FULL POWER MODE			LOW POWER MODE			UNIT
			MIN	TYP	MAX	MIN	TYP	MAX	
Quiescent Current Disabled		Low power mode, MODE = -V <sub>S</sub>					60	70	μA
+PSRR	+PSRR	$\Delta V_{OS, dm} / \Delta V_S, \Delta V_S = 1 \text{ V p-p}$		-120			-120		dB
-PSRR	-PSRR	$\Delta V_{OS, dm} / \Delta V_S, \Delta V_S = 1 \text{ V p-p}$		-120			-120		dB
OPERATING TEMPERATURE RANGE			-40		+125	-40		+125	°C

## ABSOLUTE MAXIMUM RATINGS

$T_A = 25^\circ\text{C}$  unless otherwise specified.

**Table 10. Absolute Maximum Ratings**

PARAMETER	RATING
Supply Voltage	11V
$V_{OCM}$	$\pm V_S$
Differential Input Voltage	$\pm 1\text{V}$
Operating Temperature Range	$-40^\circ\text{C}$ to $+125^\circ\text{C}$
Storage Temperature Range	$-65^\circ\text{C}$ to $+150^\circ\text{C}$
Lead Temperature (Soldering, 10 sec)	$300^\circ\text{C}$
Junction Temperature	$150^\circ\text{C}$
Electrostatic Discharge (ESD) Field Induced Charged Device Model (FICDM)	1250V
Electrostatic Discharge (ESD) Human Body Model (HBM)	4000V

Stresses at or above those listed under Absolute Maximum Ratings may cause permanent damage to the product. This is a stress rating only; functional operation of the product at these or any other conditions above those indicated in the operational section of this specification is not implied. Operation beyond the maximum operating conditions for extended periods may affect product reliability.

## Thermal Resistance

Thermal performance is directly linked to printed circuit board (PCB) design and operating environment. Careful attention to PCB thermal design is required.

$\theta_{JA}$  is the natural convection, junction to ambient, thermal resistance measured in a one cubic foot sealed enclosure.  $\theta_{JC}$  is the junction to case thermal resistance.

**Table 11. Thermal Resistance**

Package Type	$\theta_{JA}$	$\theta_{JC}$	Unit
CP-16-22	70	15	$^\circ\text{C}/\text{W}$

## Maximum Power Dissipation

The maximum safe power dissipation in the ADA4945-1 package is limited by the associated rise in junction temperature ( $T_J$ ) on the die. At approximately  $150^\circ\text{C}$ , which is the glass transition temperature, the properties of the plastic change. Even temporarily exceeding this temperature limit can change the stresses that the package exerts on the die, permanently shifting the parametric performance of ADA4945-1. Exceeding a junction temperature of  $150^\circ\text{C}$  for an extended period can result in changes in the silicon devices, potentially causing failure.

The power dissipated in the package (PD) is the sum of the quiescent power dissipation and the power dissipated in the package due to the load drive for all outputs. The quiescent power dissipation is the voltage between the supply pins ( $\pm V_S$ ) times the quiescent current ( $I_Q$ ). The load current consists of the differential and common-mode currents

flowing to the load, as well as currents flowing through the external feedback networks and internal common-mode feedback loop. The internal resistor tap used in the common-mode feedback loop places a negligible differential load on the output. Consider RMS voltages and currents when dealing with ac signals.

Airflow reduces  $\theta_{JA}$ . In addition, more metal directly in contact with the package leads from metal traces through holes, ground, and power planes reduces the  $\theta_{JA}$ .

Figure 2 shows the maximum safe power dissipation in the package vs. the ambient temperature for the 16-lead LFCSP ( $\theta_{JA} = 70^\circ\text{C}/\text{W}$ ) package on a JEDEC standard 4-layer board.  $\theta_{JA}$  values are approximations.





Figure 2. Maximum Safe Power Dissipation vs. Ambient Temperature

## ESD Caution



**ESD (electrostatic discharge) sensitive device.** Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.

## PIN CONFIGURATIONS AND FUNCTION DESCRIPTIONS



## NOTES

1. EXPOSED PAD. CONNECT THE EXPOSED PAD TO  $-V_S$ . 005

Figure 3. Pin Configuration

Table 12. Pin Descriptions

PIN	NAME	DESCRIPTION
1	-FB	Negative Output for Feedback Component Connection.
2	+IN	Positive Input Summing Node.
3	-IN	Negative Input Summing Node.
4	+FB	Positive Output for Feedback Component Connection.
5	MODE	Selects Between Full Power Mode and Low Power Mode.
6	+V <sub>S</sub>	Positive Supply Voltage.
7		
8	+V <sub>CLAMP</sub>	Positive Clamp Level.
9	V <sub>OCM</sub>	Output Common-Mode Voltage.
10	+OUT	Positive Output for Load Connection.
11	-OUT	Negative Output for Load Connection.
12	DISABLE	Disable Pin.
13	-V <sub>CLAMP</sub>	Negative Clamp Level.
14	-V <sub>S</sub>	Negative Supply Voltage.
15		
16	D <sub>GND</sub>	Digital Ground Level.
	Exposed pad (EPAD)	Exposed Pad. Connect the exposed pad to $-V_S$ .

## TYPICAL PERFORMANCE CHARACTERISTICS (FULL POWER MODE)

( $T_A = +25^\circ\text{C}$ ,  $V_S = \pm 5\text{V}$ ,  $G = 1$ ,  $R_F = R_G = 499\ \Omega$ ,  $R_T = 53.6\ \Omega$  (when used), and  $R_L = 1\ \text{k}\Omega$ , unless otherwise noted. See Figure 94, Figure 95, Figure 96, and Figure 97 for the test circuits.)




Figure 4. Small Signal Frequency Response for Various Gains and Loads




Figure 7. Large Signal Frequency Response for Various Gains and Loads




Figure 5. Small Signal Frequency Response for Various Supplies




Figure 8. Large Signal Frequency Response for Various Supplies




Figure 6. Small Signal Frequency Response for Various Temperatures




Figure 9. Large Signal Frequency Response for Various Temperatures






Figure 10. Small Signal Frequency Response at Various  $V_{OCM}$  Levels




Figure 13. 0.1 dB Flatness Small Signal Frequency Response for Various Gains and Loads




Figure 11. Large Signal Frequency Response at Various  $V_{OCM}$  Levels




Figure 14.  $V_{OCM}$  Small Signal Frequency Response




Figure 12. Small Signal Frequency Response for Various Capacitive Loads




Figure 15. Large Signal Frequency Response for Various Capacitive Loads




Figure 16. 0.1 dB Flatness Large Signal Frequency Response for Various Gains and Loads




Figure 17.  $V_{OCM}$  Large Signal Frequency Response




Figure 18. Input Offset Voltage vs. Temperature for 50 Devices




Figure 19. Input Offset Current vs. Temperature for 30 Devices




Figure 20. Harmonic Distortion vs. Frequency for Various Loads




Figure 21. Harmonic Distortion vs. Frequency for Various Supplies




Figure 22. Harmonic Distortion vs. Frequency for Various Gains




Figure 25. Harmonic Distortion vs. Frequency for Various  $V_{OUT, dm}$




Figure 23. Harmonic Distortion vs.  $V_{OCM}$ ,  $f = 1 \text{ kHz}$ ,  $\pm 5 \text{ V}$  Supplies




Figure 26. Harmonic Distortion vs.  $V_{OUT, dm}$  for Various Supplies,  $f = 1 \text{ kHz}$




Figure 24. Harmonic Distortion vs.  $V_{OCM}$ ,  $f = 1 \text{ kHz}$ ,  $\pm 2.5 \text{ V}$  Supplies




Figure 27. Harmonic Distortion vs. Frequency for Various  $R_F$  and  $R_G$  Values




Figure 28. CMRR vs. Frequency




Figure 31. Open-Loop Gain and Phase vs. Frequency




Figure 29. Output Balance vs. Frequency




Figure 32. Output Overdrive Recovery,  $G = 2$




Figure 30. PSRR vs. Frequency




Figure 33. Voltage Noise Spectral Density, Referred to Input




Figure 34. Input Current Noise Spectral Density




Figure 37. Closed-Loop Output Impedance Magnitude vs. Frequency,  $G = 1$




Figure 35.  $\overline{DISABLE}$  Pin Turn-Off Time




Figure 38.  $\overline{DISABLE}$  Pin Turn-On Time




Figure 36. 0.1% Settling Time




Figure 39. Small Signal Transient Response for Various Gains and Loads




Figure 40. Small Signal Transient Response for Various Capacitive Loads,  $V_S = 10V$




Figure 43. Large Signal Transient Response for Various Gains and Loads




Figure 41. Small Signal Transient Response for Various Capacitive Loads,  $V_S = 5V$




Figure 44. Large Signal Transient Response for Various Capacitive Loads,  $V_S = 10V$




Figure 42. Small Signal Transient Response for Various Capacitive Loads,  $V_S = 3V$




Figure 45. Large Signal Transient Response for Various Capacitive Loads,  $V_S = 5V$




Figure 46. Large Signal Transient Response for Various Capacitive Loads,  $V_S=3\text{V}$




Figure 48.  $V_{OCM}$  Large Signal Transient Response




Figure 47.  $V_{OCM}$  Small Signal Transient Response

TYPICAL PERFORMANCE CHARACTERISTICS (LOW POWER MODE)




Figure 49. Small Signal Frequency Response for Various Gains and Loads




Figure 52. Large Signal Frequency Response for Various Gains and Loads




Figure 50. Small Signal Frequency Response for Various Supplies




Figure 53. Large Signal Frequency Response for Various Supplies




Figure 51. Small Signal Frequency Response for Various Temperatures




Figure 54. Large Signal Frequency Response for Various Temperatures






Figure 55. Small Signal Frequency Response at Various  $V_{OCM}$  Levels




Figure 58. 0.1 dB Flatness Small Signal Frequency Response for Various Gains and Loads




Figure 56. Large Signal Frequency Response at Various  $V_{OCM}$  Levels




Figure 59.  $V_{OCM}$  Small Signal Frequency Response




Figure 57. Small Signal Frequency Response for Various Capacitive Loads




Figure 60. Large Signal Frequency Response for Various Capacitive Loads




Figure 61. 0.1 dB Flatness Large Signal Frequency Response for Various Gains and Loads




Figure 64. Input Offset Current vs. Temperature for 30 Devices




Figure 62.  $V_{OCM}$  Large Signal Frequency




Figure 65. Harmonic Distortion vs. Frequency for Various Loads




Figure 63. Input Offset Voltage vs. Temperature for 50 Devices




Figure 66. Harmonic Distortion vs. Frequency for Various Supplies




Figure 67. Harmonic Distortion vs. Frequency for Various Gains




Figure 70. Harmonic Distortion vs. Frequency for Various  $V_{OUT, dm}$




Figure 68. Harmonic Distortion vs.  $V_{OCM}$ ,  $f = 1 \text{ kHz}$ ,  $\pm 5 \text{ V}$  Supplies




Figure 71. Harmonic Distortion vs.  $V_{OUT, dm}$  for Various Supplies,  $f = 1 \text{ kHz}$




Figure 69. Harmonic Distortion vs.  $V_{OCM}$ ,  $f = 1 \text{ kHz}$ ,  $\pm 2.5 \text{ V}$  Supplies




Figure 72. Harmonic Distortion vs. Frequency for Various  $R_F$  and  $R_G$  Values




Figure 73. CMRR vs. Frequency

049




Figure 76. Open-Loop Gain and Phase vs. Frequency

051




Figure 74. Output Balance vs. Frequency

028




Figure 77. Output Overdrive Recovery, G = 2

031




Figure 75. PSRR vs. Frequency

050




Figure 78. Voltage Noise Spectral Density, Referred to Input

276




Figure 79. Current Noise Spectral Density




Figure 82. Closed-Loop Output Impedance Magnitude vs. Frequency,  $G = 1$




Figure 80.  $\overline{\text{DISABLE}}$  Pin Turn-Off Time




Figure 83.  $\overline{\text{DISABLE}}$  Pin Turn-On Time




Figure 81. 0.1% Settling Time




Figure 84. Small Signal Transient Response for Various Gains and Loads




Figure 85. Small Signal Transient Response for Various Capacitive Loads,  $V_S = 10V$




Figure 88. Large Signal Transient Response for Various Gains and Loads




Figure 86. Small Signal Transient Response for Various Capacitive Loads,  $V_S = 5V$




Figure 89. Large Signal Transient Response for Various Capacitive Loads,  $V_S = 10V$




Figure 87. Small Signal Transient Response for Various Capacitive Loads,  $V_S = 3V$




Figure 90. Large Signal Transient Response for Various Capacitive Loads,  $V_S = 5V$




Figure 91. Large Signal Transient Response for Various Capacitive Loads,  $V_S=3V$




Figure 93.  $V_{OCM}$  Large Signal Transient Response





Figure 92.  $V_{OCM}$  Small Signal Transient Response

TEST CIRCUITS



► Figure 94. Equivalent Basic Test Circuit




Figure 95. Test Circuit for Distortion Measurements




Figure 96. Test Circuit for *DISABLE* Pin Turn Off Time Measurement




Figure 97. Test Circuit for *DISABLE* Pin Turn On Time Measurement



## TERMINOLOGY

### Differential Voltage

Differential voltage is the difference between two node voltages. For example, the differential output voltage (or equivalently, output differential mode voltage) is defined as

$$V_{OUT, dm} = (V_{+OUT} - V_{-OUT})$$

where  $V_{+OUT}$  and  $V_{-OUT}$  refer to the voltages at the +OUT and -OUT terminals with respect to a common reference. Similarly, the differential input voltage is defined as

$$V_{IN, dm} = (+D_{IN} - (-D_{IN}))$$

### Common-Mode Voltage (CMV)

CMV is the average of two node voltages. The output common mode voltage is defined as

$$V_{OUT, cm} = (V_{+OUT} + V_{-OUT})/2$$

Similarly, the input common-mode voltage is defined as

$$V_{IN, cm} = (+D_{IN} + (-D_{IN}))/2$$

### Common-Mode Offset Voltage

Common-mode offset voltage is the difference between the voltage applied to the V<sub>OCM</sub> terminal and the common mode of the output voltage.

$$V_{OS, cm} = V_{OUT, cm} - V_{OCM}$$

### Differential V<sub>OS</sub>, Differential CMRR, and V<sub>OCM</sub> CMRR

The differential mode and common-mode voltages each have their own error sources. The differential offset ( $V_{OS, dm}$ ) is the voltage error between the +IN and -IN terminals of the amplifier. Differential CMRR reflects the change of  $V_{OS, dm}$  in response to changes to the common-mode voltage at +D<sub>IN</sub> and -D<sub>IN</sub> (see Figure 98).

$$CMRR_{DF} = \frac{\Delta V_{IN, cm}}{\Delta V_{OS, dm}}$$


$V_{OCM}$  CMRR reflects the change of  $V_{OS, dm}$  in response to changes to the common-mode voltage at the output terminals.

$$CMRR_{V_{OCM}} = \frac{\Delta V_{OCM}}{\Delta V_{OS, dm}}$$

## Balance

Balance is a measure of how well the differential signals are matched in amplitude. The differential signals are exactly 180° apart in phase. By this definition, the output balance is the magnitude of the output common-mode voltage divided by the magnitude of the output differential mode voltage.

$$\text{Output Balance Error} = \left| \frac{V_{\text{OUT,cm}}}{V_{\text{OUT,dm}}} \right|$$



**Figure 98. Circuit Definitions**

014

## THEORY OF OPERATION




Figure 99. ADA4945-1 Architectural Block Diagram

The ADA4945-1 is a high speed, low power differential amplifier fabricated on Analog Devices advanced dielectrically isolated SiGe bipolar process. The device provides two closely balanced differential outputs in response to either differential or single-ended input signals. An external feedback network that is similar to a voltage feedback operational amplifier sets the differential gain. The output common-mode voltage is independent of the input common-mode voltage and is set by an external voltage at the  $V_{OCM}$  terminal. The PNP input stage allows input common-mode voltages between the negative supply and 1.3 V less than the positive supply. A rail-to-rail output stage supplies a wide output voltage range. The  $\overline{DISABLE}$  pin can reduce the supply current ( $I_q$ ) of the amplifier to 50  $\mu\text{A}$ .

### Fully Differential and Common-Mode Signal Paths

Figure 99 shows a simplified diagram of the ADA4945-1 architecture. The differential feedback loop consists of the differential transconductance ( $G_{DIFF}$ ) working through the  $G_O$  output buffers and the  $R_F/R_G$  feedback networks. The common-mode feedback loop is set up with a voltage divider across the two differential outputs to create an output voltage midpoint ( $V_{OUT(CM)}$ ) and a common-mode transconductance ( $G_{CM}$ ).

The differential feedback loop forces the voltages at +IN and -IN to equal each other. This voltage equalization sets the following relationships:

$$\frac{+D_{IN}}{R_G} = -\frac{V_{-OUT}}{R_F}$$

$$\frac{-D_{IN}}{R_G} = -\frac{V_{+OUT}}{R_F}$$

Subtracting the previous equations gives the relationship that shows  $R_F$  and  $R_G$  setting the differential gain.

$$(V_{+OUT} - V_{-OUT}) = (+D_{IN} - (-D_{IN})) \times \frac{R_F}{R_G}$$

The common-mode feedback loop drives the output common mode voltage that is sampled at the midpoint of the output voltage divider to equal the voltage at  $V_{OCM}$ . This voltage equalization results in the following relationships:

$$V_{+OUT} = V_{OCM} + \frac{V_{OUT,dm}}{2}$$

$$V_{-OUT} = V_{OCM} - \frac{V_{OUT,dm}}{2}$$

Note that the summing junction input voltages of the differential amplifier (+IN and -IN in Figure 99) are set by both the output voltages and the input voltages.


$$V_{+IN} = +D_{IN} \left( \frac{R_F}{R_F + R_G} \right) + V_{-OUT} \left( \frac{R_G}{R_F + R_G} \right)$$

$$V_{-IN} = -D_{IN} \left( \frac{R_F}{R_F + R_G} \right) + V_{+OUT} \left( \frac{R_G}{R_F + R_G} \right)$$

## Output Voltage Clamp


In addition to the differential and common-mode signal paths, the ADA4945-1 implements clamping circuits to protect the input devices of circuits being driven by the ADA4945-1, hereafter assumed to be an ADC, from being overdriven and potentially damaged. These clamping circuits use both differential and common-mode feedback to limit the output voltages to a range defined by the voltage applied to two reference pins,  $+V_{CLAMP}$  and  $-V_{CLAMP}$ . These high impedance pins are typically connected to potentials that define the allowable input range of the ADC, which are the ADC reference voltages ( $+V_{REF}$  and  $-V_{REF}$ ) for most ADCs.

As shown in Figure 100, the common-mode clamping circuit senses the output voltage midpoint and applies a common mode feedback signal to prevent  $V_{OUT, cm}$  from exceeding  $+V_{CLAMP}$  or going below  $-V_{CLAMP}$ .



**Figure 100. Common-Mode Clamp Block Diagram**

The differential clamping circuit, shown in Figure 101, senses each output (+OUT and -OUT) and applies a differential feedback signal to prevent either output from exceeding  $(+V_{CLAMP} + 0.5 \text{ V})$  or going below  $(-V_{CLAMP} - 0.5 \text{ V})$ . The approximately 500 mV offset voltage is designed to allow the outputs to fully use the input range of the ADC without any clamp engagement, while providing input protection prior to the turn on of the ADC input protection diodes. This feature allows the ADA4945-1 to provide a full-scale signal to the ADC without incurring any clamp induced distortion, thus maximizing signal-to-noise ratio (SNR) and linearity while protecting the ADC inputs.



**Figure 101. Differential Clamp Block Diagram**

By applying a differential feedback signal in response to one or both outputs exceeding the clamp reference voltages, both outputs are limited equally, even if only one output exceeds one of the clamp reference voltages. This feature allows the ADA4945-1 to maintain a constant output common-mode voltage even while clamping the differential outputs, which enables a faster system recovery from a clamped condition.

In systems where output clamping is not desired, the upper output clamp can be disabled by connecting  $+V_{CLAMP}$  to  $+V_S$ , and the lower output clamp can be disabled by connecting  $-V_{CLAMP}$  to  $-V_S$ . If one clamp is disabled (for example,  $-V_S = -V_{CLAMP} = 0\text{ V}$ ), the other can remain active, and the output is limited when either or both outputs reaches the active clamp reference.

An additional feature of the ADA4945-1 is the use of a resistor divider between the  $+V_{CLAMP}$  and  $-V_{CLAMP}$  pins, as shown in Figure 99, to set the default potential on the  $V_{OCM}$  pin when the pin is not externally driven. Because the  $+V_{CLAMP}$  and  $-V_{CLAMP}$  pins are typically set to the maximum and minimum desired input voltage of the ADC (for example,  $+V_{REF}$  and  $-V_{REF}$ ), respectively, this resistor divider sets the output common-mode voltage of the ADA4945-1 at the midpoint of the ADC input range by default. By contrast, most fully-differential amplifiers use a resistor divider between the amplifier supply voltages to set the default output common-mode voltage, which may not be optimal for maximizing ADC input range usage.

## Power Modes

The ADA4945-1 implements two fully characterized active power modes (full power, low power) and a disable mode to optimize system power and performance trade-offs. The transition time from disable mode to either of the active power modes is fast ( $<2\mu\text{s}$ ), allowing additional power savings by dynamically placing the ADA4945-1 in disable mode when the output voltage is not needed (for example, between ADC samples in low data rate systems).

## APPLICATIONS INFORMATION

### Analyzing an Application Circuit

The ADA4945-1 uses open-loop gain and negative feedback to force the differential and common-mode output voltages to minimize the differential and common-mode error voltages. The differential error voltage is the voltage between the differential inputs labeled +IN and -IN (see Figure 98). For most purposes, this voltage is 0 V. Similarly, the difference between the actual output common-mode voltage and the voltage applied to  $V_{OCM}$  is also 0 V. Starting from these two assumptions, any application circuit can be analyzed.

### Setting the Closed-Loop Gain

Determine the differential mode gain of the circuit in Figure 98 by using the following equation:

$$\left| \frac{V_{OUT,dm}}{V_{IN,dm}} \right| = \frac{R_F}{R_G}$$

This calculation assumes that the input resistors ( $R_G$ ) and feedback resistors ( $R_F$ ) on each side are equal.

### Estimating the Output Noise Voltage

The differential output noise of the ADA4945-1 can be estimated by using the noise model in Figure 102. The input-referred noise voltage density,  $v_{nIN}$ , is modeled as a differential input, and the noise currents,  $i_{nIN-}$  and  $i_{nIN+}$ , appear between each input and ground. The noise currents are assumed equal and produce a voltage across the parallel combination of the gain and feedback resistances.  $v_{nCM}$  is the noise voltage density at the  $V_{OCM}$  pin. Each of the four resistors contributes  $(4kTR_x)^{1/2}$ . Table 13 summarizes the input noise sources, the multiplication factors, and the output referred noise density terms. For more noise calculation information, go to the Analog Devices Differential Amplifier Calculator ([DiffAmpCalc™](#)), click ADIDiffAmpCalculator.zip, and follow the on-screen prompts.




Figure 102. ADA4945-1 Noise Model

As with conventional op amps, the output noise voltage densities can be estimated by multiplying the input referred terms at +IN and -IN by the appropriate output factor, where:

$$G_N = \frac{2}{(\beta_1 + \beta_2)} \text{ is the circuit noise gain.}$$

$$\beta_1 = \frac{R_{G1}}{R_{F1} + R_{G1}} \text{ and } \beta_2 = \frac{R_{G2}}{R_{F2} + R_{G2}}$$

are the feedback factors. When  $R_{F1}/R_{G1} = R_{F2}/R_{G2}$ , then  $\beta_1 = \beta_2 = \beta$ , and the noise gain becomes

$$G_N = \frac{1}{\beta} = 1 + \frac{R_F}{R_G}$$

Note that the output noise from  $V_{OCM}$  goes to zero in this case. The total differential output noise density,  $v_{nOD}$ , is the root-sum square of the individual output noise terms

$$v_{nOD} = \sqrt{\sum_{i=1}^8 v_{nOi}^2}$$

**Table 13. Output Noise Voltage Density Calculations**

Input Noise Contribution	Input Noise Term	Input Noise Voltage Density	Output Multiplication Factor	Output-Referred Noise Voltage Density Term
Differential Input	$v_{nIN}$	$v_{nIN}$	$G_N$	$v_{nO1} = G_N (v_{nIN})$
Inverting Input	$i_{nIN-}$	$i_{nIN-} \times (R_{G2}    R_{F2})$	$G_N$	$v_{nO2} = G_N [i_{nIN-} \times (R_{G2}    R_{F2})]$
Noninverting Input	$i_{nIN+}$	$i_{nIN+} \times (R_{G1}    R_{F1})$	$G_N$	$v_{nO3} = G_N [i_{nIN+} \times (R_{G1}    R_{F1})]$
$V_{OCM}$ Input	$v_{nCM}$	$v_{nCM}$	$G_N (\beta_1 - \beta_2)$	$v_{nO4} = G_N (\beta_1 - \beta_2) (v_{nCM})$
Gain Resistor, $R_{G1}$	$v_{nRG1}$	$(4kTR_{G1})^{1/2}$	$G_N (1 - \beta_2)$	$v_{nO5} = G_N (1 - \beta_2) (4kTR_{G1})^{1/2}$
Gain Resistor, $R_{G2}$	$v_{nRG2}$	$(4kTR_{G2})^{1/2}$	$G_N (1 - \beta_1)$	$v_{nO6} = G_N (1 - \beta_1) (4kTR_{G2})^{1/2}$
Feedback Resistor, $R_{F1}$	$v_{nRF1}$	$(4kTR_{F1})^{1/2}$	1	$v_{nO7} = (4kTR_{F1})^{1/2}$
Feedback Resistor, $R_{F2}$	$v_{nRF2}$	$(4kTR_{F2})^{1/2}$	1	$v_{nO8} = (4kTR_{F2})^{1/2}$

## Impact of Mismatches in the Feedback Networks

Even if the external feedback networks ( $R_F/R_G$ ) are mismatched, the internal common-mode feedback loop still forces the outputs to remain balanced. The amplitudes of the signals at each output remain equal and 180° out of phase. The input-to-output, differential mode gain varies proportionately to the feedback mismatch, but the output balance is unaffected.

As well as causing a noise contribution from  $V_{OCM}$ , ratio matching errors in the external resistors result in a degradation of the ability of the circuit to reject input common-mode signals, similar to a four resistors difference amplifier made from a conventional op amp.

In addition, if the dc levels of the input and output common mode voltages are different, matching errors result in a small differential mode, output offset voltage. When  $G = 1$ , with a ground referenced input signal and the output common-mode level set to 2.5 V, an output offset of as much as 25 mV (1% of the difference in common-mode levels) can result if 1% tolerance resistors are used. Resistors of 1% tolerance result in a worst case input CMRR of about 40 dB, a worst case differential mode output offset of 25 mV due to the 2.5 V level shift, and no significant degradation in output balance error.

## Calculating the Input Impedance of an Application Circuit

The effective input impedance depends on whether the signal source is single-ended or differential. For a balanced differential input signal, as shown in Figure 103, the input impedance ( $R_{IN, dm}$ ) between the inputs ( $+D_{IN}$  and  $-D_{IN}$ ) is  $R_{IN, dm} = 2 \times R_G$ .




Figure 103. ADA4945-1 Configured for Balanced (Differential) Inputs

For an unbalanced single-ended input signal, as shown in Figure 104, the input impedance is

$$R_{IN,SE} = R_{G1} \frac{\beta_1 + \beta_2}{\beta_1(\beta_2 + 1)}$$

where:

$$\beta_1 = \frac{R_{G1}}{R_{G1} + R_{F1}}$$

$$\beta_2 = \frac{R_{G2}}{R_{G2} + R_{F2}}$$




Figure 104. ADA4945-1 with Unbalanced (Single-Ended) Input

For a balanced system where  $R_{G1} = R_{G2} = R_G$  and  $R_{F1} = R_{F2} = R_F$ , the equations simplify to

$$\beta_1 = \beta_2 = \frac{R_G}{R_G + R_F} \text{ and } R_{IN,SE} = \left( \frac{R_G}{1 - \frac{R_F}{2(R_G + R_F)}} \right)$$

The input impedance of the circuit is effectively higher than it would be for a conventional op amp connected as an inverter because a fraction of the differential output voltage appears at the inputs as a common-mode signal, partially bootstrapping the voltage across the  $R_{G1}$  input resistor.

## Terminating a Single-Ended Input

This section describes how to properly terminate a single-ended input to the ADA4945-1. Assume a system gain of 1 where  $R_{F1} = R_{F2} = R_{G1} = R_{G2} = 499 \Omega$ , an input source with an open-circuit output voltage of  $2V_{p-p}$ , and a source resistance of  $50 \Omega$ . Figure 105 shows the circuit.

1. Calculate the input impedance.

$$\beta_1 = \beta_2 = 499/998 = 0.5 \text{ and } R_{IN} = 665.33 \Omega$$






Figure 105. Single-Ended Input Impedance  $R_{IN}$

2. Add a termination resistor ( $R_T$ ) to match the 50  $\Omega$  source resistance. Because  $R_T || 665.33 \Omega = 50 \Omega$ ,  $R_T = 54.06 \Omega$ .




Figure 106. Adding Termination Resistor,  $R_T$

3. Replace the source termination resistor combination with the Thevenin equivalent. The Thevenin equivalent of the source resistance,  $R_S$ , and the termination resistance,  $R_T$ , is  $R_{TH} = R_S || R_T = 25.976 \Omega$ . The Thevenin equivalent of the source voltage is

$$V_{TH} = V_S \frac{R_T}{R_S + R_T} = 1.039 V_{p-p}$$




Figure 107. Thevenin Equivalent Circuit

4. Set  $R_{F1} = R_{F2} = R_F$  to maintain a balanced system. Compensate the imbalance caused by  $R_{TH}$ . There are two methods available to compensate, as follows:
  - Add  $R_{TH}$  to  $R_{G2}$  to maintain balanced gain resistances and increase  $R_{F1}$  and  $R_{F2}$  to  $R_F = \frac{V_S}{V_{TH}} \text{Gain}(R_G + R_{TH})$  to maintain the system gain.
  - Decrease  $R_{G2}$  to  $R_{G2} = \frac{R_F \times V_{TH}}{V_S \times \text{Gain}}$  to maintain system gain and decrease  $R_{G1}$  to  $(R_{G2} - R_{TH})$  to maintain balanced gain resistances.

The first compensation method is used in the Analog Devices [DiffAmpCalc™](#) tool. Using the second compensation method,  $R_{G2} = 259.241 \Omega$  and  $R_{G1} = 259.241 - 25.976 = 233.265 \Omega$ . The modified circuit is shown in Figure 108




Figure 108. Thevenin Equivalent with Matched Gain Resistors

Figure 108 shows an easily manageable circuit with matched feedback loops that can be easily evaluated.

- The modified gain resistor,  $R_{G1}$ , changes the input impedance. Repeat Step 1 through Step 4 several times using the modified value of  $R_{G1}$  from the previous iteration until the value of  $R_T$  does not change from the previous iteration. After three additional iterations, the change in  $R_{G1}$  is less than 0.1%. The final circuit is shown in Figure 109 with the closest 1% resistor values.




Figure 109. Terminated Single-Ended-to-Differential System with  $G=1$

## Input Common-Mode Voltage Range

The input common-mode range at the summing nodes of the ADA4945-1 is specified as  $-V_S$  to  $+V_S - 1.3V$ . By extending the input common-mode range down to  $-V_S$ , the ADA4945-1 is especially well suited to dc-coupled, single-ended-to-differential, and single-supply applications, such as ADC driving.

## Input and Output Capacitive AC Coupling

Although the ADA4945-1 is best suited to dc-coupled applications, it is possible to use the device in ac-coupled circuits. Input ac coupling capacitors can be inserted between the source and  $R_G$ . This ac coupling blocks the flow of the dc common-mode feedback current and causes the ADA4945-1 dc input common-mode voltage to equal the dc output common-mode voltage. These ac coupling capacitors must be placed in both loops to keep the feedback factors matched. Output ac coupling capacitors can be placed in series between each output and the respective load of each output.

## Setting the Output Common-Mode Voltage

The  $V_{OCM}$  pin of the ADA4945-1 is internally biased at a voltage approximately equal to the midway between the output voltage clamps,  $((+V_{CLAMP}) + (-V_{CLAMP}))/2$ . Relying on this internal bias results in an output common-mode voltage that is within approximately 100 mV of the expected value.

When more accurate control of the output common-mode level is required, it is recommended that an external source, or resistor divider (10 k $\Omega$  or greater resistors), be used. The output common-mode offset listed in Table 2, Table 5, and Table 8 assumes that the  $V_{OCM}$  input is driven by a low impedance voltage source.

It is also possible to connect the  $V_{OCM}$  input to a common-mode level (CML) output of an ADC. However, care must be taken to ensure that the output has sufficient drive capability. The input impedance of the  $V_{OCM}$  pin is approximately 125 k $\Omega$ .

## Disable Pin

The ADA4945-1 features a  $\overline{DISABLE}$  pin that can be used to minimize the quiescent current consumed when the device is not being used.  $\overline{DISABLE}$  is asserted by applying a low logic level to the  $\overline{DISABLE}$  pin. The logic level for the  $\overline{DISABLE}$  pin is referenced to  $D_{GND}$ . See Table 3, Table 6, and Table 9 for the threshold limits.

The  $\overline{DISABLE}$  pin features an internal pull-up network that enables the amplifier for normal operation. The ADA4945-1  $\overline{DISABLE}$  pin can be left floating (that is, no external connection is required) and does not require an external pullup resistor to ensure normal on operation (see Figure 110). When the ADA4945-1 is disabled, the output is high impedance. Note that the outputs are tied to the inputs through the feedback resistors and to the source using the gain resistors. In addition, there are back to back diodes on the input pins that limit the differential voltage to 1.2 V.




Figure 110.  $\overline{DISABLE}$  Pin Circuit

## Driving a Capacitive Load

A purely capacitive load reacts with the bond wire and pin inductance of the ADA4945-1, resulting in high frequency ringing in the transient response and loss of phase margin. One way to minimize this effect is to place a resistor in series with each output to buffer the load capacitance. The resistor and load capacitance form a first-order, low-pass filter. Therefore, the resistor value must be as small as possible. In some cases, the ADCs require small series resistors to be added on their inputs.

Figure 111 shows the capacitive load vs. the series resistance required to maintain a minimum 45° of phase margin. The test circuit is shown in Figure 112.




Figure 111. Series Resistance vs. Load Capacitance




Figure 112. Series Resistance with a Capacitive Load Test Circuit

### Output Clamps

The ADA4945-1 implements output voltage clamps to effectively limit the differential and common-mode signal levels, thereby protecting circuitry following the ADA4945-1 from being overdriven. The operation of these clamps is discussed in the Theory of Operation section. Figure 113 shows an example where the output voltage clamp may be used while driving an ADC. In this example, the ADA4945-1 is operating from +7 V and -2 V supplies, and the ADC is using +5 V reference. In such a scenario, the ADC input can potentially be overdriven if no clamping were present. By connecting the clamps to the positive and negative references of the ADC, the differential and common-mode signal levels are limited as shown in Figure 114 and Figure 115. Note that the differential signals are clamped ~500 mV beyond the clamp set voltage to allow full swing to the references. The common-mode signal is clamped right at the clamp set voltages.




Figure 113. ADA4945-1 Output Voltage Clamp Usage




Figure 114. Clamped Differential Signal Levels




Figure 115. Clamped Common-Mode Signal Levels

## Driving a High Precision ADC

The ADA4945-1 is ideally suited for broadband dc-coupled applications. The recommended list of precision converters is shown in Table 15. The circuit in Figure 116 shows an example of the ADA4945-1 driving a precision ADC such as the AD4003 (an 18-bit, 2 MSPS, successive approximation ADC), or the AD7768 (a 24-bit, 256 kSPS, sigma-delta ADC). The ADA4945-1 is dc-coupled on the input and the output, which eliminates the need for a transformer to drive the ADC. In this example, the ADA4945-1 is applied in a differential input to differential output configuration, with a gain of 1, and with dual supplies of +7 V and -2 V. The output of the ADA4945-1 is level shifted to match the input common mode of the ADC. The gain is set by the ratio of the feedback resistor to the gain resistor. In addition, the circuit can be used in a single-ended input to differential output configuration. If needed, a termination resistor in parallel with the source input can be used. When a single-ended input is used, the input impedance of the amplifier can be calculated as shown in the Terminating a Single-Ended Input section. If the feedback and gain resistors are all 1 k $\Omega$ , as in Figure 116, the single-ended input impedance is approximately 1.33 k $\Omega$ , which, in parallel with a 52.3  $\Omega$  termination resistor, provides a 50  $\Omega$  termination for the source. An additional 25.5  $\Omega$  (1025.5  $\Omega$  total) at the inverting input balances the parallel impedance of the 50  $\Omega$  source and the termination resistor driving the noninverting input. However, if a differential source input is used, the differential input impedance is 2 k $\Omega$ . In this case, two 52.3  $\Omega$  termination resistors are used to terminate the inputs.

When driving the AD7768 in this example, the ADA4945-1 is driven by a signal generator having an 8 V<sub>p-p</sub> symmetric, bipolar output. The V<sub>OCM</sub> input of the ADA4945-1 is bypassed for noise reduction and is driven via the common-mode

source of the AD7768 to 2.5 V. With an output common-mode voltage of 2.5 V, each ADA4945-1 output swings between 0.5 V and 4.5 V, opposite in phase, providing a gain of 1 and a 8 V p-p differential signal to the ADC input. The differential RC section between the ADA4945-1 output and the ADC input provides a single-pole, low-pass filter to help reduce current spikes due to ADC input switching.

Table 14 shows the SNR and total distortion (THD) of the ADA4945-1 driving the AD7768 and AD4003 for various input frequencies at a near full-scale signal. The RC filter values in Figure 116 are also shown, as well as the reference voltage (REF) level.




Figure 116. ADA4945-1 Driving Precision ADC

Table 14. SNR and THD for ADA4945-1 Driving AD7768 and AD4003

ADC	Frequency (kHz)	Signal Level (V p-p)	REF (V)	R (Ω)	C (pF)	C <sub>DIFF</sub> (pF)	SNR (dB)	THD (dB)
AD7768	1	8.0	4.096	10	270	680	106.7	-115.9
	2	8.0	4.096	10	270	680	106.5	-115.5
	10	8.0	4.096	10	270	680	105.8	-116.9
	20	7.98	4.096	10	270	680	104.7	-116.2
AD4003	1	9.5	5.0	200	180	Not applicable	98.5	-123.5
	10	9.5	5.0	200	180	Not applicable	98.3	-117.0
	100	9.1	5.0	200	180	Not applicable	96.3	-100.3

**Table 15. Recommended Converters**

Product	Power (mW)	Throughput (MSPS)	Resolution (Bits)	SNR (dB)
<a href="#">AD4001</a>	16	2	16	96
<a href="#">AD4003</a>	16	2	18	100
<a href="#">AD4005</a>	8	1	16	96
<a href="#">AD4007</a>	8	1	18	100
<a href="#">AD4011</a>	4	0.5	18	100
<a href="#">AD4020</a>	20	2	20	100

## LAYOUT, GROUNDING, AND BYPASSING


As a high speed device, the ADA4945-1 is sensitive to the PCB environment in which it operates. Using the superior performance of the ADA4945-1 requires attention to the details of high speed PCB design.

Ensure that signal routing is short and direct to avoid parasitic effects. Wherever complementary signals exist, provide a symmetrical layout to maximize balanced performance. When routing differential signals over a long distance, ensure that PCB traces are close together, and twist any differential wiring such that loop area is minimized. This configuration reduces radiated energy and makes the circuit less susceptible to interference.

Bypass the power supply pins as near to the device as possible and directly to a nearby ground plane. Use high frequency ceramic chip capacitors. Use two parallel bypass capacitors (0.1  $\mu$ F and 10  $\mu$ F) for each supply. Place the 0.1  $\mu$ F capacitor as near to the device as possible. Further away, provide low frequency bypassing using 10  $\mu$ F tantalum capacitors from each supply to ground.

The ground plane must be as continuous and unbroken as possible to provide a low impedance path for return currents to the supply. As such, the ground plane should be kept free of any signal traces or other interruptions.

## OUTLINE DIMENSIONS



COMPLIANT TO JEDEC STANDARDS MO-220-WEED-6

**Figure 117. 16-Lead Lead Frame Chip Scale Package (LFCSP)  
3 mm x 3 mm Body and 0.75 mm Package Height  
(CP-16-22)**

*Dimensions shown in millimeters*

## ORDERING GUIDE

**Table 16. Ordering Guide**

Model <sup>1</sup>	Temperature Range	Package Description	Package Option	Ordering Quantity	Marking Code
ADA4945-1ACPZ-R2	-40°C to +125°C	16-Lead LFCSP	CP-16-22	250	C9D
ADA4945-1ACPZ-RL	-40°C to +125°C	16-Lead LFCSP	CP-16-22	5,000	C9D
ADA4945-1ACPZ-R7	-40°C to +125°C	16-Lead LFCSP	CP-16-22	1,500	C9D
ADA4945-1CP-EBZ		Evaluation Board			
AMC-ADA4945-1EBZ		ADC Mezzanine Card			

<sup>1</sup>Z = RoHS-compliant part.



ALL INFORMATION CONTAINED HEREIN IS PROVIDED “AS IS” WITHOUT REPRESENTATION OR WARRANTY. NO RESPONSIBILITY IS ASSUMED BY ANALOG DEVICES FOR ITS USE, NOR FOR ANY INFRINGEMENTS OF PATENTS OR OTHER RIGHTS OF THIRD PARTIES THAT MAY RESULT FROM ITS USE. SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE. NO LICENCE, EITHER EXPRESSED OR IMPLIED, IS GRANTED UNDER ANY ADI PATENT RIGHT, COPYRIGHT, MASK WORK RIGHT, OR ANY OTHER ADI INTELLECTUAL PROPERTY RIGHT RELATING TO ANY COMBINATION, MACHINE, OR PROCESS WHICH ADI PRODUCTS OR SERVICES ARE USED. TRADEMARKS AND REGISTERED TRADEMARKS ARE THE PROPERTY OF THEIR RESPECTIVE OWNERS.