



EKSELANS BY ITS

REPARTIDORES COM CONECTOR F RI 2 / RF 12 / RF 13 / RF 14 / RF 16 / RF 18

Blindagem classe A

Passagem DC em todas as saídas

5-2400 MHz

REFERÊNCIA		RI 2	RF 12	RF 13	RF 14	RF 16	RF 18
Código		141006	141001	141002	141003	141004	141005
Banda de passagem	MHz	5-2400	5-2400	5-2400	5-2400	5-2400	5-2400
Saídas	Nº	2	2	3	4	6	8
Perdas inserção	dB 860 MHz	4	4	7	8,1	11	12
	dB 2400 MHz	5,5	5,5	9,5	10	14,5	15,5
Isolamento entre as saídas	dB	>20	>20	>20	>20	>20	>20
Perdas de retorno	dB	>10	>10	>10	>10	>10	>10
Passagem de corrente	mA	800	800	800	800	800	800



RI 2



PMM

Proteção contra intempéries (opcional)

REFERÊNCIA		PMM
Código		024001



RF 12



RF 13 / RF 14



RF 16 / RF 18