



## Applications



Monuments



Fairgrounds



Facades










Historic buildings









Cultural spaces

## Specifications (Series luminaires)



	<b>Voltage (V)</b>	220-240V
Hz	<b>Frecuency (Hz)</b>	50-60Hz
	<b>Current (A)</b>	1.400mA
	<b>Power factor (Cos fi)</b>	0.97
	<b>Dimming</b>	DALI
	<b>IP Tightness index</b>	IP67
	<b>IK Impact resistance</b>	IK10
	<b>Body</b>	FE
	<b>CRI Colour rendering index</b>	>70

	<b>Measures</b>	233x94x165mm
	<b>Weight</b>	1.2Kg
	<b>Operating temperature</b>	-40~+40°C
	<b>Surges protection</b>	No
	<b>Electrical isolation</b>	CI
	<b>Lifetime</b>	L90B10>200.000h




Prilux guarantees a  $\pm 10\%$  tolerance in light flux measurements.

## Dimensions



## References



	<b>W</b>		
628501	58,8W	1400mA	Yes

## Accessories



**480307**

ACCESS. 3P TANEK  
ARCH CONNECTOR



**480291**

ACCESS. 2P TANEK  
ARCH CONNECTOR



**480635**

ACCES. SUPPORT  
BOX TANEK ARQ  
REMOTE



**628716**

CONNECTION KIT  
TANEK ARQ NEO  
REMOTE 5M



**628723**

CONNECTION KIT  
TANEK ARQ NEO  
REMOTE 10M



**628730**

CONNECTION KIT  
TANEK ARQ NEO  
REMOTE 20M

## Technologies



# Overstorm

### Overstorm



OVERSTORM technology is designed for those luminaires that normally face electrically aggressive environments. It provides the product with three spheres of protection: In the outer sphere, an independent surge protector suppresses eventual voltage surges, in the intermediate sphere the drivers are prepared to withstand voltage peaks of up to 6 kV and 10kV. In the nuclear sphere, the protection in the LED module is provided both at its input, for small surges that have not been filtered by the external spheres.

### Warning



The RSSY remote installation systems are indivisibly composed of HEXAGON RSSY floodlights connected to a POWER BOX(not included in the luminaire). The POWER BOX must be purchased separately. Check with your local sales representative for the best combination adapted to your installation.