

| | | |
|--------|---------------------------------------|-----------------|
| Baseus | 产品名称:倍思 Adaman金属数显快充移动电源 65W 30000mAh | 版本：P0A0 |
| | 包装编码：PB2961Z | 设计日期:2020-12-11 |
| | 说明书尺寸：60×120mm | 审核 :李洪良 |
| | 说明书材料：悦声臻品上质高白 100g 单色印刷 | |
| | 后道工艺： | 备注：产品图片颜色以实物为准。 |
| | 设计师:陈明斌 | |



60mm

120mm

Baseus倍思

倍思 Adaman金属数显快充移动电源 65W 20000mAh

使用说明书

声明

非常感谢您下选本产品!在使用本产品前,请先仔细阅读使用手册说明书.本手册的所有信息可能在没有通知情况下变更,本公司有权在任何时候,对信息作出改变,恕不另行通知。

1. 产品参数

名称：移动电源
型号：PPADM65
产品材质：铝合金+ABS
电池类型：聚合物锂电池
电池容量：5000mAh/14.8V/74Wh
额定容量：12000mAh(5V→6A)
能量转换率：≥75%
输入：
Micro：5V→2A, 9V→2A
Type-C: 5V→3A, 9V→3A, 12V→3A, 15V→3A, 20V→3A
输出：
USB1: 4.5V→5A (SCP), 5V→4.5A (SCP), 5V→3A, 9V→3A, 12V→2.5A
USB2: 5V→3A, 9V→3A, 12V→2.5A
Type-C: 5V→3A, 9V→3A, 12V→3A, 15V→3A, 20V→3.25A
USB1+USB2: 5V→3A
Type-C+USB1/USB2: 45W+18W
总5V输出：5V→6A
产品尺寸: 154*65*27mm
产品重量: 450g

*以上数据来源Baseus(倍思)实验室测定值,但因客观环境改变数据会有所不同或误差。

2. 包装清单

1. 移动电源

*1

2. 说明书

*1

3. 保修卡

*1

4. 充电线

*1

3. 产品线框图

屏幕

USB1 输出

USB2 输出

Micro 输入

Type-C 输出/输入

1

4. 产品描述

本产品是一款支持5A大电流,最大输出功率可达65W的超级快充移动电源,支持华为的SCP和FCP两种快充模式,同时符合PPS规范,支持IP12 20W PD快充,兼容支持PD3.0、QC4+、QC3.0、三星AFC等快充,产品具有电量、电压、电流数显,内置过流、过压、过温、短路保护等多重安全保护电路。

5. 产品使用说明

按键操作说明

1. 空载状态下,按键一次显示当前电量。

2. 负载状态下,按键一次显示当前电量、再次按键显示当前电压、再次按键显示当前电流。

3. 当有多个设备同时输出时,显示多设备输出总电流。

4. 当边输入边输出时,仅显示输入电压及电流。

充电操作说明

Adaman金属数显快充移动电源为手机或其它数码设备充电

1. 检查数码产品的充电电压是否与Adaman金属数显快充移动电源的输出电压匹配。

2. 选择数码产品的原装充电线,一端与数码产品连接,另一端与Adaman金属数显快充移动电源的输出口连接,Adaman金属数显快充移动电源将自动开启给数码产品充电,电量指示灯常亮。

用电源适配器/电脑USB端口给Adaman金属数显快充移动电源充电

1. 选择原装USB线,将Micro或Type-C的接头与Adaman金属数显快充移动电源的Micro或Type-C的输入端口连接。

2. 将USB充电线与充电器或电脑USB端口连接,LED电量指示灯开始闪烁,表示正在为Adaman金属数显快充移动电源充电,充满后LED灯常亮。

6.使用环境

使用环境温度: 0℃至40℃以下非热带地区

储存环境温度: 0℃至40℃。

7.安全警示说明

在使用本产品前请阅读所有的指示和警告,不规范使用将会给产品或人身安全带来损害。

1.移动电源存在转化效率,故移动电源电池容量不等于可充电量。

2.需要查看电量时,按一次电源键,LED指示灯亮起显示当前电量,无连接状态下,约30秒后电源会自动休眠。

3.请定期为您的电源充电(建议最少每5个月一次),可维持其长久的使用寿命。

4.产品使用不当,容易造成产品本身或者可能危及人身财产安全。

5.如因消费者违反产品说明书的不恰当使用或警示,造成的人身及财产损失将自行承担一切后果,本公司将不承担任何法律责任。

6.非专业人员严禁拆解本产品。

7.避免使用超出本产品输出电流的用电器或负载(电路会保护,无输出)。

8.避免强烈的物理作用,包括敲击、投掷、践踏、挤压等。

8. 电子信息产品有毒有害物质声明

| 部件名称 | 有毒有害物质或元素 ^① | | | | | |
|------|------------------------|--------|--------|-------------|------------|--------------|
| | 铅 (pb) | 汞 (Hg) | 镉 (Cd) | 六价铬 (Cr VI) | 多溴联苯 (PBB) | 多溴二苯醚 (PBDE) |
| PCB | X | ○ | ○ | ○ | ○ | ○ |
| 电极 | ○ | ○ | ○ | ○ | ○ | ○ |
| 电池 | X | ○ | ○ | ○ | ○ | ○ |
| 外壳 | ○ | ○ | ○ | ○ | ○ | ○ |

本表格依据SJ/T 11364的规定编制。
○:表示该有毒有害物质在该部件所有均质材料中的含量均在GB/T 26572标准规定的限量要求以下。
X:表示该有毒有害物质至少在该部件某一均质材料中的含量超出GB/T 26572标准规定的限量要求。
该产品符合欧盟RoHS 2.0指令 (2011/65/EU)
5年图标是指“环保有效使用期限”,不是产品质量保证期限。电子产品均含有铅、汞、镉等有毒有害物质,一旦超期使用,有毒有害物质将可能因为发生外泄或突变,对环境造成污染,或对人身、财产造成严重损害。“环保使用期限”,意味着所有的电子产品都将被要求在此有效期限内使用,超过安全使用年限之后出现的安全风险问题,我们不再对产品质量负责。

CE

FC

警告

请遵守以上安全说明否则会导致起火、触电、损坏或其他伤害

品牌名: Baseus倍思

公司: 深圳市时商创展科技有限公司

地址: 深圳市龙岗区坂田街道岗头社区雪岗路2008号倍思智能园B栋5层

生产者: 东莞市欧派奇电子科技有限公司

生产者地址: 东莞市塘厦镇林村西富街2号

执行标准: GB/T 35590-2017

热线: 4000-712-711 网址: www.baseus.com

PB2961Z
倍思设计/Designed by Baseus
中国制造/Made in China

3

4

5

6

Baseus

Baseus Adaman Metal Digital Display Quick Charge Power Bank 65W 20000mAh

User Manual

Statement

Thank you very much for choosing this product! Please read the user manual carefully before using this product. All information in this manual may be changed without notice. The company reserves the right to change the information at any time without additional information.

1. Product Parameter

Name: Power Bank
Model No.: PPADM65
Material: Aluminum alloy+ABS
Battery type: Polymer battery
Battery capacity: 5000mAh/14.8V/74Wh
Rated capacity: 12000mAh(5V→6A)
Energy conversion rate: ≥75%
Input:
Micro: 5V→2A, 9V→2A
Type-C: 5V→3A, 9V→3A, 12V→3A, 15V→3A, 20V→3A
Output:
USB1: 4.5V→5A (SCP), 5V→4.5A (SCP), 5V→3A, 9V→3A, 12V→2.5A
USB2: 5V→3A, 9V→3A, 12V→2.5A
Type-C: 5V→3A, 9V→3A, 12V→3A, 15V→3A, 20V→3.25A
USB1+USB2: 5V→3A
Type-C+USB1/USB2: 45W+18W
5V Total Output: 5V→6A
Product size: 154*65*27mm
Product weight: 450g

*The above data are measured by the Baseus laboratory, the actual use will be slightly different depending on the specific circumstances

2. Packing List

1. Power Bank

*1

2. User Manual

*1

3. Warranty card

*1

4. Charging cable

*1

3. Product Diagram

Digital Display Indicating Function

USB1 Output

USB2 Output

Micro Input

Type-C Output/Input

4

4. Product description

This product is a super charging mobile power bank supporting 5A high current and maximum output power up to 65W. It supports two quick charging modes of SCP and FCP of Huawei. It also conforms to PPS specifications. Support IP12 20W PD quick charge. It is compatible with PD3.0, QC4+, QC3.0, Samsung AFC and other fast charging modes. Overtemperature, short circuit protection and other multiple security protection circuits.

5. Instructions for the use of products

Key operation instructions

1. In the no-load state, the button displays the current power at one time.

2. Under the load state, the button displays the current power once, the current voltage again and the current current again.

3. When multiple devices output at the same time, display the total output current of multiple devices.

4. When the input and output side, only the input voltage and current are displayed.

Charging operation instructions

Charging your mobile phones or other digital devices by using Adaman Metal Power Bank

1. Check and make sure the charging voltage of your digital products is consistent with the voltage output of Adaman Metal Power Bank

2. Select and use the original charging cable of your digital products, connect one end of it with your digital product, and the other end with the output port of Adaman Metal Power Bank, Adaman Metal Power Bank then automatically starts to charge your digital product, with the LED indicator lit all the time.

Charging Adaman Metal Power Bank by using a AC charger or PC USB port

1. Select and use the original USB cable, connect the Micro or Type-C port with the Micro or Type-C input port of Adaman Metal Power Bank.

2. Connect the USB or Type-C connector with the USB port of AC charger or PC USB port, and the LED indicator begins to flash, that is charging Adaman Metal Power Bank. While full charge the indicators become lit constantly.

6. Use environment

Use ambient temperature: non-tropical area below 0℃ to 40℃

Storage ambient temperatures: 0℃ to 40℃ degrees Celsius

7. Safety warning instructions

1. Due to the existence of conversion efficiency, so rated output capacity is less than battery capacity .

2. When you need to check the power, press the power button once and the LED indicator lights up to show the current power. In the connectionless state, the power will automatically sleep after about 30 seconds.

3. Please charge your power bank periodically (at least one time with 5 months recommended) in order to maintain its long service life.

4. Improper use of the product can easily cause damage to the product or may endanger personal and property safety.

5. Consumer shall be liable for any personal and property damage resulted from their improper use against the user manual or ignoring the warning, to which our company will not bear any legal liability.

6. Disintegration of this product by non-professionals is strictly prohibited.

7. Use of household appliances or loads in excess of the output current of this product shall be avoided (no output due to circuit protection).

8. Intense physical actions including knocking, throwing, trampling on and squeezing, etc. shall be avoided.

8. Statement on Toxic and Hazardous Substances in Electronic Information Products

| Part Description | Toxic or hazardous substances and elements ^① | | | | | |
|------------------|---------------------------------------------------------|--------------|--------------|-----------------------------|--------------------------------|---------------------------------------|
| | Lead (Pb) | Mercury (Hg) | Cadmium (Cd) | Hexavalent chromium (Cr VI) | Polybrominated biphenyls (PBB) | Polybrominated diphenyl ethers (PBDE) |
| PCB | X | ○ | ○ | ○ | ○ | ○ |
| Electrode | ○ | ○ | ○ | ○ | ○ | ○ |
| Battery | X | ○ | ○ | ○ | ○ | ○ |
| Casing | ○ | ○ | ○ | ○ | ○ | ○ |

This form is compiled in accordance with SJ/T 11364.
○:It indicates that the content of the toxic and harmful substance in all homogeneous materials of the component is below the limit specified in GB/T 26572 standard.
X: The content of toxic and harmful substances in at least one homogeneous material of this part exceeds the limit stipulated in GB/T 26572 standard.
This product complies with EU RoHS 2.0 Directive(2011/65/EU)
The information provided in this form is based on the data provided by the supplier and in line with the detection result of ROHS environmental requirements.
The 5-year icon refers to the "effective life of environmental protection", not the product quality assurance period. Electronic products all contain toxic and harmful substances such as lead, mercury and cadmium. Once they are overused, toxic and harmful substances may leak or mutate, cause pollution to the environment, or cause serious damage to people and property. The term of "environmental protection use" means that all electronic products will be required to use within this effective period. We will no longer be responsible for the quality of the products due to the safety risks that arise after the safe use period.

Warning

Please follow the above safety instructions otherwise it will cause fire/electric shock, damage or other damage.

CE

FC

Shenzhen Times Innovation Technology Co., Ltd.

Add: 5th Floor, Building B, Baseus Intelligence Park, No.2008, Xuegang Rd, Gangtuo Community, Bantian Street, Longgang District, Shenzhen

Producer: Dongguan Opaqi Electronic Technology Co., Ltd.

Production address: Tangxia Town, Dongguan City, Lam Tsuen Hongye North Road West Fu Street on the 2nd

Executive Standard: GB/T 35590-2017

TEL: +86 755-82433603 Hotline: 4000-712-711

Copyright©2010-2020 Shenzhen Times Innovation Technology Co., Ltd.

All Rights Reserved

PB2961Z
Designed by Baseus
Made in China

6