## 储能逆变器(WI-FI版)数采器

## 快速安装指南



步骤1: 将数据采集器的两个组件组装在一起,并用通讯线连接。





步骤2: 将通讯线一头与 WIFI 模块相连, 另一水晶头与逆变器 COMM 端 口相连,并插紧。



- 注意:将 WIFI 模块放置在安全位置并固 定,请勿直接放置在逆变器上,避免产生干 扰。
- 步骤3: 当数采器指示灯"PWR"和"COM"显示绿灯常亮时,表示 WIFI 与逆 变器连接成功。



序列	标识	描述
1	PWR/电源	灯亮:外部电源输入
2	COM/设备	灯亮:下属设备有回应
3	NET/连网	灯亮:连接到基站
4	SRV/连云	灯亮: 连接到指定服务器

# 2. 无线路由器连接

## 2.1 APP 下载

① 扫描右方的二维码,下载 APP。



#### 2.2 WI-FI 数采器连接

① 打开光储宝 APP,在登录页面找到"工具箱",点击"WI-FI 配网"。

② 打开手机的无线局域网, 找到与数采器 PN 相同的 WI-FI 进行连接。(初始 密码: 12345678)

③ 手机连接数采器 WI-FI 成功后,打开 APP,回到"WI-FI 配网"页面,点击 "下一步"进入"联网设置"



i@m Wi-	Fi init	R <	Wi-	Fi配网
Wi-Fi			50 50	Step1
✓ Q0044203542873 低安全性	₽ \$ ()			进入系统"设置- 无线局域网"
我的网络		Ste	p2	
HHJ1	≜ ≉ (j)	选择 一致	与忠数采器PN号 的Wi-Fi进行连接	ran en
其他网络		<b></b>		1 13
仓库1	€ * (1)	-		Step3
其他				连接成功后,返回 APP点击下一步
询问是否加入网络	通知 >			连接
将自动加入已知网络。如果没 有可用网络。	有已如网络,将道如你		Ŧ	一步
自动加入执卢	(御岡加入 >			

## 2.3 联网设置

① 在"联网设置"页面,填写路由器相关信息,完成联网设置。 ② 数采器重启成功后,断开数采器 WIFI,连接本地可用的 WIFI。

<	联网设置 g0044203542873		<	网络配 ■ Q00442	置成功 03542873	<	设 <b>型</b>	Wi-Fi	编辑
	1 2			0			Wi-Fi		
	网络连接 配置成功			网络连接	配置成功		√ ннл		ي ج 4
路由器		-					我的网络		
彩田		<u> </u>					Q004420	03542873	≜ ≑ 🛈
			•		6	<b> </b>	其他网络 崇		
					- J	-	仓库1		<b>≜</b> ≈ (j)
							其他		
				网络配	置成功				
							询问是否加入	入网络	通知 >
	确定		_				将自动加入已知 有可用网络。	网络,如果没有已知网	8络,将通知你
温馨提示 1.请保证该	、 I接网络的信号良好且网络畅通			回到	首页		自动加入热。	ά.	询问加入 >
2.日前暂7 3.積保路自	F支持5G颈段的路由器,请使用2.4G级i 由器的密码正确无误	的該由醫					无可用Wi-Fi网络 个人热点。	8时,允许此设备自动	查找附近的
	设置失败?	联网诊断							

## 3. 注册账号与添加数采器

#### 3.1 账号注册

① 在 APP 首页, 点击"注册"按钮, 按提示填写相关信息, 完成注册。

手机注册 邮箱注册 用户名 请设置用户名 手机号码 +86 读该项手机号纳 请给入油证码	获取验证码
用户名 请设置用户名 手机号码 +86 请请将手机号码 请输入验证码	获取验证码
手机号码 +86 请填写手机号码 请输入验证码	获取验证码
	获取验证码
387.473	
请输入密码	کې
磷认密码 请输入再次确认密码	
●我已阅读并同意益邦条款	
立即注册	
	<ul> <li>我已阅读并用集益邦质款</li> <li>立同注册</li> </ul>

### 3.2 添加设备

① 登录 APP, 在底部导航栏中选择"监控"进入该页面, 点击右上角"+"按钮, 进入到"扫描二维码"界面。

- ② 扫描数采器的 PN 或者手动输入 PN, 添加数采器。
- ③ 根据提示输入相关信息,完成设备添加。



### 3.3 连接成功

① 连接成功后,数采器四个指示灯将会显示绿色,三灯常亮,"NET"闪烁。



## 0 0

# WI-FI Plug Pro

### **Quick Installation Guideline**

## 1. Installation

Step 1: Assemble the two components of the Datalogger together and connect the COMM wiring.



Step 3: When the indicator lights "PWR" and "COM" on the Datalogger are solid green, it indicates that the WIFI is successfully connected to the inverter.

0	0	0
COM	NET	SRV
	О сом	O O Com Net

No.	lcon	Description	
1	PWR/Power	Light on: External power input	
2	COM/Device	Light on: Subordinate device responds	
3	NET/Network	Light on: Connected to the base station	
4	SRV/Server	Light on: Connected to the specified server	

## 2. Wireless Router Connection

### 2.1 Download APP

① Scan the QR code on the right to download the APP.



### 2.2 Connection WI-FI Datalogger

① Open the SmartESS app and find the "Toolbox" on the login page. Click on "WI-FI Network."

② Open your phone's Wi-Fi settings and connect to the Wi-Fi network that matches the Datalogger's PN (initial password: 12345678).

③ After successfully connecting your phone to the Datalogger's Wi-Fi, open the app, return to the "WI-FI pairing" page, and click "Next" to enter the "Internet Settings."



#### 2.3 Network Setting

① According to the prompts, type in the information to finish the network setting.

② After the Datalogger restarts successfully, disconnect it from its Wi-Fi and connect it to an available local Wi-Fi network.



## 3. Create Account And Add Datalogger

#### 3.1 Create Account

- ① Open the APP, tap the Register button to enter this page.
- ② According to the Prompts, type in the information to create an account.

	English 🗸	< Sign up	
		Sign up for phone Sign up	or e-mail
V3.3611	Terran and the second	Username Please set username	
Q HHJ01	•	Phone	
		+86 Please fill in cell phone	
	¥	Please input the verification of	ode Obtain
<ul> <li>Auto login</li> <li>I have read and agree Evice</li> </ul>	and terms	Password	
Sign in			L,
angin in		Confirm password	
Sign up			
Toolbox	DEMO	I have read and agree Eybond t	erms

### 3.2 Add Device

① Login to the app, then select "Monitor" from the bottom navigation bar to enter the page. Click the "+" button in the top right corner to enter the "Scan QR Code" screen.

- ② Scan the PN on the Wi-Fi Plug Pro, or input it manually.
- ③ According to the prompts, type in the information to finish add device.



### 3.3 Connection Successful

Once connected successfully, the four indicator lights on the Datalogger will turn green, with three lights staying on and the "NET" light flashing.