




PARRI emergency exit sign

big, ceiling/wall, white

The PARRI3 emergency lighting system is suitable for use as a wall and ceiling light. The safety lights are fitted with a built-in Ni-MH battery with an automatic self-test. The detection range is 24 m. The emergency operating time of the luminaires is three hours. The luminaires can be operated permanently switched on / stand-by operation. The luminaire is connected directly to the 230V mains supply. Other variants of the PARRI series are available. The luminaire is supplied with three signs with different arrow directions (right / left / down). As an option, other signs are available.



TECHNICAL DATA

Item no.:	1000295
Number of different light outlets	1
Primary nominal voltage	220-240V ~50/60Hz mA/V
Width	33.0 cm
Height	25.0 cm
Depth	6.0 cm
Net weight	1.458 kg
Gross weight	1.646 kg
IP Code	IP 20
Safety class	II
Assembly	Surface
Assembly details	Wall
Wattage	4 W
Lumen	32 lm
Colour temperature	4000 Kelvin
Color	white
CRI	>70
LXXBXX data	70/50
Service life	25000 h

Accessories

240008	PICTOGRAM FOILS , for P-LIGHT emergency exit light, set of 4, diagonal arrow in all directions, L/H 30/16.1 cm
240021	RECHARGEABLE BATTERY , for P-LIGHT, 3.6V, 1000mA

Notes
