

LED Double Moon Color

USER'S MANUAL

Products Introduction

To congratulate you order WPG006 light .Features as the following:

- ☐ LED lamp-house :80 pcs LED
- ☐ Self-motion mode
- ☐ Sound controller mode
- ☐ Master slave mode
- ☐ Standard DMX control signal .6DMX channels .
- ☐ Power supply : AC100V-240V 50/60HZ
- ☐ Rated Power Consumption :15w
- ☐ Work environment :indoor 20⁰C-40⁰C .
- ☐ Outline size :280×280×160mm
- ☐ Packing size :350×350×210mm
- ☐ N/W :2.5KG G/W :3.3KG

Installation

Fix up it at any place .but the distance between the light and other objects or person should be at least 1m.and ensure fastness well .do safety measure well .the light should earthing safety .

DMX512 connections :

Through 3-pin XLR "input" and "output" socket Controller DMX512 signal (1earth,2-,3-)connect as follow. (Note : pls exchange and connect signal 2 and 3 if it can't by control. generic controller don't use this. signal line should be within 100 meter, prevent others equipment to be disturbed as excess line.

Ensure the voltage and frequency of the factory enactment are suit your locate .you can open it after connect it well .

Operation introduction

DMX CHANNEL	DMX VALUE	SPECIFICATION
Channel 1	0--15	off
	16--255	Auto Mode
Channel 2	(CH3 CH6)	Portfolio Effect
	0--18	Off
	19--255	Flash Speed Slow --Quick
Channel 3	0--28	Off
Channel 6	29--55	Red
	56--81	Green
	85--115	Blue
	116--144	R G
	145--173	B G
	174--202	B R
	203--230	R G B
	231--255	R G B Flicker
Combination With Channel 1		