

DMX Follow Spot Light



Use Manual

=====PROFESSIONAL LIGHTING EQUIPMENT=====

Instruction

Thank you for trusting and choosing our product. Wish you will satisfy for our products. In order to use this Bubble Machine in security, please read the Use Manual seriously.

Productbriefintroduction

This Light uses the advance technology, high effect optics system so that let this light has the steady capability and high brightness. The cast shell use the Aluminum alloy and let it has the good give out the heat and good shape.

PackingList

DMX 1200W Follow Spot Light 1pc. Power Case 1pc. Light Stand 1pc. Use Manual 1pc.

TechnologyParameter

Voltage: **AC220V~240V/.50HZ-60HZ**

Power: **1350W**

Light-Source: **HMI-1200W**

Resist the voltage: **1.5KV**

Insulated resistance: **72MΩ**

Color: **5Colors + White beam**

Zoom: **Adjusting**

Flash: **1-5Hz**

DMX Channels: **4 CH**

Safetystatement

!!!Don't open the cover for yourself, pay attention to get an electric shock.

1, The light beam strong, do not look directly at the light source and the beam, to avoid of hurt eyes.

2, The product end of the main box has a power switch. Connected to the power required to switch to open source at this time in the trigger process

Need to wait for a few seconds, circuit board has a 10 second delay after the start of work, the fan normal rotation.

3, Due to the characteristics of bubbles, the product is powered and will not

immediately produce light beams, while the need to complete only a few seconds after the trigger completed. After a few seconds to complete as the trigger to lamp brightness.

4, To be fully lit the lamp, press the control panel in the open light key and the beam injection.

5, The beam projected onto the venue, and adjust the tube, until the aperture clearly.

6, Press the face should be the function keys, can flash, change color, aperture zoom and other functions.

7, When the bright yellow light, indicating attenuation of the lamp life is approaching, please replace the lamp professionals.

Operation Manual

Open the packing, please check the light in good status, and then put in the fit location and set up the stand well. Connect the power and turn on the light, the system will be time-lapse in 10sec and into the checking status, check itself about 30sec later, the buttons can be controlled.

When in using press the **"RISING HOOD"** turn on the light, and then press the **"BIG LIGHT CIRCLE"** or **"SMALL LIGHT CIRCLE"** adjust the zoom, choose color (**"WHITE"****"BLUE"****"YELLOW"****"GREEN"****"RED"** etc.) . If want the special effects, please press the **"FLASH"** in strobe flash, press again it stops flash.

When in using, if has some other statuses, you can press the **"RESET"**.

DMX Control Manual

Use DMX controller to control this Light, first of all, please pull out the cable which connect the control board on light.

And then connect the DMX cable with port DMX IN, can use the DMX console to control.

The DIP is fixture, ecumenical states don't change it.

CH1-Color Change

CH2-Color Change

CH3-Zoom

CH4-Dimmer and Strobe