

Assembly Box

for BioTag Home Fingerprint Reader

With 12 V Relay (C, NO, NC), Jumper and Tamper switch.

Clamp	Fingerprint Reader (Art. No. 460190)		Function	Notes	Notes
1	Red	+ 12 V			
2	Black	GND			
3	Green	Delete all	Delete all fingers		
4	White	Enroll	Enroll by Masterfinger		
5	Blue	Delete	delete individual by Masterfinger		
6	Orange	Extern LED	Extern red LED	0 V active	
7	Brown	Extern buzzer	Extern buzzer	0 v active	
8					
9	Yellow	OC Output	Open Collector (500mA, direct, 0V active)	Relay (0 V)	*with relay
10				NC*	*with relay
11				C*	*with relay
12				NO*	*with relay