Schottky Barrier Rectifier





Features:

- · Metal-Semiconductor junction with guard ring
- Epitaxial construction
- · Low forward voltage drop
- · High current capability
- The plastic material carries UL recognition 94V-0
- For use in low voltage, high frequency inverters, free wheeling, and polarity protection applications

Mechanical Data:

Case : JEDEC DO-27 molded plastic
Polarity : Colour band denotes cathode
Weight : 0.04ounces , 1.1grams

Mounting Position : Any

Reverse Voltage : 50 to 60 Volts Forward Current : 3 Amperes

Maximum Ratings and Electrical Characteristics:

Rating at 25°C ambient temperature unless otherwise specified.

Single phase, half wave, 60Hz, resistive or inductive load. For capacitive load, derate current by 20%.

Characteristics	Symbol	SR350	SR360	Unit
Max. Recurrent Peak Reverse Voltage	Vrrm	50	60	
Max. RMS Voltage	VRMS	35	42	V
Max. DC Blocking Voltage	VDC	50	60]
Max. Average Forward Rectified Current 0.375" (9.5mm) Lead Lengths	I(AV)	3 80		
Peak Forward Surge Current, 8.3ms Single Half Sine-wave Superimposed on Rated Load (JEDEC method)	Ігѕм			A
Peak Forward Voltage at 3A DC	VF	0.7		V
Max. DC Reverse Current at $T_J = 25^{\circ}C$ Rated DC Blocking Voltage at $T_J = 100^{\circ}C$	lR	1 20		mA
Typical Junction Capacitance (Note 1)	CJ	250		pF
Typical Thermal Resistance (Note 2)	Rejl	10		°C/W
Operating Temperature Range	TJ	-55 to +150		°C
Storage Temperature Range	Tstg			

Notes:

- 1. Measured at 1.0MHz and applied reverse voltage of 4.0V DC.
- 2. Thermal resistance junction to lead
- 3. The typical data above is for reference only


Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro





Schottky Barrier Rectifier multicomp PRO





Ratings and Characteristic Curves












Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro



Schottky Barrier Rectifier



Dimensions:



Dimensions: Inches (Millimetres)

Part Number Table

Description	Part Number	
Schottky Barrier Rectifier, 3A 60V, DO-27	SR360	
Schottky Barrier Rectifier, 3A 50V, DO-27	SR350	

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro

