

FEATURES

- DC-AC power inverter
- Chassis mounting
- Pure sine wave
- One output connection
- Single-phase electrical output
- Input voltage of 24 V
- Output voltage of 230 V
- Universal output connection type
- Efficiency rating over 90%
- Mean time between failures of 50,000 h
- Output current of 34.78 A
- Maximum input of 333.3 A
- Length of 543 mm
- Width of 230 mm
- Depth of 107.7 mm

4000W Fixed Installation DC-AC Power Inverter, 24V / 230V

RS Stock No.: 179-3345



RS Professionally Approved Products bring to you professional quality parts across all product categories. Our product range has been tested by engineers and provides a comparable quality to the leading brands without paying a premium price.

Product Description

Use this 4000 W fixed installation DC to AC power inverter from RS PRO to charge a range of appliances. The handy electronic device can be connected to car batteries for power on-the-go. Power inverters take direct current (DC) from your car battery and turn it into alternating current (AC), which is the electricity you find in wall outlets. Most devices run on AC, so power inverters are a great way to charge appliances from a car or mobile home.

General Specifications

Inverter Directionality	DC to AC
Output Connection Type	Universal
Mounting Type	Chassis Mount
MTBF	50000h
Applications	Home appliance, Power tools, Office and Portable equipment

Electrical Specifications

Output Specifications	
AC Voltage	230V
Rated Power	4000W
Peak Power	4100W
Surge Power	8000 W
Current	34.78A
Waveform	Pure Sine Wave
Frequency Range	50Hz
Number of Output Connection	2
Output Electrical Phase	1
Efficiency	>90%

Input Specifications	
DC Voltage	24V
Maximum DC Current	333.3A

Mechanical Specifications

Dimension	543mm x 230mm x 107.7mm
Length	543mm
Width	230mm
Depth	107.7mm
Weight	9kg

Operation Environment Specifications

Cooling	Natural convection
Operating Temperature Range	-20°C to +50°C

Approvals

Compliance/Certifications	CE, ECE R10.05:2014, EN 60950-1, EN 61000-6-1, EN 61000-6-3, RoHS
----------------------------------	---



