



ENGLISH



Stock No. 123-2207

IPM 6200

Graphic Power Quality Analyzer





19/09/2016

FEATURES :

- Power Quality Analysis for Single and Balanced 3 Phase System
- Harmonic Analysis of Voltage and Current (1 to 50th order)
- True RMS measurement of V with 0.5% basic accuracy
- True RMS measurement of A with 1% of range basic accuracy
- Graphic Waveform of Voltage and Current
- Graphic Phasor Diagram
- Transient Detection and Logging of Swell, Dip, and Outage
- Fast peak function (39µs for 50 Hz, 33µs for 60Hz)
- Active (W, KW, HP), reactive (VAR, KVAR) and apparent (VA, KVA) power
- Power factor (PF), phase angle (Φ), and energy (WH, KWH)
- Programmable VT ratio from 1 to 3000
- Hold functions
- Auto power off function in 15 minutes (selectable)

SPECIFICATIONS : (23°C±5°C)

AC Watt

| Range | Resolution | Accuracy o | f Readings |
|------------------|------------|------------------|----------------|
| (0 to 1500A) | | > 20 V and > 20A | < 20V or < 20A |
| 10.0 – 999.9 W | 0.1W | ±1% ±20dgts | ±2% ±40dgts |
| 1.000 – 9.999 KW | 0.001 KW | ±1% ±20dgts | ±2% ±40dgts |
| 10.00 – 99.99 KW | 0.01 KW | ±1% ±20dgts | ±2% ±40dgts |
| 100.0 – 999.9 KW | 0.1 KW | ±1% ±20dgts | ±2% ±40dgts |
| 1000 – 9999 KW | 1 KW | ±1% ±20dgts | ±2% ±40dgts |

AC Apparent Power (VA)

| Range | Range Resolution | Accuracy of Readings | |
|-------------------|------------------|----------------------|---------------|
| (0 to 1500A) | | > 20 V and > 20A | <20V or < 20A |
| 10.0 – 999.9 VA | 0.1VA | ±1% ±20dgts | ±2% ±40dgts |
| 1.000 – 9.999 KVA | 0.001 KVA | ±1% ±20dgts | ±2% ±40dgts |
| 10.00 – 99.99 KVA | 0.01 KVA | ±1% ±20dgts | ±2% ±40dgts |
| 100.0 – 999.9 KVA | 0.1 KVA | ±1% ±20dgts | ±2% ±40dgts |
| 1000 – 9999 KVA | 1 KVA | ±1% ±20dgts | ±2% ±40dgts |

19/09/2016

AC Reactive Power (VAR)

| Range | Resolution | Accuracy o | f Readings |
|------------------|------------|------------------|---------------|
| (0 to 1500A) | | > 20 V and > 20A | <20V or < 20A |
| 10.0–999.9 VAR | 0.1VAR | ±2% ±30dgts | ±3% ±40dgts |
| 1.000–9.999 KVAR | 0.001 KVAR | ±2% ±30dgts | ±3% ±40dgts |
| 10.00–99.99 KVAR | 0.01 KVAR | ±2% ±30dgts | ±3% ±40dgts |
| 100.0–999.9 KVAR | 0.1 KVAR | ±2% ±30dgts | ±3% ±40dgts |
| 1000 – 9999 KVAR | 1 KVAR | ±2% ±30dgts | ±3% ±40dgts |

Power Factor (PF)

| Range | Resolution | Acc | uracy |
|---------------|------------|------------------------------|----------------|
| | Resolution | > 20V & > 20A < 20V or < 20A | < 20V or < 20A |
| 0.000 – 1.000 | 0.001 | ± 0.04 | ±0.1 |

AC Current (50 or 60 Hz, Auto Range, True RMS, Crest Factor < 4, Overload Protection AC 2000A)

| Range | Resolution | Accuracy of Readings |
|----------------|------------|----------------------|
| 4.0 – 1500.0 A | 0.01 A | ±1.0% ± 5dgts |

AC Voltage (Overload Protection AC 800V)

| Range | Resolution | Accuracy of Readings |
|-----------------|------------|----------------------|
| 4.0 V – 600.0 V | 0.1 V | ±0.5% ± 5dgts |

Harmonics of AC Voltage in Percentage

| Range | Resolution | Accuracy |
|-----------------------|------------|---------------------|
| 1 – 20 th | 0.1% | ±2% |
| 21 – 50 th | 0.1% | 4% of reading ±2.0% |

Harmonics of AC Voltage in Magnitude

| Range | Resolution | Accuracy |
|-----------------------|------------|---------------------|
| 1 – 20 th | 0.1% | ±2% ± 0.5V |
| 21 – 50 th | 0.1% | 4% of reading ±0.5V |

Harmonics of AC Current in Percentage

| Range | Resolution | Accuracy |
|-----------------------|------------|---------------------|
| 1 – 20 th | 0.1% | ±2% |
| 21 – 50 th | 0.1% | 4% of reading ±2.0% |

Harmonics of AC Current in Magnitude

| Range | Resolution | Accuracy |
|-----------------------|------------|--------------------|
| 1 – 20 th | 0.1% | ±2% of range ±0.4A |
| 21 – 50 th | 0.1% | ±4% of range ±0.4A |

Phase Angle (Φ)

| Range | Resolution | Accuracy |
|---------------|------------|----------|
| -180° to 180° | 0.1° | ± 1° |
| 0° to 360° | 0.1° | ± 1° |

19/09/2016

Total Harmonic Distortion

| Range | Resolution | Accuracy |
|---------------|------------|-----------------------|
| 0.0 – 20% | 0.1% | ± 2% |
| 20 – 100% | 0.1% | ± 6% of reading ± 1% |
| 100 – 999.9 % | 0.1% | ± 10% of reading ± 1% |

Peak Value of AC Voltage (RMS value > 20V) or AC Current (RMS value > 30A)

| Range | Sampling Time | Accuracy of Reading |
|-------|---------------|---------------------|
| 50 Hz | 39 µs | ± 5% ± 50 digits |
| 60 Hz | 33 µs | ± 5% ± 50 digits |

Frequency of AC Voltage (RMS value > 20V) or AC Current (RMS value > 30A)

| Range | Resolution | Accuracy |
|---------|------------|----------|
| 46 – 65 | 0.1 | ± 0.3Hz |

| Conductor Size: | 55mm (approx.), 65 x 24mm (bus bar) |
|---------------------------|--|
| Data Logging Memory Size: | 512K bytes |
| Maximum Transient Events: | 32000 |
| Battery Type: | two 1.5V SUM-3 |
| Display: | 128 X 64 Dot Matrix LCD with Backlight |
| Range Selection: | Auto |
| Overload Indication: | OL |
| Power Consumption: | 10mA (approx) |
| Auto-Power-Off: | 15 minutes after power-on |
| LCD Update Time: | 2 times/sec. |
| No. Of Samples per Period | 512 (voltage or current); |
| No. Of Samples per Period | 256 (power) |
| Operating Temperature: | -10°C to 50°C |
| Operating Humidity: | Less than 85% RH |
| Altitude: | up to 2000M |
| Storage Temperature: | -20°C to 60°C |
| Storage Humidity: | Less than 75% RH |
| Dimension (Box): | 271 x 112 x 46 mm |
| Weight: | 647g (battery included) |
| | Users manual, Batteries 1.5V x 2, Software CD, |
| Accessories: | Software users manual, Carrying Bag, Test leads, |
| | Alligator clips, Optical USB cable |