

# LEADER400



- Battery charger and starter: WET/START/STOP battery charger and cranking of any type of 12/24V petrol engine.
- Normal charge, fast (BOOST) charge, rapid cranking selection.
- Display of charging and cranking current.
- Protection against overcharging and pole inversion.

## Description

Battery charger and starter for charging free electrolyte batteries (WET) with 12V/24V voltage, and starting all types of petrol-driven and diesel-driven vehicles, up to 70 hp.

## Technical Data

Single-phase mains voltage	230 V
Mains frequency	50/ 60 Hz
Charge power	1 kw
Charging voltage	12/ 24V
Start power	6.4 kw
Effective charging current	45 A
Rated charge curr. EN60335-2-29	31 A
Start current 1V/C EN60335-2-29	180 A
Max. starting current	300 A
Min. rated reference capacity	20 Ah
Max. rated reference capacity	700 Ah
Adjustment positions	3
Dimensions	26.5 x 34.5 x 23 cm
Weight	10.9 kg