

Bench Top Power Supply **multicomp**PRO



Description

This small 80W auto ranger laboratory power supply has 0.5V to 36V and 0 to 5A output range.

The settings of functions such as upper voltage limit, upper current limit, and power up output status, 3 presets are intuitive and easy to get used to fast and fine tuning of voltage and current, using the shifting integer makes setting of voltage and current ever so fast, accurate and easy.

Features

- Auto range selection with maximum 80W output
- Resolution with 10mV and 10mA with 4 digit display
- Upper Voltage and Current level setting for the protection of DUT
- 3 User presets of frequently used Voltage and Current outputs
- Output on-off switch and control panel lock button for safer operation
- Master/Slave configuration for synchronization of the parallel connected output of multiple units.
- Over Temperature, Over Current, Over Voltage and Short Circuit Protection
- Voltage remote sensing

Specifications

Output Voltage and Current	
Output Voltage	0.5V DC to 36V DC
Output Current	0 to 5A (Auto range with maximum output power 80W ($V \times A \leq 80W$))
Constant Voltage Characteristics:	
Adjust Resolution	10mV
Load Regulation (10 – 90%)	$\leq 30mV$
Line Regulation ($\pm 10\%$)	$\leq 4mV$
Ripple & Noise (peak-peak)	$\leq 35mA$
Constant Current Characteristics:	
Adjust Resolution	1mA (start from 30mA)
Load Regulation (10 – 90%)	$\leq 10mA$
Line Regulation ($\pm 10\%$)	$\leq 10mA$
Meter Accuracy	
Voltage Meter Accuracy	$\pm(0.5\% + 5counts)$

Bench Top Power Supply **multicomp** PRO

Current Meter Accuracy	±(0.5% +5 counts)
User adjustable upper voltage & current limit	Yes
Number of frequently used V & I presets	3
Remote Sensing	Yes
Protection	Tracking Over Voltage Protection, Current Limiting Protection, Short Circuit, Overload, Over Temperature, Upper Voltage Limit, Upper Current Limit.
Additional Function	Master/Slave Control
Cooling Method	Natural Convection
No Load Input Current at 230V AC	≤150mA
Full Load Input Current at 230V AC	≤500mA
Input Voltage Range	100V AC to 240V AC, 50 Hz / 60 Hz
Efficiency	≥78%
Power Factor	≥0.9
Dimensions (WxHxD)	53.5mm × 127mm × 330mm / 2" × 5" × 13"
Weight	Approx. 1.9kgs / 4.2lbs

All values are based on the Standard ambient Temperature 25°C and Pressure 0.1Mpa.

Accessories

AC Power Cord (UK / EU), Test Lead set, Master/ Slave Connection Cable, Terminator for Master/ Slave Connection and Quick Start Guide

Standard Warranty

12 Months

Part Number Table

Description	Part Number
Power Supply, 5mV DC to 36V DC, 5A	MP710082

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/exclusive-brands
 Farnell.com/exclusive-brands
 Element14.com/exclusive-brands

multicomp PRO