

Product Environmental Profile

400W 220V~ 1G Dimmer Controller






General information

Representative product	400W 220V~ 1G Dimmer Controller - A3B31_DC
Description of the product	The main purpose of the Dimmer Controller is to meet people's different needs for light brightness at different times
Functional unit	<p>The main functions of this product is to change the input voltage and current of the electric light source to obtain different intensity of light output, suitable for a variety of public places. It must contain:</p> <ul style="list-style-type: none"> - Open the voltage: 0-50V - Termination of sample: 200-220V - 25W-400W incandescent light - IP20 - Standard GB/T 16915.2



Constituent materials

Reference product mass	84 g	including the product, its packaging and additional elements and accessories
-------------------------------	------	--



Plastics	51.5%
Metals	17.6%
Others	31.0%



Substance assessment

Products of this range are designed in conformity with the requirements of the RoHS directive (European Directive 2011/65/EU of 2 January 2013, amended in March 2015, 2015/863/EU and in November 2017, 2017/2102/EU) and do not contain, or only contain in the authorised proportions, lead, mercury, cadmium, hexavalent chromium or flame retardants (polybrominated biphenyls - PBB, polybrominated diphenyl ethers – PBDE), Bis (2-ethylhexyl)phthalate - DEHP, Benzyl butyl phthalate– BBP, Dibutyl phthalate - DBP, Diisobutyl phthalate - DIBP) as mentioned in the Directive.

Details of ROHS and REACH substances information are available on the Schneider-Electric Green Premium website

<http://www2.schneider-electric.com/sites/corporate/en/products-services/green-premium/green-premium.page>

Additional environmental information


The 400W 220V~ 1G Dimmer Controller presents the following relevant environmental aspects

Manufacturing	Manufactured at a Schneider Electric production site ISO14001 certified
Distribution	Weight and volume of the packaging optimized, based on the European Union's packaging directive Packaging weight is 4 g, consisting of cardboard (91.2%), Paper (3.3%), PET (5.5%) Product distribution optimised by setting up local distribution centres
Installation	Reference A3B31_DC does not require any installation operations.
Use	The product does not require special maintenance operations.
End of life	End of life optimized to decrease the amount of waste and allow recovery of the product components and materials No special end-of-life treatment required. According to countries' practices this product can enter the usual end-of-life treatment process. Recyclability potential: 16% Based on "ECO'DEEE recyclability and recoverability calculation method" (version V1, 20 Sep. 2008 presented to the French Agency for Environment and Energy Management: ADEME).

Environmental impacts

Reference life time	10 years			
Product category	Other equipments - Active product			
Installation elements	No special components needed			
Use scenario	The product is in active mode 30% of the time with a power use of 1.3W and in off mode 70% of the time with a power use of 0W, for 10 years			
Geographical representativeness	China			
Technological representativeness	The main purpose of the Dimmer Controller is to meet people's different needs for light brightness at different times			
Energy model used	Manufacturing	Installation	Use	End of life
	Energy model used: China	Electricity mix; AC; consumption mix, at consumer; 220V; CN	Electricity mix; AC; consumption mix, at consumer; 220V; CN	Electricity mix; AC; consumption mix, at consumer; 220V; CN

Compulsory indicators		400W 220V~ 1G Dimmer Controller - A3B31_DC					
Impact indicators	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Contribution to mineral resources depletion	kg Sb eq	8.26E-05	8.24E-05	0*	0*	1.53E-07	0*
Contribution to the soil and water acidification	kg SO ₂ eq	4.02E-02	2.47E-03	4.95E-05	0*	3.77E-02	2.56E-05
Contribution to water eutrophication	kg PO ₄ ³⁻ eq	1.06E-02	6.00E-04	1.14E-05	0*	9.94E-03	7.39E-06
Contribution to global warming	kg CO ₂ eq	3.67E+01	1.93E+00	1.08E-02	0*	3.47E+01	1.46E-02
Contribution to ozone layer depletion	kg CFC11 eq	4.35E-07	1.58E-07	0*	0*	2.77E-07	6.23E-10
Contribution to photochemical oxidation	kg C ₂ H ₄ eq	4.83E-03	3.71E-04	3.53E-06	0*	4.45E-03	2.62E-06
Resources use	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Net use of freshwater	m ³	2.08E-01	1.70E-01	0*	0*	3.88E-02	0*
Total Primary Energy	MJ	5.97E+02	2.76E+01	1.53E-01	0*	5.69E+02	1.22E-01



Optional indicators		400W 220V~ 1G Dimmer Controller - A3B31_DC					
Impact indicators	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Contribution to fossil resources depletion	MJ	5.45E+02	1.99E+01	1.52E-01	0*	5.25E+02	9.86E-02
Contribution to air pollution	m³	3.85E+03	2.45E+02	4.61E-01	0*	3.60E+03	8.94E-01
Contribution to water pollution	m³	2.14E+03	4.14E+02	1.78E+00	0*	1.73E+03	1.10E+00
Resources use	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Use of secondary material	kg	3.65E-03	3.65E-03	0*	0*	0*	0*
Total use of renewable primary energy resources	MJ	2.99E+01	7.33E-01	0*	0*	2.92E+01	0*
Total use of non-renewable primary energy resources	MJ	5.67E+02	2.69E+01	1.53E-01	0*	5.39E+02	1.22E-01
Use of renewable primary energy excluding renewable primary energy used as raw material	MJ	2.99E+01	7.07E-01	0*	0*	2.92E+01	0*
Use of renewable primary energy resources used as raw material	MJ	2.59E-02	2.59E-02	0*	0*	0*	0*
Use of non renewable primary energy excluding non renewable primary energy used as raw material	MJ	5.65E+02	2.52E+01	1.53E-01	0*	5.39E+02	1.22E-01
Use of non renewable primary energy resources used as raw material	MJ	1.74E+00	1.74E+00	0*	0*	0*	0*
Use of non renewable secondary fuels	MJ	0.00E+00	0*	0*	0*	0*	0*
Use of renewable secondary fuels	MJ	0.00E+00	0*	0*	0*	0*	0*
Waste categories	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Hazardous waste disposed	kg	3.30E+00	2.03E+00	0*	0*	1.12E+00	1.53E-01
Non hazardous waste disposed	kg	6.76E+00	4.59E-01	0*	0*	6.30E+00	0*
Radioactive waste disposed	kg	4.40E-04	2.32E-04	2.74E-07	0*	2.08E-04	6.04E-07
Other environmental information	Unit	Total	Manufacturing	Distribution	Installation	Use	End of Life
Materials for recycling	kg	2.49E-02	7.75E-03	0*	3.98E-03	0*	1.32E-02
Components for reuse	kg	0.00E+00	0*	0*	0*	0*	0*
Materials for energy recovery	kg	2.23E-03	0*	0*	0*	0*	2.23E-03
Exported Energy	MJ	1.26E-05	1.19E-06	0*	1.15E-05	0*	0*

* represents less than 0.01% of the total life cycle of the reference flow

Life cycle assessment performed with EIME version EIME v5.9.4, database version 2022-01 in compliance with ISO14044.

The use phase is the life cycle phase which has the greatest impact on the majority of environmental indicators (based on compulsory indicators).

Please note that the values given above are only valid within the context specified and cannot be used directly to draw up the environmental assessment of an installation.

Registration number	ENVPEP2211026_V1	Drafting rules	PCR-ed3-EN-2015 04 02
Date of issue	12/2022	Supplemented by	PSR-0005-ed2-EN-2016 03 29
Validity period	5 years	Information and reference documents	www.pep-ecopassport.org
<i>Independent verification of the declaration and data</i>			
Internal	X	External	
<i>The elements of the present PEP cannot be compared with elements from another program.</i>			
<i>Document in compliance with ISO 14021:2016 « Environmental labels and declarations - Self-declared environmental claims (Type II environmental labelling) »</i>			

Schneider Electric Industries SAS

Country Customer Care Center
<http://www.schneider-electric.com/contact>

35, rue Joseph Monier

CS 30323

F- 92506 Rueil Malmaison Cedex

RCS Nanterre 954 503 439

Capital social 896 313 776 €

www.schneider-electric.com

Published by Schneider Electric

ENVPEP2211026_V1

© 2019 - Schneider Electric – All rights reserved

12/2022