

DYNAMIC 620 START



- Battery charger and starter for 12/24V WET batteries and rapid cranking of all types of cars, vans, light goods vehicles. 570A max.
- Normal charge, fast (BOOST) charge, rapid cranking selection.
- Display of charging and cranking current.
- Protection against overcharging and pole inversion.

Description

Battery charger and starter for charging free electrolyte batteries (WET) with 12V/24V voltage and starting all kinds of cars, vans and light trucks.

Technical Data

Single phase mains voltage	230 V
Mains frequency	50/ 60 Hz
Charge power	2 kw
Charging voltage	12/ 24V
Start power	10 kw
Effective charging current	90A
Rated charge curr. EN60335-2-29	70A
Start current 1V/C EN60335-2-29	360A
Max. starting current	570A
Min. rated reference capacity	20 Ah
Max. rated reference capacity	1550 Ah
Adjustment positions	4
Dimensions	36.5 x 46 x 75.5 cm
Weight	24 kg