

LEADER220



- Battery charger and starter: WET/START/STOP battery charger and cranking of any type of 12/24V petrol engine.
- Normal charge, fast (BOOST) charge, rapid cranking selection.
- Display of charging and cranking current.
- Protection against overcharging and pole inversion.

Description

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage, and starting all types of petrol-driven vehicles.

Technical Data

Single-phase mains voltage	230 V
Mains frequency	50/ 60 Hz
Charge power	0.8 kw
Charging voltage	12/ 24V
Start power	3.6 kw
Effective charging current	30 A
Rated charge curr. EN60335-2-29	20 A
Start current 1V/C EN60335-2-29	120 A
Max. starting current	180 A
Min. rated reference capacity	30 Ah
Max. rated reference capacity	400 Ah
Adjustment positions	2
Dimensions	22.5 x 29 x 20.5 cm
Weight	9 kg