

## Datasheet

### RS 6 Digit , LED, Counter, 20kHz, 24 V

RS Stock number 808-6611



#### INPUTS

**Counting Inputs(Ch-A, Ch-B):** Switch, proximity, capacitive sensor or encoder can be connected.

**Reset Input:** Switch, proximity or capacitive sensor can be connected.

**Pause Input:** Switch, proximity or capacitive sensor can be connected.

**Sensor Type Selection:** NPN or PNP can be selected.

**Reset Function:** Automatic or Manual

**Count Input Types and Maximum Frequency:**

INC, DEC, INC/DEC, INC/INC, UP/DOWN Max. 20kHz.

x1 / x2 / x4: phase shifting (for encoder) counting; Maximum 10kHz.