

PNP Silicon Planar Switching Transistor, TO-39



Pin Configuration

- 1. Emitter
- 2. Base
- 3. Collector

Absolute Maximum Ratings

Parameter	Symbol	Value	Unit
Collector Emitter Voltage	V_{CEO}	600	V
Collector Base Voltage	V_{CBP}	40	
Emitter Base Voltage	V_{EBO}	60	
Collector Current Continuous	I_c	5	mA
Power Dissipation @ $T_A=25^{\circ}C$ Derate Above $25^{\circ}C$	PD	600	mW
		3.43	mW/ $^{\circ}C$
Power Dissipation @ $T_c=25^{\circ}C$ Derate Above $25^{\circ}C$	PD	3	W
		17.2	mW/ $^{\circ}C$
Operating And Storage Junction Temperature Range	T_J, T_{STG}	-65 to +200	$^{\circ}C$

Electrical Characteristics: ($T_A = 25^{\circ}C$ unless otherwise specified)

Description	Symbol	Test Condition	Min.	Typ.	Max.	Unit
Collector Emitter Voltage	$*V_{CEO}$	$I_c=10mA, I_B=0$	40	-	-	V
Collector Base Voltage	V_{CBO}	$I_c=10\mu A, I_E=0$	60	-	-	
Emitter Base Voltage	V_{EBO}	$I_E=10mA, I_c=0$	5	-	-	
Collector Cut Off Current	I_{CEX}	$V_{CE}=30V, V_{BE}=0.5V$	-	-	50	nA
Collector Cut Off Current	I_{CBO}	$V_{CB}=50V, I_E=0$	-	-	20	
		$V_{CB}=50V, I_E=0, T_A=150^{\circ}C$	-	-	20	μA
Base Current	I_B	$V_{CE}=30V, V_{BE}=0.5V$	-	-	50	nA

Description	Symbol	Test Condition	Values
DC Current Gain	hFE	$I_c=0.1mA, V_{CE}=10V$	>35
		$I_c=1mA, V_{CE}=10V$	>50
		$I_c=10mA, V_{CE}=10V$	>75
		$*I_c=150mA, V_{CE}=10V$	100 - 300
		$*I_c=500mA, V_{CE}=10V$	>30

*Pulse Test: Pulse Width $\leq 300\mu s$, Duty Cycle $\leq 2\%$

PNP Silicon Planar Switching Transistor, TO-39

Small Signal Characteristics

Description	Symbol	Test Condition	Min.	Typ.	Max.	Unit
Collector Emitter Saturation Voltage	*V _{CE(SAT)}	I _C =150mA, I _B =15mA	-	-	0.4	V
		I _C =500mA, I _B =50mA	-	-	1.6	V
Base Emitter Saturation Voltage	*V _{BE(SAT)}	I _C =150mA, I _B =15mA	-	-	1.3	V
		I _C =500mA, I _B =50mA	-	-	2.6	V
Transition Frequency	**f _T	I _C =50mA, V _{CE} =20V, f=100MHz	200	-	-	MHz
Output Capacitance	C _{obo}	V _{CB} =10V, I _E =0, f=100kHz	-	-	8	pF
Input Capacitance	C _{ibo}	V _{BE} =2V, I _C =0, f=100kHz	-	-	30	pF


Switching Time

Description	Symbol	Test Condition	Min.	Typ.	Max.	Unit
Delay Time	t _d	I _C =150mA, I _{B1} =15mA, V _{CC} =30V	-	-	10	ns
Rise Time	t _r		-	-	40	ns
Turn On Time	t _{on}		-	-	45	ns
Storage Time	t _s	I _C =150mA, I _{B1} =I _{B2} =15mA, V _{CC} =6V	-	-	80	ns
Fall Time	t _f		-	-	30	ns
Turn Off Time	t _{off}		-	-	100	ns

*Pulse Test: Pulse Width ≤ 300ms, Duty Cycle ≤ 2%

** f_T is defined as the frequency at which |h_{fe}| extrapolates to unity.

TO-39 Metal Can Package



Dimensions	Min.	Max.
A	8.5	9.39
B	7.74	8.5
C	6.09	6.6
D	0.4	0.53
E	-	0.88
F	2.41	2.66
G	4.82	5.33
H	0.71	0.86
J	0.73	1.02
K	12.7	-
L	42°	48°

Dimensions : Millimetres

PNP Silicon Planar Switching Transistor, TO-39



Part Number Table

Description	Part Number
PNP Silicon Planar Switching Transistor, TO-39	2N2905

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro
Farnell.com/multicomp-pro
sg.element14.com/b/multicomp-pro

