

ENERGY 1000 START



- Battery charger and starter for 12/24V WET batteries and rapid cranking of all types of cars, vans, light goods vehicles, excavators, tractors and lorries.
- Fast (BOOST) charge and rapid cranking.
- Remote control. Timer to program timed BOOST charge and avoid overloading the battery.
- Display of charging and cranking current.
- Protection against overcharging and pole inversion.

Description

Battery charger and starter for charging free electrolyte batteries (WET) with 12V/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

Technical Data

Three-phase mains voltage	230 V/ 400V
Mains frequency	50/ 60 Hz
Charge power	2.5 kw
Charging voltage	12/ 24V
Start power	20 kw
Effective charging current	100 A
Rated charge curr. EN60335-2-29	80A
Start current 1V/C EN60335-2-29	640A
Max. starting current	1000 A
Min. rated reference capacity	20 Ah
Max. rated reference capacity	1600/ 800Ah
Adjustment positions	5
Dimensions	38 x 56 x 88.5 cm
Weight	45 kg