



EKSELANS BY ITS

REPARTIDORES COM CONECTOR F RF 12/ RF 13/ RF 14/ RF 16/ RF 18

Blindagem classe A

Passagem DC em todas as saídas

5-2300 MHz

REFERÊNCIA		RF 12	RF 13	RF 14	RF 16	RF 18
Código		141001	141002	141003	141004	141005
Banda de passagem	MHz	5-2400	5-2400	5-2400	5-2400	5-2400
Saídas	Nº	2	3	4	6	8
Perdas inserção	dB 860 MHz	4	7	8,1	11	12
	dB 2300 MHz	5,5	9,5	10	14,5	15,5
Isolamento entre as saídas	dB	>20	>20	>20	>20	>20
Perdas de retorno	dB	>10	>10	>10	>10	>10
Passagem de corrente	mA	800	800	800	800	800



RF 13 / RF 14



RF 16 / RF 18