



## Digital Acceleration Decoder D-AD-4N

### Ultrafast FPGA-based Digital Signal Processing

Optomet Vibrometers feature an end-to-end FPGA-based digital signal processing allowing a fully digital read-out of the measurement data. Digital signal processing avoids any drawbacks of analog demodulation which may result from component aging, temperature dependencies, noise and non-linearities. Significantly higher sensitivity, better resolution, and stability are the benefits of OptoMET's end-to-end digital signal processing. Extremely low noise levels produce precise results even from poorly reflecting measurement objects.



#### HIGHLIGHTS:

- Digital decoder
- 9 acceleration measuring ranges
- Frequency range: 0 Hz - 10 MHz
- Max. acceleration 76,800,000 g
- Best acceleration resolution 90  $\mu\text{g} / \sqrt{\text{Hz}}$ \*

### High-Frequency Acceleration Decoder

All vibrometers series feature by default a velocity decoder and can be supplemented with a suitable displacement and/or acceleration decoder.

The D-AD-4N acceleration decoder enables acceleration measurements up to 76,800,000 g at a maximum of 10 MHz and 12 m/s.  
Required velocity decoder: D-VD-4N

\* The resolution is defined as the signal amplitude (rms) that produces 0 dB signal/noise ratio with 1 Hz spectral resolution at 50 % fmax.

## Technical data

<b>Pos.</b>	<b>Full Scale Output (Peak)</b> <b>g</b>	<b>Max. Frequency</b> <b>kHz</b>	<b>Max. Velocity</b> <b>m/s</b>
1	392	25	12
2	1,560	50	12
3	7,800	100	12
4	39,200	250	12
5	156,000	500	12
6	784,000	1,000	12
7	2,350,000	1,500	12
8	7,840,000	2,500	12
9	76,800,000	10,000	12