



Digital Velocity Decoder D-VD-3

Ultrafast FPGA-based Digital Signal Processing

Optomet Vibrometers feature an end-to-end FPGA-based digital signal processing allowing a fully digital read-out of the measurement data. Digital signal processing avoids any drawbacks of analog demodulation which may result from component aging, temperature dependencies, noise and non-linearities. Significantly higher sensitivity, better resolution, and stability are the benefits of OptoMET's end-to-end digital signal processing. Extremely low noise levels produce precise results even from poorly reflecting measurement objects.



HIGHLIGHTS:

- Digital decoder
- 11 velocity measuring ranges
- Frequency range: 0 Hz - 2.5 MHz
- Max. velocity up to 10 m/s
- Resolution down to $6 \text{ nm s}^{-1}/\sqrt{\text{Hz}}$

High Speed Velocity Decoder

All vibrometers series feature by default a velocity decoder and can be supplemented with a suitable displacement and/or acceleration decoder.

The D-VD-3 high-speed velocity decoder with 11 measuring ranges can measure from 6 nm/s to 10 m/s. The maximum permissible acceleration is 16,000,000 g, and the working frequency range is between DC and 2.5 MHz. It is thus suitable for both high-frequency measurements in microsystems engineering as well as for structural dynamics investigations with large vibration amplitudes, e.g. in the automotive industry.

Technical data

| Pos. | Full Scale Output (Peak) m/s | Typical Resolution* $\mu\text{m s}^{-1} / \sqrt{\text{Hz}}$ | Signal Frequency Range kHz | Max. Acceleration g |
|------|---------------------------------|--|-------------------------------|------------------------|
| 1 | 0.01 | 0.006 | 25 | 160 |
| 2 | 0.02 | 0.008 | 50 | 640 |
| 3 | 0.05 | 0.015 | 100 | 3,200 |
| 4 | 0.1 | 0.035 | 250 | 16,000 |
| 5 | 0.2 | 0.08 | 500 | 64,000 |
| 6 | 0.5 | 0.20 | 1,000 | 320,000 |
| 7 | 1 | 0.26 | 1,500 | 960,000 |
| 8 | 2 | 0.35 | 2,500 | 3,200,000 |
| 9 | 5 | 0.37 | 2,500 | 8,000,000 |
| 10 | 8 | 0.37 | 2,500 | 12,800,000 |
| 11 | 10 | 0.38 | 2,500 | 16,000,000 |

* The resolution is defined as the signal amplitude (rms) that produces 0 dB signal/noise ratio with 1 Hz spectral resolution at 50 % f_{max} .

