



#### **Applications**







**Covered car parks** 


Large surfaces



Spe	cifications (Series lumin	aires)			Ξ
4	Voltage (V)	220-240V	$\longrightarrow$	Measures	2x-1.570x125x88mm
Hz	Frecuency (Hz)	50-60Hz		Weight	2.6Kg
	Current (A)	400mA			·
φ	Power factor (Cos fi)	0.96	- Atc	Operating temperature	-20~+35°C
-)	LED number	120			
$\bigcirc$	Dimming	No	ф	Flux (lm)	8692lm
		,			,
00	IP Tightness index	IP65		Electrical isolation	CI
)L	IK Impact resistance	IK08			
$\odot$	Body color	Light grey		Lifetime	L70B10>50.000h
1/1	Diffuser Material	PC-O			
[;	Body	PC			
			<del></del>		
K	Colour temperature	5.000K			

#### **Dimensions**





References														
	<b>₩</b>	W	Ţ	ф <sub>LED</sub>	ф <sub>ьим</sub>	-)	K	<b>∀</b>	$\longleftrightarrow$					
550741	2 × 37	76W	400mA	10107lm	8692lm	120	5.000K	>80	2x-1.570x125x 88mm					



#### On request





Emergency kit 3h (mod. 1x/2x 1.200mm/1.500mm)



Presence and brightness sensor (mod. 1x/2x 1.200mm/1.500mm)



Regulation 1-10V

Dali



>80 4.000K

#### **Accessories**





#### 378406

SET OF 10 PLASTIC CLIPS BERLIN ECO T8 1500MM



Technologies Property of the control of the control



#### **Overstorm**



OVERSTORM technology is designed for those luminaires that normally face electrically aggressive environments. It provides the product with three spheres of protection: In the outer sphere, an independent surge protector suppresses eventual voltage surges, in the intermediate sphere the drivers are prepared to withstand voltage peaks of up to 6 kV and 10kV. In the nuclear sphere, the protection in the LED module is provided both at its input, for small surges that have not been filtered by the external spheres.

### Warning



You need DALI drive



Solutions S



#### description



The CORA device in its three versions; INDUSTRY UNIT, INDUSTRY and CORA INDUSTRY MASTER controls the lighting of new or even existing installations thanks to wireless technology such as BLUETOOTH 5.0

#### Info



For more information on the different solutions compatible with this luminaire, consult the following BIDI codes or on the web www.prilux.es