



### **Applications**







Covered car parks


Large surfaces



Spe	cifications (Series lumin	aires)						
\$	Voltage (V)	220-240V	$\overline{\longleftrightarrow}$	Measures	1x-1.270x85x88mm			
Hz	Frecuency (Hz)	50-60Hz		Weight	2.6Kg			
	Current (A)	390mA			,			
φ	Power factor (Cos fi)	0.95	Atc.	Operating temperature	-20~+35°C			
<u>-                                     </u>	LED number	48						
$\bigcirc$	Dimming	No	Ф_	Flux (lm)	3.558lm			
0 0	IP Tightness index	IP65		Electrical isolation	CI			
\L	IK Impact resistance	IK08						
$\odot$	Body color	Light grey		Lifetime	L70B10>50.000h			
14	Diffuser Material	PC-O						
	Body	PC						
		'						
K	Colour temperature	5.000K						

## **Dimensions**





References														
	<b>V</b> LED	W		ф <sub>LED</sub>	ф	- <u>`</u>	K	Ą	$\longleftrightarrow$					
550833	1 x 30	32W	390mA	4.043lm	3.558lm	48	5.000K	>80	1x-1.270x85x8 8mm					



### On request





Emergency kit 3h (mod. 1x/2x 1.200mm/1.500mm)



Presence and brightness sensor (mod. 1x/2x 1.200mm/1.500mm)



Regulation 1-10V

Dali



>80 4.000K

**Accessories** 





### 378376

SET OF 8 PLASTIC CLIPS BERLIN ECO T8 1200MM



Technologies ###



#### **Overstorm**



OVERSTORM technology is designed for those luminaires that normally face electrically aggressive environments. It provides the product with three spheres of protection: In the outer sphere, an independent surge protector suppresses eventual voltage surges, in the intermediate sphere the drivers are prepared to withstand voltage peaks of up to 6 kV and 10kV. In the nuclear sphere, the protection in the LED module is provided both at its input, for small surges that have not been filtered by the external spheres.

## Warning



You need DALI drive



Solutions S



### description



The CORA device in its three versions; INDUSTRY UNIT, INDUSTRY and CORA INDUSTRY MASTER controls the lighting of new or even existing installations thanks to wireless technology such as BLUETOOTH 5.0

### Info



For more information on the different solutions compatible with this luminaire, consult the following BIDI codes or on the web www.prilux.es