





Applications









Roads

Motorways

Parks









Viaducts

Residential Areas

Tunnels



Certifications













Pedestrian Zones

Cycle lanes

Car parks





| Spe | cifications (Series lumina | aires) | | | 듣 |
|--|----------------------------|-----------|------------------|-----------------------|-------------------|
| 4 | Voltage (V) | 220-240V | | Measures | 318 a 408x116mm |
| Hz | Frecuency (Hz) | 50-60Hz | | | |
| | Current (A) | 350mA | | Operating temperature | -40~+50°C |
| φ | Power factor (Cos fi) | 0.9 | | | - |
| -\ | LED number | 12 | ф _{ьим} | Flux (lm) | 1.847lm |
| \bigcirc | Dimming | 8N - DALI | | | ' |
| | Comm. Prot. for reprogr. | CMR | | Electrical isolation | CI |
| | | | | | |
| K | Colour temperature | 3.000K | (270 | Lifetime | L90 B10 >200.000h |
| \\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\ | CRI Colour rendering index | >70 | φ / W | Efficacy | 139lm/W |
| | Optical | VA00L1P | | | |

Prilux guarantees a ± 10% tolerance in light flux measurements.

Dimensions








| References | | | | | | | | | | | | | |
|------------|------------------|-------|-------|---------|---------|---------|---------|-----------|--------|--|--|--|--|
| | V _{LED} | W | | ф | ф | ф | ф/W | <u>-\</u> | K | | | | |
| 570909 | 12W | 13,3W | 350mA | 2.292lm | 2.099lm | 1.847lm | 139lm/W | 12 | 3.000K | | | | |



Photometry





On request





Dali

Double Level with Line of Command



Class II

| K |
|------------|
| PCAmbar |
| >70 2.700K |
| >80 3.000K |
| >80 4.000K |
| >70 2.700K |



Available RAL colors (Consult)

| 深 |
|---------|
| S138L0M |
| S15011P |
| S150L0M |
| VA00I0P |
| VAOOLOM |
| VA01L0M |
| VA02L0M |
| VA03D0P |
| VA04D0P |
| VA05I0P |
| VA06I0P |
| VA07L0P |
| VA08L0M |



Light packages Solution

| | · | | P | PCA 722 | | 22 | 2 727 | | 730 | | 827 | | 830 | | 840 | |
|-------|----|-------|---------|--------------|---------|--------------|---------|---------|---------|---------|---------|---------|---------|---------|---------|--------------|
| W | -\ | | ф | φ / W | ф | φ / W | ф | φ/\/ | ф | ф⁄W | ф | φ/W | ф | ф⁄W | ф | φ / W |
| 13,3W | 12 | 350mA | 1.022lm | 77lm/W | 1.475lm | 111Im/W | 1.738lm | 131lm/W | 1.846lm | 139lm/W | 1.571lm | 118lm/W | 1.571lm | 118lm/W | 1.655lm | 124lm/W |



Technologies







Overstorm



SystemShield



OVERSTORM technology is designed for those luminaires that normally face electrically aggressive environments. It provides the product with three spheres of protection: In the outer sphere, an independent surge protector suppresses eventual voltage surges, in the intermediate sphere the drivers are prepared to withstand voltage peaks of up to 6 kV and 10kV. In the nuclear sphere, the protection in the LED module is provided both at its input, for small surges that have not been filtered by the external spheres.

SYSTEMSHIELD technology is designed to guarantee the hours of useful life of luminaires installed in environments where exceeding the maximum operating temperature is possible and even probable. Using thermal probes, the luminaire knows its operating temperature at all times.



CMR



CMR (CORA MANAGER READY) identifies the prilux luminaires compatible with the CORA MANAGER system that provides the luminaires with control, regulation and programming.

Warning



UNIVERSAL GROUPE OPTIQUE a été testé avec succès dans notre laboratoire dans 35°C température villa type de chambre lanterne.



Solutions S



description



One of the key pieces to achieve the pathtowards smart cities is lighting. Lighting management systems are advancing by leapsand bounds, prioritizing primary objectives such as service quality, cost reduction and care for the environment. CORA Manager is the control system developedby Prilux that, together with our compatible luminaires that provides intelligent management of public lighting, maintaining harmony between sustainable development and quality of life forcitizens, while promoting safety and saving.

Info



For more information on the different solutions compatible with this luminaire, consult the following BIDI codes or on the web www.prilux.es