### **Arisa Top 1** 573399







#### **Applications**









Roads

**Parks** 

**Viaducts** 







**Residential Areas** 

**Pedestrian Zones** 

Cycle lanes



Certifications



















Spe	cifications (Series lumin	aires)			Ξ
4	Voltage (V)	220-240V	$\overline{\longleftrightarrow}$	Measures	478x478x546mm
Hz	Frecuency (Hz)	50-60Hz	Q /kg	Weight	8Kg
	Current (A)	500mA		Wind Resistance	0,188m2
φ	Power factor (Cos fi)	0.94			·
<u>'</u>	LED number	12	Atc	Operating temperature	-40~+50°C
$\bigcirc$	Dimming	8N - DALI			
0	Comm. Prot. for reprogr.	CMR	ф	Flux (lm)	2.632lm
		,			,
L O	IP Tightness index	IP66		Electrical isolation	CI
L L	IK Impact resistance	IK09			·
$\odot$	Body color	9007		Lifetime	L90 B10 >200.000h
11/	Diffuser Material	VT-T	φ/w	Efficacy	140lm/W
	Body	AL iap			
		-			
K	Colour temperature	4.000K			
Ø	CRI Colour rendering index	>70	Prilux	guarantees a ± 10% tolerance in	light flux measurements.
<del>ڳ</del>	Optical	VA00K0M			

#### **Dimensions**








References													
	<b>V</b> LED	W	<del></del>		ф <sub>LED</sub>	ф	ф/W	- <u>'</u>	K				
573399	18W	18,8W	500mA	3.310lm	3.171lm	2.632lm	140lm/W	12	4.000K				

## **Arisa Top 1** 573399



#### **Photometry**





On request





Class II



Double Level with Line of Command



PC-T (IK10)

K
PCAmbar
>70 2.700K
>80 3.000K
>80 4.000K
>70 2.700K



VA00I0P

VA00L0M

VA01L0M

VA02L0M

VA03D0P

VA04D0P

VA05I0P

VA06I0P

VA07L0P

VA08L0M




#### Light packages



		PCA		722		727		730		827		830		840		
W	-11-		ф	φ⁄W	ф	φ <b>/</b> W	ф	<b>∳</b> /W	ф	φ <b>/</b> W	ф	φ <b>/</b> W	ф	φ <b>/</b> W	ф	φ/W
18,8W	12	500mA	1.373lm	73lm/W	2.032lm	108lm/W	2.355lm	125lm/W			2.164lm	115lm/W	2.164lm	115lm/W	2.281lm	121lm/W

Mounting "I





Accessories

3 "

3 \*\*\*

...

586573

KIT ADAP. A POSTE Ø33MM ARISA TOP 581417

KIT ADAP. A POSTE Ø42MM ARISA TOP 579827

KIT ADAP. A POSTE Ø50MM ARISA TOP 501743

KIT ADAP. A POSTE Ø76MM POLIVALENTE TECN. RAL9007T



Technologies Establishment 
E





#### **Overstorm**



#### SystemShield



OVERSTORM technology is designed for those luminaires that normally face electrically aggressive environments. It provides the product with three spheres of protection: In the outer sphere, an independent surge protector suppresses eventual voltage surges, in the intermediate sphere the drivers are prepared to withstand voltage peaks of up to 6 kV and 10kV. In the nuclear sphere, the protection in the LED module is provided both at its input, for small surges that have not been filtered by the external spheres.

SYSTEMSHIELD technology is designed to guarantee the hours of useful life of luminaires installed in environments where exceeding the maximum operating temperature is possible and even probable. Using thermal probes, the luminaire knows its operating temperature at all times.



#### **CMR**



CMR (CORA MANAGER READY) identifies the prilux luminaires compatible with the CORA MANAGER system that provides the luminaires with control, regulation and programming.



Solutions S



#### Was Outdoor

### Cora Manager

#### description



WAS (White Adaptive System) technology provides PRILUX luminaires with the ability to change both the amount of light they provide and the correlated color temperature, CCT. WAS (White Adaptive System) technology provides PRILUX luminaires with the ability to change both the amount of light they provide and the correlated color temperature



#### **Safelight**

#### description



SAFELIGHT allows the lighting of zebra crossings with road luminaires adapted with special optics for this application that illuminate with white light with a continuous level of 100%

#### description



One of the key pieces to achieve the pathtowards smart cities is lighting. Lighting management systems are advancing by leapsand bounds, prioritizing primary objectives such as service quality, cost reduction and care for the environment. CORA Manager is the control system developedby Prilux that, together with our compatible luminaires that provides intelligent management of public lighting, maintaining harmony between sustainable development and quality of life forcitizens, while promoting safety and saving.

#### Info



For more information on the different solutions compatible with this luminaire, consult the following BIDI codes or on the web www.prilux.es