

CONVERTER CASAMBI | CASAMBI TO PHASE

CONVERTER CASAMBI, CASAMBI to PHASE

The lighting control device CONVERTER CASAMBI TO PHASE is designed for the control of lighting systems and enables the integration of CASAMBI wireless technology into phase-cut dimmer applications. It is suitable for installation in electrical systems to enable wireless lighting control. The device supports the conversion of CASAMBI control signals into phase-cut dimming, allowing flexible and convenient light regulation in various environments.

Item no.	1012593
Lamps included	No
IP Code	IP20
Assembly	Recessed
Assembly details	Ceiling,Wall,
Dimmable	true
Dimming technology	trailing edge
Primary nominal voltage	220-240V ~ 50/60Hz
Safety class	II
Safety class	II
Minimum ambient temperature	-20°C
Maximum ambient temperature	40°C
Color	white
Length	4.5 cm
Width	4.5 cm
Height	2.2 cm
Net weight	0.06 kg
Gross weight	0.06 kg