

# LED bridge driver

**42 W, 700 mA for NUMINOS®, including radio interface for RF module, DALI**

Dimmable DALI LED bridge driver with 700 mA constant current and an output of 12 Watts including radio interface for the RF module with either Zigbee or Casambi. The LEDs must be connected in series.

## TECHNICAL DATA

| | |
|---|---|
| **Item no.** | 1006460 |
| **IP Code** | IP20 |
| **Dimmable** | Yes |
| **Dimming technology** | DALI,Touch |
| **Primary nominal voltage** | 220-240V ~50/60 Hz |
| **Secondary power / voltage** | 500-1050 |
| **Safety class** | II |
| **Safety class** | II |
| **Wattage** | 48.3 W |
| **Minimum ambient temperature** | -20 °C |
| **Maximum ambient temperature** | 45 °C |
| **Number of luminaires at LS B16A** | 23 |
| **Number of luminaires at LS C16A** | 23 |
| **Level of inrush current** | 20 A |
| **Duration of inrush current** | 30 µs |
| **Color** | white |
| **Length** | 12.3 cm |
| **Width** | 7.9 cm |
| **Height** | 3 cm |
| **Depth** | 0 cm |
| **Net weight** | 0.29 kg |
| **Gross weight** | 0.306 kg |

## Accessories

| | |
|---|---|
| 1006454 | RF module Casambi for LED bridge driver , single colour |
| 1006199 | RF module Zigbee for DALI LED bridge driver , single colour |