



3,500 watts of direct power to power two air conditioners (e.g. Dometic B 1600PLUS, B 2200, B 3200) or other devices requiring 230 volt alternating current. Powerful petrol engine (9.0 HP).

- Quality characteristics
- Remote Control
 - 12 V voltage for battery charger
 - Automatic switch-off in case of low oil level
 - Electric Ignition
 - Electric starter
 - Overload and short circuit protection
 - Sound absorbing housing
 - High continuous power
 - Suitable, for example, for operation of two air conditioners Dometic B 2200
 - Powerful motor
 - Remote control for displaying all the parameters of working
 - Fueled with unleaded petrol

Certifications
EC, E3

Non-binding images and technical data.

Characteristic	Value
Phase	Single phase
Maximum power single phase (KW)	3.8
Continuous power single phase (KW)	3.5
Fuel	Gasoline
Frequency (Hz)	50
Voltage (V)	230
Engine	Honda GX270
Starting system	Manual / Electric
Cooling	Air
Poles	2
Consumption (L/h)	2.3
Acoustic power	89 dB(A)
Acoustic pressure	62 dB(A) at 7 m
Length (mm)	660
Width (mm)	480
Height (mm)	355
Dry weight (Kg)	102
Silenced	Yes
Super silenced	Yes
Net power (kW)	6.6
Brushes	No
Voltage regulator	No
Engine manufacturer	Honda

Short description

Fuel: Petrol
Phase: Single Phase
Maximum output (kW): 3.8
Continuous output (kW): 3.5
Voltage (V): 230
Frequency (Hz): 50
Engine: Honda GX270
Consumption (Lt/h): 2.3
Lenght (mm): 660
Width (mm): 480
Altezza (mm): 355
Dry Weight (Kg): 102