



MBJ2R345U LTE

Indoor multi-input amplifier to mix and amplify signals coming from different aerials
The whole range is equipped with the innovative A.B.L.A. (Automatic Building Level Adjustment) feature, able to keep constant the TV output level (set through the dedicated trimmers), even when the input signal level changes.

ITEM	MBJ2R345U LTE/..*	
Item	MBJ2r345U LTE	
Code	223603	
Code	223604	
Input no.	4	
Band	III+DAB , IV , V , UHF , ...	
Gain	(dB)	20, 20, 20, 20
Gain adjustment	(dB)	20, 20, 20, 20
Noise figure	(dB)	6, 9, 9, 9
Output level	(dBµV)	110, 115