

Channel attenuators

SF4-SF5



For connection after the aerial and before any amplifiers. For two or more sections which can be tuned to different frequencies or to the same frequency if greater attenuation is required. To tune, turn the core of the trimmer. D.C. through-line (apart from SF5).

Main Specifications

- The various sections are independent and do not affect each other

		SF4	SF5
Fracarro code		226707	226708
Inputs	No.	1	1
Impedance	Ω	75	75
Input 1	Band	IV	V
Insertion loss input 1 to output	dB	0.5	0.5
Bandwidth	MHz	470-590	610-862
Notch	No.	2	2
Notch selectable channels		E21-E35	E38-E69
Input Return Loss	dB	10	10
Outputs	No.	1 + DC pass	1
Main Features			
Operating temperature	$^{\circ}\text{C}$	-10 to +55	
Connector	type	F female	

Fracarro Code	Item	Packaging	EAN code	Quantity	Dimensions	Net weight	Total weight
				Pcs	mm	Kg	Kg
226707	SF4	Single	8016978018055	1	28x78x20	0.054	0.054
		Multiple		10	45x80x170	0.540	0.540
226708	SF5	Single	-	1	28x78x20	0.054	0.054