

Program your Bluetooth remote

Unpair and pair your remote with your TV Box

Unpair the remote with the TV Box:

- 1 Hold down the **tv box**  and **del** buttons together for three seconds until **tv box**  blinks twice.
- 2 Your Bluetooth remote is unpaired.

Pair the remote with the TV Box:

- 1 Point your Bluetooth remote at the TV Box.
- 2 Press any key (except **tv**  and **input**) and release it while continuing to point your remote at the TV Box.

Program your remote to control your TV

- 1 With your TV turned on, press and hold the **tv**  and **ok** buttons together for 3 seconds.
- 2 When the **tv**  button blinks twice and stays on, release both buttons.
- 3 Enter the 4-digit code for your TV brand. The  **tv** button blinks twice and stays on. If the button blinks several times, repeat the process.
- 4 Press and hold the **tv**  button until your TV turns off. If the button blinks several times, try the process again.

If you're still unable to program your remote, contact our support team by visiting support.google.com/fiber or calling (866) 777-7550.

For more information, visit support.google.com/fiber and search for "Bluetooth remote."

Google fiber

BRAND	CODE	BRAND	CODE	BRAND	CODE	BRAND	CODE	BRAND	CODE	BRAND	CODE	BRAND	CODE
Abex	14	Chung Hsin	547	Futuretech	1064	Jean	1424	National	1942	Revolution	3503	Tagar Systems	2831
ABS	16	Cinema	555	Gateway	1076	Jensen	1429	NEC	1950	Ricavision	2388	Tandy	2843
Acer	28	Cineral	559	GE	1081	Jiahua	1435	NetTV	1967	Rowa	2416	Tashiko	2850
Action	33	Citizen	567	GFM	3820	Jinfeng	1438	Newave	1981	Runco	2423	Tatung	2852
Admiral	46	Clarion	575	Gibralter	1114	Jinxing	1442	Newsonic	4299	Sampo	2446	TCL	2856
Advent	54	Coby	597	Gibson	4294	JVC	1464	Nexus El	3948	Samsung	2448	Teac	2860
Adventura	55	Com Solu	61	Go Video	1126	Kangli	1478	Nikko	2000	Samsux	2449	Technics	2869
Aiko	69	Concerto	625	GoldStar	1140	KDS	1494	Nimbro	4065	Sansei	2457	Technika	2870
Aiwa	72	Conrowa	634	GPX	1150	KEC	1496	Nive Med	2012	Sansui	2458	Technol Ace	2875
Akai	74	Contec	635	Gradiente	1151	Ken Brown	1499	Noblex	2013	Sanyo	2462	Techview	2883
Alaron	85	Continental	4291	Grundig	1162	Kenwood	1507	Norcent	2020	Sanyuan	2464	Techwood	2884
Albatron	87	Craig	650	Grunpy	1165	Kioto	1523	Northgate	2027	Sceptre	2498	Teco	2886
Alfide	96	Crosley	655	Haier	1175	KLH	1529	Norw M	2029	Scimitsu	2505	Teknika	2895
Alienware	99	Crown	658	Hallmark	1180	Kloss	1532	NTC	2045	Scotch	2506	Telefunken	2914
Amer Act	123	Crown Mustang	659	Hankook	1188	Kolin	1541	NuVision	2053	Scott	2508	Thomas	2971
Ampro	139	Curtis	666	Hanns.G	3478	Konka	1548	Olevia	2067	Sears	2514	Thomson	2972
Anam	146	Curtis Mathes	667	Hannspree	1189	Kreisen	1568	Onida	2081	Semp	2530	Tiane	2980
Anam Nat	147	CXC	670	Harley Davi	1197	KTV	1572	Onwa	2087	Shaofeng	2549	TMK	2994
Anhua	153	CyberPower	674	Harman/Kard	1198	Kunlun	1578	Oppo	2092	Sharp	2550	TNCi	2996
AOC	165	Cytron	680	Harvard	1202	LG	1628	Optimus	2095	Shen Ying	2552	Tobo	2999
Aomni	3555	Daewoo	692	Hauptauge	1206	Linksys	1640	Optoma	2097	Shencai	2553	Toshiba	3021
Apex Digital	170	Daytron	710	Havermy	1208	Lloyd's	1648	Optonica	2099	Sheng Chai	3922	Totevision	3024
Apple	172	Dayu	711	Helios	1219	Logik	1661	Orion	2111	Sheng Chia	2554	Touch	3025
Astar	218	Dell	725	Hello Kitty	1221	Luxman	1682	Otic	2125	Sherwood	2557	TruTech	3467
Audiovox	268	Denon	731	Heran	3828	LXI	1686	Panasonic	2153	Shogun	2568	TVS	3081
Aventura	287	Diam Vision	748	Herosonic	4295	M & S	1687	Panda	2155	Signature	2582	Ultra	3093
Baile	310	Digisonic	4292	Hewlett Pack	1229	MAG	1701	PARK	3951	Simpson	2598	Universal	3113
Bang & Olu	314	Digital Lifest	3567	Hikona	1237	Magnasoni	1704	Penney	2182	Sinotec	2600	US Logic	3124
Beijing	345	DirecTV	794	Hisense	1249	Magnavox	1706	Petters	2189	Skyworth	2631	Vector Res	3137
Belcor	348	Dumont	840	Hitachi	1251	Magnin	1708	Philco	2192	Sole	2655	Venturer	3143
Bell & How	350	Durabrand	842	Hongmei	1272	Majestic	1713	Philips	2195	Sony	2679	VEOS	3144
BenQ	359	Dwin	848	Howard Com	1281	Marantz	1724	Pilot	2207	Soundesign	2684	Victor	3155
BGH	3507	Dynex	3476	HP	1283	Mastro	1743	Pioneer	2212	Sova	2690	Videocon	3163
Blue Sky	395	Electroband	888	Huafa	1287	Matsushita	1751	Polaroid	2230	Sowa	2691	Vidikron	3178
BPL	413	Electrograph	889	Huari	1294	Maxent	1757	Polyvision	4304	Soyo	2693	Vidtech	3179
Bradford	414	Electrohome	890	Humax	1298	Media Cent	1777	Portland	2238	Spectroniq	2701	Viewsonic	3186
Brillian	422	Elektra	896	Huodateji	1302	Megapower	1791	Prima	2253	Squareview	2703	Viking	3188
Brockwood	430	Element	3477	Hush	1304	Megatron	1795	Princeton	2258	SSS	2708	Viore	3192
Broksonic	432	Emerson	917	Hyundai	1315	Memorex	1800	Prism	2261	Stack 9	2710	Vision	3198
Bush	445	Emprex	922	iBUYPOWE	1322	MGA	1811	Proscan	2279	Starlite	2728	Vizio	3211
Byd:sign	448	Encross	3815	I-Inc	3462	Microsoft	1826	Proton	2288	Studio Exp	2750	Voodoo	3215
Cailing	463	Envision	933	iLo	1341	Midland	1831	Protron	2289	SunBrite	2759	VU	4078
Candle	480	Epson	937	Imp Crown	1347	Mind	1837	Proview	2290	Superscan	2786	Wards	3231
Carnivale	491	ESA	943	Infinity	1352	Mintek	1845	Pulsar	2296	Supre-Macy	2794	Warumaia	3232
Carver	494	Fisher	1009	InFocus	1353	Minutz	1847	Pvision	2300	Supreme	2795	Waycon	3237
CCE	504	Fortress	1027	Initial	1356	Mitsubishi	1855	Qingdao	2308	SVA	2800	Westinghouse	3249
Celebrity	509	Frigidaire	1041	Insignia	1368	Monivision	1872	Quasar	2320	Sylvania	2809	Wharfedale	3255
Celera	510	Fujimaro	1050	Inteq	1373	Motorola	1878	Rad Shack	3547	Symphonic	2810	White	3258
Changcheng	526	Fujimaru	3575	IRT	1397	MTC	1889	Rad Shack	2333	Synco	2811	Westinghouse	
Changfeng	528	Fujitsu	1052	Janeil	1414	Mudan	1896	RCA	2351	Syntax	2814	Wyse	3288
Changhong	530	Funai	1056	JBL	1420	Multitech	1907	Realistic	2354	Systemax	2817	Yamaha	3326
Chun Yun	545	Furi	1057	JCB	1421	NAD	1926	Relon	3594	Tacico	2823	Yapshe	3329
												Zenith	3356
												ZT Group	3370