



**NOTES:**

1. MAIN SWITCH SHALL BE RATED 200A (MIN).
2. A FULL-SIZED NEUTRAL SERVICE CABLE SHALL BE CONNECTED TO AN INSULATED NEUTRAL TERMINAL INSIDE THE METER BASE.
3. SUPPLY CABLE TO BE CONNECTED RED, WHITE, BLUE, LEFT TO RIGHT INSIDE THE MAIN SWITCH.
4. THE ELECTRICAL ROOM SHALL BE LOCKED. ACCESS MUST BE AVAILABLE AT ALL HOURS TO HALTON HILLS HYDRO PERSONNEL. OWNER SHALL PROVIDE ALL REQUIRED KEYS AND PASS CODES TO HALTON HILLS HYDRO INC. FOR ACCESS.
5. SERVICE ENTRANCE MAIN DISCONNECT DEVICE MUST BE LOCKABLE.
6. OPERATING HANDLE CLEARANCE MUST BE SUFFICIENT TO PROVIDE UNRESTRICTED OPERATION OF THE SERVICE ENTRANCE MAIN SWITCH.
7. CUSTOMER WIRING TO MEET ONTARIO ELECTRICAL SAFETY CODE REQUIREMENTS.
8. SEE HALTON HILLS HYDRO INC. CONDITIONS OF SERVICE, SECTION 2.3.8 "METERING" FOR ADDITIONAL DETAILS.
9. LAYOUT OF CUSTOMER OWNER ELECTRICAL EQUIPMENT SUBJECT TO ESA APPROVAL.

**INDUSTRIAL/COMMERCIAL UNDERGROUND INSTALLATION  
GS <50kW, 200A, 120/208V OR 347/600V  
SERVICE ENTRANCE EQUIPMENT AND METER INSTALLATION**