



World ToneTM

Mfrs. of : All Type of P.A. Systems (W.T.X.)

ISO Certified Manufacturing Co.

SUPER POWER PA MIXER AMPLIFIERS



WTX DJ -1600, DP

Power Supply AC : 220-240V, 50/60 Hz
Power Output : 1600W RMS, 1650W Max.
Frequency Response: 50Hz - 15,000Hz $\pm$ 1dB
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Mid : $\pm$ 10dB at 1kHz,
Treble : $\pm$ 10dB at 10kHz
Speaker Output : 2 Ω , 4 Ω , 8 Ω , 70V & 100V Line
Cooling : 1x Fan (120 x 120 mm)
Dimensions : W510 x D490 x H155 mm



MX-1200 DP

Power Supply : AC : 220-240V 50/60Hz
Power Output : 1200W RMS, 1300W Max.
Frequency Response: 50Hz - 15,000Hz $\pm$ 1dB
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Mid : $\pm$ 10dB at 1kHz,
Treble : $\pm$ 10dB at 10kHz
Speaker Output : 2 Ω , 4 Ω , 70V & 100V Line
Cooling : 1x Fan (120 x 120mm)
Dimensions : W515 x H155x D 400 mm
Special features Built-in MP3 player with remote control for USB, SD, MMC card.



WTX-10000, DP

Power Output : 1200W Max., 1000W RMS
Input Channels : 1 Line 200mV/100k Ω , 1 Line 1V/50k Ω
Frequency Response: 50-15,000Hz $\pm$ 3dB
Signal-to-Noise Ratio : 60Db
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Treble : $\pm$ 10dB at 10kHz
Speaker Outputs : 4 Ω , 70V & 100V
Power Supply : AC : 220-240V 50/60Hz DC: 36V (3x12V Car Battery)
Power Consumption : AC: 1000VA DC: 8A
Special features : Built-in MP3 player with remote control for USB, SD, MMC card.
Dimensions : W500 x H145x D410 mm



WTX- 8000, DP

Power Output : 1000W Max., 800W RMS
Input Channels : 1 x Line 200mV/100k Ω , 1 x Line 1V/50k Ω
Frequency Response: 50-15,000Hz $\pm$ 3dB
Signal-to-Noise Ratio : 60Db
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Treble : $\pm$ 10dB at 10kHz
Speaker Outputs : 2 Ω , 4 Ω , 70V & 100V
Power Supply : AC: 220-240V 50/60Hz DC: 36V (3x12V Car Battery)
Power Consumption : AC : 1000VA DC: 8A
Special features : Built-in MP3 player with remote control for USB, SD, MMC card.
Dimensions : W500 x H145x D410 mm



WTX- 10000, DP

Power Output : 1200W Max., 1000W RMS
Input Channels : 1 x Line 200mV/100k Ω , 1 x Line 1V/50k Ω
Frequency Response: 50-15,000Hz $\pm$ 3dB
Signal-to-Noise Ratio : 60Db
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Treble : $\pm$ 10dB at 10kHz
Speaker Outputs : 4 Ω , 70V & 100V
Power Supply : AC: 220-240V 50/60Hz DC: 36V (3x12V Car Battery)
Power Consumption : AC: 1000VA DC: 8A
Special features : Built-in MP3 player with remote control for USB, SD, MMC card.
Dimensions : W500 x H145x D410 mm



WTX-6000M, DP

Power Output : 800W Max., 600W RMS
Input Channels : 7 x Mic 0.8mV/4.7k Ω , 2 x Aux 100mV/470 k Ω , 1 x Line 1V/50k Ω
Frequency Response: 50-15,000Hz $\pm$ 3dB
Signal-to-Noise Ratio : 60Db
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Treble : $\pm$ 10dB at 10kHz
Outputs : Preamp 200mV/600 Ω , Line 1V/1k Ω Speaker Outputs 4 Ω , 8 Ω , 70V & 100V
Power Supply : AC: 220-240V 50/60Hz DC: 36V (3x12V Car Battery)
Power Consumption : AC: 1000VA DC: 8A
Special features : Built-in MP3 player with remote control for USB, SD, MMC card
Dimensions : W510 x H171 x D390 mm



WTX-5000M, DP

Power Output : 750W Max., 500W RMS
Input Channels : 7 x Mic 0.8mV/4.7k Ω , 2 x Aux 100mV/470 k Ω , 1 x Line 1V/50k Ω
Frequency Response: 50-15,000Hz $\pm$ 3dB
Signal-to-Noise Ratio : 60Db
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Treble : $\pm$ 10dB at 10kHz
Outputs : Preamp 200mV/600 Ω , Line 1V/1k Ω
Speaker Outputs : 4 Ω , 8 Ω , 70V & 100V
Power Supply : AC : 220-240V 50/60Hz DC: 36V (3x12V Car Battery)
Power Consumption : AC: 1000VA DC: 8A
Special features : Built-in MP3 player with remote control for USB, SD, MMC card.
Dimensions : W510 x H171 x D390 mm



WTX- 6001 EM, DP

Power Output : 800W Max., 550W RMS
Input Channels : 1 x Line 200mV/100k Ω , 1 x Line 1V/50k Ω
Frequency Response: 50-15,000Hz $\pm$ 3dB
Signal to Noise Ratio : 60Db
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Treble : $\pm$ 10dB at 10kHz
Speaker Outputs : 4 Ω , 8 Ω , 70V & 100V
Power Supply : AC : 220-240V 50/60Hz DC: 36V (3x12V Car Battery)
Power Consumption : AC: 1000VA DC: 8A
Special features : Built-in MP3 player with remote control for USB, SD, MMC card.
Dimensions : W510 x H171 x D390 mm



WTX- 5001 EM, DP

Power Output : 750W Max., 500W RMS
Input Channels : 1 x Line 200mV/100k Ω , 1 x Line 1V/50k Ω
Frequency Response: 50-15,000Hz $\pm$ 3dB
Signal to Noise Ratio : 60Db
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Treble : $\pm$ 10dB at 10kHz
Speaker Outputs : 4 Ω , 8 Ω , 70V & 100V
Power Supply : AC : 220-240V 50/60Hz DC: 36V (3x12V Car Battery)
Power Consumption : AC: 1000VA DC: 8A
Special features : Built-in MP3 player with remote control for USB, SD, MMC card.
Dimensions : W510 x H171 x D390 mm

SUPER POWER PA MIXER AMPLIFIERS



PBT-701

Power Supply : AC : 220-240V 50/60Hz
Power Output : 700W RMS
Frequency Response : 50Hz - 15,000Hz $\pm$ 1dB
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Mid : $\pm$ 10dB at 1kHz,
Treble : $\pm$ 10dB at 10kHz
Speaker Output : 2 Ω , 4 Ω , 70V & 100V Line
Cooling : 1x Fan (120 x 120mm) force cooling
Dimensions : 490W x 460D x 155H mm



PBT-501, DP

Frequency Response : 50 Hz - 15 kHz (+/-) 3 dB
Tone Controls : BASS/MID/TREBLE (+/-) 10 dB
Power Supply : 220-240V
Line Outputs : 1V / 1K ohm Line Input 1V / 50K ohm
Product Dimensions : 483 x 425 x 155 mm
Power Output : 500W RMS at 10% THD
S/N Ratio : 70 dBAC
Power Consumption : 800 VA
Amplifier Protection : AC Bi-Metal Circuit Breaker, Short Circuit & Over Temperature protection
Special features : Built-in MP3 player with remote control for USB, SD, MMC card.
Cooling : Force cooling 4" AC Fan



WTX- 350 DP

Power Output : 400 W Max., 350 W RMS
Input Channels : 6 $\times$ Mic 0.65mV/4.7k Ω , 2 $\times$ Aux 100mV/470 k Ω , 1 $\times$ Line 1V/50k Ω
Signal-to-Noise Ratio : 60dB
Frequency Response : 50-15,000Hz $\pm$ 3dB
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Treble : $\pm$ 10dB at 10kHz
Outputs : Preamp 200mV/600 Ω , Line 1V/1k Ω
Speaker Outputs : 4 Ω , 8 Ω , 70V & 100V
Power Supply : AC : 220-240V 50/60Hz
DC : 24V (2 $\times$ 12V Car Battery)
Power Consumption : AC : 460VA
DC : 6A



WTX- 300 DP

Power Output : 350W Max., 300W RMS
Input Channels : 6 $\times$ Mic 0.65mV/4.7k Ω , 2 $\times$ Aux 100mV/470 k Ω , 1 $\times$ Line 1V/50k Ω
Signal-to-Noise Ratio : 60dB
Frequency Response : 50-15,000Hz $\pm$ 3dB
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Treble : $\pm$ 10dB at 10kHz
Outputs : Preamp 200mV/600 Ω , Line 1V/1k Ω
Speaker Outputs : 4 Ω , 8 Ω , 70V & 100V
Power Supply : AC : 220-240V 50/60Hz
DC : 24V (2 $\times$ 12V Car Battery)
Power Consumption : AC : 460VA DC : 6A
Special features : Built-in MP3 player with remote control for USB, SD, MMC card
Dimensions : W450 $\times$ H160 $\times$ D340 mm



WTX- 250 DP

Power Output : 300W Max., 250W RMS
Input Channels : 6 $\times$ Mic 0.65mV/4.7k Ω , 2 $\times$ Aux 100mV/470 k Ω , 1 $\times$ Line 1V/50k Ω
Signal-to-Noise Ratio : 60dB
Frequency Response : 50-15,000Hz $\pm$ 3dB
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Treble : $\pm$ 10dB at 10kHz
Outputs : Preamp 200mV/600 Ω , Line 1V/1k Ω
Speaker Outputs : 4 Ω , 8 Ω , 70V & 100V
Power Supply : AC : 220-240V 50/60Hz
DC : 24V (2 $\times$ 12V Car Battery)
Power Consumption : AC : 460VA DC : 6A
Special features : Built-in MP3 player with remote control for USB, SD, MMC card
Dimensions : W450 $\times$ H160 $\times$ D340 mm



WTX- 350 DP, Echo

Power Output : 400 W Max., 350 W RMS
Input Channels : 6 $\times$ Mic 0.65mV/4.7k Ω , 2 $\times$ Aux 100mV/470 k Ω , 1 $\times$ Line 1V/50k Ω
Signal-to-Noise Ratio : 60dB
Frequency Response : 50-15,000Hz $\pm$ 3dB
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Treble : $\pm$ 10dB at 10kHz
Outputs : Preamp 200mV/600 Ω , Line 1V/1k Ω
Speaker Outputs : 4 Ω , 8 Ω , 70V & 100V
Power Supply : AC : 220-240V 50/60Hz
DC : 24V (2 $\times$ 12V Car Battery)
Power Consumption : AC : 460VA DC : 6A
Special features : Built-in MP3 player with remote control for USB, SD, and MMC card. Echo with 2- mic operation. Delay digital system Digital signal processing. Delay range setting 60-300ms
Dimensions : W450 $\times$ H160 $\times$ D340 mm



WTX- 300 DP, Echo

Power Output : 350W Max., 300W RMS
Input Channels : 6 $\times$ Mic 0.65mV/4.7k Ω , 2 $\times$ Aux 100mV/470 k Ω , 1 $\times$ Line 1V/50k Ω
Signal-to-Noise Ratio : 60dB
Frequency Response : 50-15,000Hz $\pm$ 3dB
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Treble : $\pm$ 10dB at 10kHz
Outputs : Preamp 200mV/600 Ω , Line 1V/1k Ω
Speaker Outputs : 4 Ω , 8 Ω , 70V & 100V
Power Supply : AC : 220-240V 50/60Hz DC : 24V (2 $\times$ 12V Car Battery)
Power Consumption : AC : 460VA DC : 6A
Special features : Built-in MP3 player with remote control for USB, SD, MMC card. Echo with 2- mic operation Delay digital system Digital signal processing Delay range setting 60-300ms
Dimensions : W450 $\times$ H160 $\times$ D340 mm



WTX- 250 DP, Echo

Power Output : 300W Max., 250W RMS
Input Channels : 6 $\times$ Mic 0.65mV/4.7k Ω , 2 $\times$ Aux 100mV/470 k Ω , 1 $\times$ Line 1V/50k Ω
Signal-to-Noise Ratio : 60dB
Frequency Response : 50-15,000Hz $\pm$ 3dB
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Treble : $\pm$ 10dB at 10kHz
Outputs : Preamp 200mV/600 Ω , Line 1V/1k Ω
Speaker Outputs : 4 Ω , 8 Ω , 70V & 100V
Power Supply : AC : 220-240V 50/60Hz
DC : 24V (2 $\times$ 12V Car Battery)
Power Consumption : AC : 460VA DC : 6A
Special features : Built-in MP3 player with remote control for USB, SD, and MMC card. Echo with 2- mic operation. Delay digital system. Digital signal processing. Delay range setting 60-300ms
Dimensions : W450 $\times$ H160 $\times$ D340 mm



WTX-160 M DP

Power Output : 218 W Max., 160W RMS
Output Regulation : $\leq$ 2 dB, no load to full load at 1kHz
Input Channels : 5 $\times$ Mic 0.65mV/4.7k Ω , 2 $\times$ Aux 100mV/470k Ω , 1 $\times$ Line 1V/50k Ω
Signal-to-Noise Ratio : 60dB
Frequency Response : 50-15,000Hz $\pm$ 3dB
Tone Controls : Bass : $\pm$ 10dB at 100Hz,
Treble : $\pm$ 10dB at 10kHz
Output : Preamp 200mV/600 Ω , Line 1V/1k Ω
Speaker Output : 4 Ω , 8 Ω , 70V & 100V
Power Supply : AC : 220-240V 50/60Hz
DC : 24V (2 $\times$ 12V Car Battery)
Power Consumption : AC : 300VA DC : 4A
Dimensions : W420 $\times$ H155 $\times$ D320 mm

SUPER POWER PA MIXER AMPLIFIERS



WTX-120 DP

Power Output : 160W Max., 120W RMS at 10% THD
Input Channels : 5 x Mic 0.65mV/4.7kΩ, 2 x Aux 100mV/470 kΩ
Output Regulation : ≤ 2 dB, no load to full load at 1kHz
Frequency Response : 50-15,000Hz ±3dB
Signal-to-Noise Ratio : 60dB
Tone Controls : Bass : ±8dB at 100Hz,
Treble : ±8dB at 10kHz
Output : Preamp 200mV/600Ω, Line 1V/1kΩ
Speaker Outputs : 4Ω, 8Ω, 16Ω, 70V & 100V
Digital Player : MP3 Player with USB, SD and MMC Card Reader
Power Supply : AC: 220-240V 50/60Hz
DC: 12V (12V Car Battery)
Power Consumption : AC: 250VA DC: 5.5A
Dimensions : W420 x H155 x D320 mm



WTX-80 DP

Power Supply : AC : 220-240V 50/60Hz,
DC: 12V (2x 12V Car Battery)
Power Output : 80W RMS, 90W Max.
Input Channels : 5x MIC 0.60mV/4.7kΩ,
2x AUX 100mV/330kΩ
Frequency Response : 50Hz - 15,000Hz ± 3dB
Tone Controls : Bass : ± 10dB at 100Hz (Cut-Boost Type),
Treble : ± 10dB at 10kHz (Cut-Boost Type)
Outputs : Preamp 200mV/600Ω, Line 1V/1kΩ
Speaker Output : 4Ω, 8Ω, 16Ω, 70V & 100V Line
Digital Player : MP3 Digital Player
with USB/SD/BT/FM & Remote
ECHO (FX) : ECHO with Delay Repeat function
(available in RSA-80FXDP only)
Dimensions : 355W x 285D x 133H mm



WTX-60 DP

Power Output : AC: 220-240V 50/60Hz,
DC: 12V (12V Car Battery)
Power Output : 65W RMS, 80W Max.
Input Channels : 4x MIC 0.60mV/4.7kΩ,
2x AUX 50mV/470kΩ & 150mV/470kΩ
Frequency Response : 60Hz - 15,000Hz ± 3dB
Tone Controls : Bass : ± 10dB at 100Hz (Cut-Boost Type),
Treble : ± 10dB at 10kHz (Cut-Boost Type)
Outputs : Line 500mV/1kΩ
Speaker Output : 4Ω, 8Ω, 16Ω & 100V Line
Digital Player : MP3 Digital Player
with USB/SD/BT/FM & Remote
Dimensions : 355W x 295D x 133H mm



WTX-45 M DP

Power Supply : AC: 220-240V 50/60Hz,
DC: 12V (12V Car Battery)
Power Output : 45W RMS, 50W Max.
Input Channels : 3x MIC 0.50mV/4.7kΩ,
2x AUX 50mV/470kΩ & 150mV/470kΩ
Frequency Response : 100Hz - 13,000Hz ± 3dB
Speaker Output : 4Ω, 8Ω, 16Ω & 100V Line
Digital Player (DP) : MP3 Digital Player
with USB/SD/BT/FM & Remote
Dimensions : 280W x 270D x 120H mm

DOUBLE CHANNEL POWER MIXER AMPLIFIERS



S PA -5500

Power Supply : AC: 220V 50/60Hz
Power : (STEREO MODE)
8Ω Power : 1600W + 1600W
4Ω Power : 2200W + 2200W
2Ω Power : 2750W + 2750W
8Ω Power : 4200W
4Ω Power : 5600W
Frequency Response : 20Hz - 20,000Hz ± 0.5dB
Cooling : Front to Rear Air Flow
Connectors : Input: 3 Pin XLR,
Output: Speakon (for each channel)
Dimensions : 480 W x 575 D x 165 H mm



S PA. 4500

Power Supply : AC: 220-240V 50/60 Hz
Power Output : 2750W + 2750W (2Ω),
2400W + 2400W Max.
Frequency Response : 30Hz - 20,000Hz
Tone Controls : Bass : ± 10dB at 100Hz, Mid: ± 10dB at 1kHz,
Treble : ± 10dB at 10kHz (for each channel)
Speaker Output : Speakon Socket & Output Terminals
(for each channel)
Cooling : 2x Fan (120 x 120 mm)
Dimensions : 565W x 505D x 155H mm



Q S. 3.5 (3K2)

Power Supply : AC: 220-240V 50/60 Hz
Power Output : 1800W + 1800W (2Ω),
1850W + 1850W Max.
Frequency Response : 30Hz - 20,000Hz
Tone Controls : Bass : ± 10dB at 100Hz, Mid: ± 10dB at 1kHz,
Treble : ± 10dB at 10kHz (for each channel)
Speaker Output : Speakon Socket & Output Terminals
(for each channel)
Cooling : 2x Fan (120 x 120 mm)
Dimensions : 500W x 470D x 155H mm



Q S. 2.5 (2K2)

Power Supply : AC: 220-240V 50/60 Hz
Power Output : 1000W + 1000W (2Ω),
1100W + 1100W Max.
Frequency Response : 30Hz - 20,000Hz
Tone Controls : Bass : ± 10dB at 100Hz, Mid: ± 10dB at 1kHz,
Treble : ± 10dB at 10kHz (for each channel)
Speaker Output : Speakon Socket & Output Terminals
(for each channel)
Cooling : 2x Fan (120 x 120 mm)
Dimensions : 505W x 455D x 155H mm



SPA-2000

Power Supply AC : 220V 50/60 Hz, Power (STEREO MODE)
8 Ω Power 600W + 600W
4 Ω Power 800W + 800W
2 Ω Power 1000W + 1000W
8 Ω Power 1600W, 4 Ω Power 2000W
Frequency : 20Hz - 10,000Hz + 0.5dB
Cooling Fan : 4
Input : J2 + 3 Pin XLR
Output : speakon (For each channel)
Dimensions : W:505 H:140 D:495



SPA-3000

Power Supply AC : 220V 50/60 Hz
Power : (STEREO MODE)
8 Ω Power 850W + 850W
4 Ω Power 1100W + 1100W, 2 Ω Power 1500W + 1500W
8 Ω Power 1800W, 4 Ω Power 1300W
Frequency : 20Hz - 10,000Hz + 0.5dB
Cooling Fan : 4
Input : J2 + 3 Pin XLR
Output : Speakon (For each channel)
Dimensions : W:505 H:140 D:495

TWO ZONE MIXER AMPLIFIERS



TZA-10000 DP

Power Output : 750W + 750W Max., 500W + 500W RMS at 10% THD 450W + 450W RMS at 5% THD, 415W + 415W RMS at 2% THD

Input Channels : Mic/Aux: 6 × Mic 0.6mV/4.7kΩ, 2 × Aux 100 mV/470kΩ, Stereo Music Mode: L/R 200 mV/100kΩ, Line L/R 1V/50kΩ

Frequency Response: 50-15,000Hz ±3dB

Signal to Noise Ratio: 60dB

Speaker Outputs: 4Ω, 8Ω, 70V & 100V for each zone

Power Supply: AC: 220-240V 50/60 Hz DC: 36V (3×12V Car Battery)

Power Consumption: DC: 16A AC: 1600VA

Special Feature: Built in MP3 Player

Dimensions: W400 × H130 × D290 mm



TZA-7000 DP

Power Output : 500W + 500W Max., 350W + 350W RMS at 10% THD, 300W + 300W RMS at 5% THD, 280W + 280W RMS at 2% THD

Input Channels : 6 × Mic 0.6mV/4.7kΩ, 2 × Aux 100mV/470kΩ, Stereo Music

Frequency Response: 50-15,000Hz ±3dB

Signal to Noise Ratio: 60dB

Outputs: Preamp 200mV/600Ω, Line 1V/1kΩ

Dimensions: W 480 × H 170 × D490 mm



BTZ-10000 DP

Power Output : 750W + 750W Max., 500W + 500W RMS at 10% THD 450W + 450W RMS at 5% THD, 415W + 415W RMS at 2% THD

Input Channels : Mic/Aux: 6 × Mic 0.6mV/4.7kΩ, 2 × Aux 100 mV/470kΩ, Stereo Music Mode: L/R 200 mV/100kΩ, Line L/R 1V/50kΩ

Frequency Response: 50-15,000Hz ±3dB

Signal to Noise Ratio: 60dB

Speaker Outputs: 4Ω, 8Ω, 70V & 100V for each zone

Power Supply: AC: 220-240V 50/60 Hz DC: 36V (3×12V Car Battery)

Power Consumption: DC: 16A AC: 1600VA

Special Feature: Built in MP3

Dimensions: W400 × H130 × D290 mm



BTZ-10000 EX

Power Output : 750W + 750W Max., 500W + 500W RMS at 10% THD 450W + 450W RMS at 5% THD, 415W + 415W RMS at 2% THD

Input Channels : Mic/Aux: 6 × Mic 0.6mV/4.7kΩ, 2 × Aux 100 mV/470kΩ, Stereo Music Mode: L/R 200 mV/100kΩ, Line L/R 1V/50kΩ

Frequency Response: 50-15,000Hz ±3dB

Signal to Noise Ratio: 60dB

Speaker Outputs: 4Ω, 8Ω, 70V & 100V for each zone

Power Supply: AC: 220-240V 50/60 Hz DC: 36V (3×12V Car Battery)

Power Consumption: DC: 16A AC: 1600VA

Special Feature: Built in MP3

Dimensions: W400 × H130 × D290 mm



BTZ-7000 DP

Power Output : 90W + 90W Max., 60W + 60W RMS

Input Channels : 5 × Mic 0.6mV/4.7kΩ, 1 × Aux 100mV/470 kΩ, 1 × Aux 200mV/250kΩ (RCA Jack)

Frequency Response: 70-15,000Hz ±3dB

Signal to Noise Ratio: 60dB

Tone Controls: Bass : -10dB at 100Hz, Treble : -10dB at 10kHz

Outputs: Preamp 200mV/600Ω

Speaker Outputs: 4Ω, 8Ω, 70V & 100V for each zone

Power Supply: AC : 220-240V 50/60Hz DC: 12V (12V Car Battery)

Power Consumption: AC : 250VA DC: 5A

Special features: Built-in MP3 player with remote control for USB, SD, MMC card.

Dimensions: W400 × H130 × D290 mm



TZA-5000 DP

Power Output : 350W + 350W Max., 250W + 250W RMS

Input Channels : Mic/Aux: 6 × Mic 0.6mV/4.7kΩ, 2 × Aux 100mV/470kΩ, Stereo Music Mode: L/R 200mV/100kΩ, Line L/R 1V/50kΩ

Frequency Response: 50-15,000Hz ±3dB

Signal to Noise Ratio: 60dB

Tone Controls: Bass : ±10dB at 100Hz, Treble : ±10dB at 10kHz

Output: Preamp 200mV/600Ω, Line 1V/1kΩ

Speaker Output: 4Ω, 8Ω, 70V & 100V for each zone

Digital Player: MP3 Player with USB, SD and MMC Card Reader

Power Supply: AC: 220-240V 50/60Hz, DC: 24V (2×12V Car Battery)

Power Consumption: AC: 700VA DC: 9A

Special features: Built-in MP3 player with remote control for USB, SD, and MMC card.

Dimensions: W510 × H172 × D385 mm



TZA-4000 DP

Power Output : 300W + 300W Max., 200W + 200W RMS

Input Channels : Mic/Aux: 6 × Mic 0.6mV/4.7kΩ, 2 × Aux 100mV/470kΩ, Stereo Music Mode: L/R 200mV/100kΩ, Line L/R 1V/50kΩ

Frequency Response: 50-15,000Hz ±3dB

Signal to Noise Ratio: 60dB

Tone Controls: Bass : ±10dB at 100Hz, Treble : ±10dB at 10kHz

Output: Preamp 200mV/600Ω, Line 1V/1kΩ

Speaker Output: 4Ω, 8Ω, 70V & 100V for each zone

Digital Player: MP3 Player with USB, SD and MMC Card Reader

Power Supply: AC: 220-240V 50/60Hz DC: 24V (2×12V Car Battery)

Power Consumption: AC: 700VA DC: 9A

Special features: Built-in MP3 player with remote control for USB, SD, MMC card.

Dimensions: W510 × H172 × D385 mm



TZA-2000 DP

Power Output : 130W + 130W Max., 100W + 100W RMS

Input Channels : Mono 6 × Mic 0.6mV/4.7kΩ, 2 × Aux 100mV/470kΩ, Stereo L/R 250mV/47kΩ

Frequency Response: 50-15,000Hz ±3dB

Signal to Noise Ratio: 60dB

Tone Controls: Bass : ±10dB at 100Hz, Treble : ±10dB at 10kHz

Outputs: Preamp 200mV/600Ω, Line 1V/1kΩ

Speaker Outputs: 4Ω, 8Ω, 70V & 100V for each zone

Power Supply: AC: 220-240V 50/60Hz DC: 24V (2×12V Car Battery)

Power Consumption: AC: 420VA DC: 6.5A

Special features: Built-in MP3 player with remote control for USB, SD, MMC card.

Dimensions: W460 × H150 × D340 mm



TZA-1500 DP

Power Output : 100W + 100W Max., 80W + 80W RMS

Input Channels : 6 × Mic 0.6mV/4.7kΩ, 2 × Aux 100mV/470kΩ

Frequency Response: 65-15,000Hz ±3dB

Signal to Noise Ratio: 60dB

Tone Controls: Bass : -10dB at 100Hz, Treble : -10dB at 10kHz

Output: Preamp 200mV/600Ω, Line 1V/1kΩ

Speaker Output: 4Ω, 8Ω, 70V & 100V

Digital Player: MP3 Player with USB, SD and MMC Card Reader

Power Supply: AC: 220-240V 50/60Hz DC: 12V (12V Car Battery)

Power Consumption: AC: 300VA DC: 6A

Special features: Built-in MP3 player with remote control for USB, SD, MMC card.

Dimensions: W460 × H150 × D340 mm



TZA-1200, DP

Power Output : 90W + 90W Max., 60W + 60W RMS

Input Channels : 5 × Mic 0.6mV/4.7kΩ, 1 × Aux 100mV/470 kΩ, 1 × Aux 200mV/250kΩ (RCA Jack)

Frequency Response: 70-15,000Hz ±3dB

Signal to Noise Ratio: 60dB

Tone Controls: Bass : -10dB at 100Hz, Treble : -10dB at 10kHz

Outputs: Preamp 200mV/600Ω

Speaker Outputs: 4Ω, 8Ω, 70V & 100V for each zone

Power Supply: AC : 220-240V 50/60Hz DC: 12V (12V Car Battery)

Power Consumption: AC : 250VA DC: 5A

Special features: Built-in MP3 player with remote control for USB, SD, MMC card.

Dimensions: W400 × H130 × D290 mm

PA SPEAKERS SYSTEMS



PA METAL COLUMN SPEAKERS



SPEAKERS 12"/15"/18" ALL MODELS



UNITS



PROFESSIONAL WIRELESS PA MICROPHONES



PA HORN SPEAKERS



PA AUDIO MIXING CONSOLES AND DJ MIXERS



PA MIC STANDS

