



F&F Filipowski sp. j  
ul. Konstytucyjna 79/81  
95-200 Pabianice POLAND  
tel/fax 48 42 2270971  
e-mail: fif@fif.com.pl

## AS-214

### STAIRCASE TIMERS



www.fif.com.pl

F&F products are covered by an 24 months warranty from date of purchase

#### PURPOSE

Staircase timer AS-214 serves to keep switched-ON lighting of staircase, corridor, or any other object for the set time and to switch-OFF this lighting automatically, upon elapse of this set time.

#### FUNCTIONING

Turned ON staircase timer supports the lighting during set time by potentiometer (from 0,5min. to 10min.). After passage of set time timer will switch OFF the lighting automatically. After switching OFF the lighting there is possibility to switch it ON again.

#### ATTENTION!

AS-214 is not adapted to co-operate with pushbuttons equipped with neon lamp.



#### ASSEMBLY

1. Take OFF the power.
2. Put on the relay on the rail in switchgear box.
3. Connect the relay to circuitry with wiring diagram.
4. By flat screwdriver set to switching threshold.

#### TECHNICAL DATA

supply	24V AC/DC
current load	<16A
switching OFF delay (to set)	0,5+10min
switching ON delay	<1sec
connection	screw terminals 2,5mm <sup>2</sup>
power consumption	0,56W
working temperature	-25+50°C
dimensions	1 module (18mm)
fixing	on the rail TH-35

#### WIRING DIAGRAM



A090625