

EMEA Region

[Download Instructions \(multilingual\)](#)

## Mini Charger

### ENHANCED COMMUNICATION

- Multiple colored LED lights indicate charge status



### VERSATILE

- Charges 1 or 2 AA or AAA NiMH batteries



### SAFETY TIMER

- Ensures charger is not active for extended periods of time



#### Before Using Your Charger:

Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with *Energizer*® NiMH batteries.

### Product Detail:

**Designation:** Mini Charger

**Model:** CH2PC4

**Color:** Black

**Charge Capability:** "AA" (1) or (2)  
"AAA" (1) or (2)

**Note:** Do not charge (1) "AA" and (1) "AAA" at the same time. Please refer to the instructions for orientation diagram.

| Charging Times:<br>(estimated) | Battery | Capacity  | Estimated |
|--------------------------------|---------|-----------|-----------|
|                                | (NiMH)  | (mAh)     | (time)    |
|                                | AA      | 1300-2000 | 7-10 hrs  |
|                                | AA      | 2000-2300 | 10-12 hrs |
|                                | AAA     | 500-800   | 5-8 hrs   |

**Shutoff Mechanism:** Timer (15 hours)

**Charging Current:** "AA" 170-200mA  
"AAA" 80-100mA

**Trickle Charge:** None

**Input Rating:** 100-240VAC, 50/60Hz, 3W

**Typical Weight:** 65 grams

**Dimensions (mm):** 115 x 45 x 70 (L x W x H)

**Safety Features:** Reverse Polarity Protection  
Safety Timer to Prevent Overcharge

#### Important Notice

This datasheet contains information specific to products manufactured at the time of its publication.

Contents herein do not constitute a warranty.