



SQUARE QR-C51

recessed fitting, square, titanium, max. 50W, incl. clip springs

The adjustable low-voltage recessed fitting SQUARE CR-C51 is available in white, chrome, matt-chrome, titanium and silver-grey colour and allows independent adjustment of the desired beam angle. To operate the recessed fitting, a matching transformer with 12V alternating current is required.

TECHNICAL DATA

| (5.3 |
|--------------|
| 10.0 |
| R-C51 |
| |
| |
| V ~50Hz mA/V |
| 7 cm |
| 7 cm |
| 5 cm |
| 123 kg |
| 147 kg |
| 20 |
| |
| ecessed |
| eiling |
| W |
| kel |
| R |





Recommended lamp

| 1001574 | Philips Master LED Spot MR16 , 5W, 2700K, 36°, dimmable |
|---------|---|
| 1001575 | Philips Master LED MR16 5W , 3000K, 36° |

| Notes | | | |
|-------|--|--|--|
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |