




## **KALU TRACK**

spot for 240V 3-phase track, QPAR111, black, max. 75 W, incl. 3-phase adapter

Adjustable spot KALU TRACK with suitable adapter for the 240V 3-phase track system. Conceived as an extension to the popular KALU series, this track spot takes on the shape of the product family. By the incorporated GU10 lamp holder, the spot is suitable to take LED and halogen ES111 lamps. To meet all lighting requirements, we alternatively offer versions with G53 socket and such with incorporated Philips LED modules for the 1- and 3-phase systems.



## **TECHNICAL DATA**

Item no.:	152610		
Socket	GU10		
Lamp	QPAR111		
Number of sockets	1		
Lamps included	0		
Primary nominal voltage	230V ~50Hz mA/V		
Tiltrange	90 °		
Horizontal rotation range	350 °		
Length	18.0 cm		
Diameter	12.0 cm		
Net weight	0.32 kg		
Gross weight	0.43 kg		
IP Code	IP 20		
Safety class	II		
Assembly	Surface		
Assembly details	Ceiling, Track Ceiling, Track Wall, Wall		
Wattage	75 W		
Color	black		
BIG WHITE Page	492		



## Recommended lamp

1001242	LED lamp , GU10 111mm 30° 2700K
1003087	LED lamp , QPAR111, GU10, 4000K, 1100lm, 30°, dimmable
1003094	LED lamp , QPAR111, GU10, 2700K, 40°, dimmable
551882	LED ES111 , lamp, 6.5W, COB LED, 38°, 2700K, not dimmable

Notes			