

La legrand[®]

Belanko[™] S 13A Sockets with USB

Cat. No(s): 6 17X 44/57/58/65/66











6 17X 65

6 17X 66

1. USE

Sockets with USB chargers for recharging portables devices such as smartphones, tablets, powerbanks, etc.

(Supplied with M3.5 screws for BS boxes. Flush mounting or surface mounting.)

2. RANGE

Designation	Cat. No.
2G BS SP switched socket 13A+USB Type A+C	6 17X 44
1G BS unswitched socket 13A + USB A 2.4A	6 17X 57
1G BS SP 13A switched socket +USB A 2.4A	6 17X 58
1G BS 13A unswitched socket + USB Type C	6 17X 65
1G BS 13A switched socket + USB Type C	6 17X 66


Colours

-Front: white/anthracite/ivory

-Rear: grey

- 6 176 XX White
- 6 177 XX Anthracite
- 6 178 XX Ivory

3. DIMENSIONS (mm)



4. CONNECTION


4.1 Terminals


Terminal capacity: 4 X 2.5 mm²

3 X 4 mm² 2 X 6 mm²

Recommended screwdriver size: <4 mm flat blade Recommended stripping length: 12 mm Recommended terminal tightening torque: 0.5Nm

4.2 Circuit diagrams





Technical data sheet:F02982EN/01

Created: 14/09/2019

Belanko[™] S 13A Sockets with USB

5. TECHNICAL CHARACTERISTICS

5.1 Material characteristics

Rocker: Polycarbonate Frame: Polycarbonate Base: PP Self-extinguishing: + 850° C / 30 s for insulating parts holding live parts in place + 650° C / 30 s for other parts made of insulating materials

5.2 Electrical characteristics

BS socket: Voltage: 250V~ Current: 13A Frequency: 50/60 Hz

USB Chargers:

All values listed below are measured at an ambient temperature of + 25° and after 15 minutes of operation.

Туре	1 USB (Type A)		1 USB (Type C)	2 USB (Type A+C)
Nominal input voltage	220	-240V~	100-240V~	220-240V~
Nominal input frequency	50-60 Hz			
Power consumption	12 W		15 W	15 W
Maximum input current	30	300 mA 500 mA		300 mA
Maximum power consumption in standy	0.075 W			
Power average efficiency	79.94%		81.39%	81.39%
Nominal output voltage	5V 			
Maximum output current	2.4A		3.0 A	3.0 A*
No-load consumption and average energy efficienvy: Level VI**				
Protection class	II - Low voltage			

* Note : shared on A and C output

** Note : European Regulation No. 278/2009 of 6 April 2009, Directive 2005/32/EC on eco-design requirements for AC/DC power supplies.

Note : To optimize the charging time of your device, ensure to turn it off during the charging phase.

5.3 Climatic characteristics

Storage temperatures: -20° C to $+70^{\circ}$ C Operating temperatures: -5° C to $+35^{\circ}$ C

5.4 Mechanical characteristics

Impact test: IK04 Protection against solids & liquids: IP20

6. CLEANING

Surface cleaning with a soft, slightly damp cloth. Do not use: acetone, tar remover, trichloroethylene

7. CONFORMITY - APPROVALS

Conform with installation and manufacturing standards. Refer to e-catalogue.