



# **GENIE**

## Genie 23W CDL E27 220-240V 1PF/6

Functional non-covered Energy saving lamp, with money saving high quality light and compact design. This lamp is small enough to fit neatly wherever you need extra bright light at home, enables easy replacement of most incandescent lamp all the way.

#### **Product data**

General Information	
Cap-Base	E27 [ E27]
Nominal Lifetime (Nom)	10000 h
Switching Cycle	10000X
Light Technical	
Color Code	865 [ CCT of 6500K]
Luminous Flux (Nom)	1370 lm
Luminous Flux (Rated) (Nom)	1370 lm
Color Designation	Cool Daylight
Lumen Maintenance 2000 h (Nom)	88 %
Chromaticity Coordinate X (Nom)	313
Chromaticity Coordinate Y (Nom)	337
Correlated Color Temperature (Nom)	6500 K
Luminous Efficacy (rated) (Nom)	60 lm/W
Color Rendering Index (Nom)	80
LLMF At End Of Nominal Lifetime (Nom)	65 %
Operating and Electrical	
Input Frequency	50 or 60 Hz
Power (Rated) (Nom)	23 W
Lamp Current (Nom)	165 mA
Wattage Equivalent	98 W


Starting Time (Nom)	0.3 s			
Warm Up Time To 60% Light (Min)	5 s			
Warm Up Time To 60% Light (Max)	40 s			
Power Factor (Nom)	0.6			
Voltage (Nom)	220-240 V			
Controls and Dimming				
Dimmable	No			
Approval and Application				
Energy Efficiency Label (EEL)	A			
Mercury (Hg) Content (Max)	2 mg			
Mercury (Hg) Content (Nom)	1.5 mg			
Energy Consumption kWh/1000 h	23 kWh			
Product Data				
Full product code	871829114415100			
Order product name	Genie 23W CDL E27 220-240V 1PF/6			
EAN/UPC - Product	8718291144151			
Order code	929689244001			
Numerator - Quantity Per Pack	1			
Numerator - Packs per outer box	6			
Material Nr. (12NC)	929689244001			

Datasheet, 2017, October 19 data subject to change

### Warnings and Safety


- Breaking a lamp is extremely unlikely to have any impact on your health. If a lamp breaks, ventilate the room for 30 minutes and remove the parts, preferably with gloves. Put them in a closed plastic bag and take it to your local waste facilities for recycling. Do not use a vacuum cleaner
- Compact fluorescent lamps have to be treated as special waste, they must be taken to your local waste facilities for recycling. The European Lighting Industry has set up an infrastructure, capable of recycling mercury, other metals, glass etc.

#### **Dimensional drawing**



Product	D (max)	C (max)	F (max)
Genie 23W CDL E27 220-240V 1PF/6	36 mm	157.0 mm	48.5 mm

#### Econ Genie ErP NG 23W/865 E27 220-240V



Econ Genie ErP NG 23W/865 E27 220-240V

Product	D (max)	C (max)	F (max)
Genie 23W CDL E27 220-240V 1PF/6	36 mm	157.0 mm	48.5 mm

