

PIR SENSOR

Product&Family Code:










WHITE BLACK

| Technical Data | |
|------------------------|-----------------------|
| Voltage | AC 220-240V / 50-60Hz |
| Detection Distance | 8 ± 1 m Max. (<24°C) |
| Time-delay | 5 sec ~ 10±2 min. |
| Ambient Light | < 10Lux ~ 2000Lux |
| Average Load | Max 1000W (~220V AC) |
| Protection Class | II |
| IP Rating | 20 |
| Detection Motion Speed | 0,6-1,5 m/s |
| Material | Plastic |
| CE Approved | Yes |

Technical Drawing



Applications

• For use indoors

Features

- A passive infrared sensor (PIR sensor) is an electronic sensor that measures infrared (IR) light radiating from objects in its field of view.
- The wide detection range senses an up, down, left and right field of motion.
- It works by seeing human body heat in motion via infrared rays.

